



INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : H01Q 11/12	A1	(11) International Publication Number: WO 97/20362 (43) International Publication Date: 5 June 1997 (05.06.97)
--	-----------	---

(21) International Application Number: **PCT/US96/19120**(22) International Filing Date: **29 November 1996 (29.11.96)**

(30) Priority Data:

60/007,748	30 November 1995 (30.11.95)	US
60/007,749	30 November 1995 (30.11.95)	US
60/007,742	30 November 1995 (30.11.95)	US
08/654,198	28 May 1996 (28.05.96)	US
08/700,943	21 August 1996 (21.08.96)	US
08/728,227	10 October 1996 (10.10.96)	US

(60) Parent Applications or Grants

(63) Related by Continuation


US	60/007,748 (CIP)
Filed on	30 November 1995 (30.11.95)
US	60/007,742 (CIP)
Filed on	30 November 1995 (30.11.95)
US	60/007,749 (CIP)
Filed on	30 November 1995 (30.11.95)
US	08/654,198 (CIP)
Filed on	28 May 1996 (28.05.96)
US	08/700,943 (CIP)
Filed on	21 August 1996 (21.08.96)
US	08/728,227 (CIP)
Filed on	10 October 1996 (10.10.96)

(71) Applicant (for all designated States except US): **AMSC SUBSIDIARY CORPORATION [US/US]; 10802 Parkridge Boulevard, Reston, VA 22091 (US).**

(72) Inventors; and

(75) Inventors/Applicants (for US only): **GARNER, William, B. [US/US]; 10802 Parkridge Boulevard, Reston, VA 22091 (US). TISDALE, William, R. [US/US]; 10802 Parkridge Boulevard, Reston, VA 22091 (US). THREADGILL, Michael, E. [US/US]; 10802 Parkridge Boulevard, Reston, VA 22091 (US). MODZELESKY, Edward, J. [US/US]; 10802 Parkridge Boulevard, Reston, VA 22091 (US). CHURAN, Gary, G. [US/US]; 10802 Parkridge Boulevard, Reston, VA 22091 (US). BIEGEL, Charles, H. [US/US]; 10802 Parkridge Boulevard, Reston, VA 22091 (US). KITTIVER, Charles [US/US]; 10802 Parkridge Boulevard, Reston, VA 22091 (US).**(74) Agents: **DONNER, Irah, H. et al.; Lowe, Price, Leblanc & Becker, Suite 300, 99 Canal Center Plaza, Alexandria, VA 22314 (US).**(81) Designated States: **AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, CA, CH, CN, CU, CZ, DE, DK, EE, ES, FI, GB, GE, HU, IL, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MD, MG, MK, MN, MW, MX, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, TJ, TM, TR, TT, UA, UG, US, UZ, VN, ARIPO patent (KE, LS, MW, SD, SZ, UG), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, ML, MR, NE, SN, TD, TG).**

Published

With international search report.
With amended claims.(54) Title: **VIRTUAL NETWORK CONFIGURATION AND MANAGEMENT SYSTEM FOR SATELLITE COMMUNICATIONS SYSTEM**

(57) Abstract

In a mobile satellite system, a system for providing satellite communication between multiple users in a virtual network arrangement includes first and second mobile earth terminals (METs) responsively connected to and registering with the mobile satellite system. The first MET selects a virtual network identifier (VN ID) representing a virtual network group including the first and second METs to establish voice communication therewith and transmits the VN ID to a central controller. The central controller receives the VN ID from the first MET, validates the first MET for communication, validates the VN ID, allocates a frequency for the virtual network group, and broadcasts the message to the virtual network group including the second MET informing the virtual network group of the allocated frequency and the voice communication associated therewith. The second MET tunes to the frequency in response to the message broadcast by the central controller.

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AM	Armenia	GB	United Kingdom	MW	Malawi
AT	Austria	GE	Georgia	MX	Mexico
AU	Australia	GN	Guinea	NE	Niger
BB	Barbados	GR	Greece	NL	Netherlands
BE	Belgium	HU	Hungary	NO	Norway
BF	Burkina Faso	IE	Ireland	NZ	New Zealand
BG	Bulgaria	IT	Italy	PL	Poland
BJ	Benin	JP	Japan	PT	Portugal
BR	Brazil	KE	Kenya	RO	Romania
BY	Belarus	KG	Kyrgyzstan	RU	Russian Federation
CA	Canada	KP	Democratic People's Republic of Korea	SD	Sudan
CF	Central African Republic	KR	Republic of Korea	SE	Sweden
CG	Congo	KZ	Kazakhstan	SG	Singapore
CH	Switzerland	LI	Liechtenstein	SI	Slovenia
CI	Côte d'Ivoire	LK	Sri Lanka	SK	Slovakia
CM	Cameroon	LR	Liberia	SN	Senegal
CN	China	LT	Lithuania	SZ	Swaziland
CS	Czechoslovakia	LU	Luxembourg	TD	Chad
CZ	Czech Republic	LV	Latvia	TG	Togo
DE	Germany	MC	Monaco	TJ	Tajikistan
DK	Denmark	MD	Republic of Moldova	TT	Trinidad and Tobago
EE	Estonia	MG	Madagascar	UA	Ukraine
ES	Spain	ML	Mali	UG	Uganda
FI	Finland	MN	Mongolia	US	United States of America
FR	France	MR	Mauritania	UZ	Uzbekistan
GA	Gabon			VN	Viet Nam

VIRTUAL NETWORK CONFIGURATION AND MANAGEMENT
SYSTEM FOR SATELLITE COMMUNICATIONS SYSTEM

Related Applications

This application claims priority from: U.S. provisional application serial number 60/007,742 filed on November 30, 1995 entitled "COMMUNICATIONS GROUND
5 SEGMENT SYSTEMS ARCHITECTURE," U.S. application serial no. 08/565,036, filed November 30, 1995, entitled "FRAUD DETECTION AND USER VALIDATION SYSTEM FOR MOBILE EARTH TERMINAL COMMUNICATION DEVICE," U.S. patent application serial number 08/654,198 filed on May 28,
10 1996 entitled "COMMUNICATION PROTOCOL FOR MOBILE EARTH TERMINAL COMMUNICATION DEVICE USED IN MOBILE SATELLITE COMMUNICATION SYSTEM," U.S. provisional application serial number 60/007,748 filed on November 30, 1995 entitled "NETWORK OPERATIONS CONTROLLER (NOC)," U.S.
15 patent application serial number 08/700,943 filed on August 21, 1996 entitled "NETWORK OPERATIONS CONTROLLER FOR MOBILE EARTH TERMINAL SATELLITE COMMUNICATIONS SYSTEM," U.S. provisional application serial number 60/007,749 filed on November 30, 1995 entitled "GROUP
20 CONTROLLER," and U.S. patent application serial number 08/728,227 filed on October 10, 1996 entitled "IMPROVED NETWORK CONTROL CENTER FOR SATELLITE COMMUNICATION SYSTEM," all of which are hereby incorporated by reference.

Technical Field

The present invention relates generally to a
satellite trunked radio service system for satellite
communication, and more particularly, to a virtual
network configuration and management system for
30 satellite communication utilizing a shared satellite demand period circuit associated with private voice networks.

Background Art

An overview of the satellite network system is illustrated in Figure 1. The satellite network system design provides the capability for METs and FESs to
5 access one or more multiple beam satellites located in geostationary orbit to obtain communications services.

The heart of the satellite network system for each of the networks is the Network Control System (NCS) which monitors and controls each of the networks. The
10 principal function of the NCS is to manage the overall satellite network system, to manage access to the satellite network system, to assign satellite circuits to meet the requirements of mobile customers and to provide network management and network administrative
15 and call accounting functions.

The satellites each transmit and receive signals to and from METs at L-band frequencies and to and from Network Communications Controllers (NCCs) and Feederlink Earth Stations (FESs) at Ku-band
20 frequencies. Communications at L-band frequencies is via a number of satellite beams which together cover the service area. The satellite beams are sufficiently strong to permit voice and data communications using inexpensive mobile terminals and will provide for
25 frequency reuse of the L-band spectrum through inter-beam isolation. A single beam generally covers the service area.

The satellite network system provides the capability for mobile earth terminals to access one or
30 more multiple beam satellites located in geostationary orbit for the purposes of providing mobile communications services. The satellite network system is desired to provide the following general categories of service:

35 Mobile Telephone Service (MTS). This service provides point-to-point circuit switched voice

connections between mobile and public switched telephone network (PSTN) subscriber stations. It is possible for calls to be originated by either the mobile terminal or terrestrial user. Mobile terminal-to-mobile terminal calls are also supported.

Mobile Radio Service (MRS). This service provides point-to-point circuit switched connections between mobile terminal subscriber stations and subscriber stations in a private network (PN) which is not a part of the PSTN. It is possible for calls to be originated from either end. Mobile terminal-to-mobile terminal calls are also supported.

Mobile Telephone Cellular Roaming Service (MTCRS). This service provides Mobile Telephone Service to mobile subscribers who are also equipped with cellular radio telephones. When the mobile terminal is within range of the cellular system, calls are serviced by the cellular system. When the mobile terminal is not in range of the cellular system, the MTCRS is selected to handle the call and appears to the user to be a part of the cellular system. When the mobile terminal is not in range of the cellular system, the MTCRS is selected to handle the call and appears to the user to be a part of the cellular system. It is possible for calls to be originated either from the MET or the PSTN. Mobile terminal-to-mobile terminal calls are also supported.

Mobile Data Service (MDS). This service provides a packet switched connection between a data terminal equipment (DTE) device at a mobile terminal and a data communications equipment (DCE)/DTE device connected to a public switched packet network. Integrated voice/data operation is also supported.

The satellites are designed to transmit signals at L-band frequencies in the frequency band 1530-1559 MHz. They will receive L-band frequencies in the frequency band 1631.5 - 1660.5 MHz. Polarization is right hand

circular in both bands. The satellites will also transmit in the Ku frequency band, 10,750 MHz to 10,950 MHz, and receive Ku-band signals in the frequency band 13,000 to 13,250 MHz.

5 The satellite transponders are designed to translate communications signals accessing the satellite at Ku-band frequencies to an L-band frequency in a given beam and vice versa. The translation will be such that there is a one-to-one relation between
10 frequency spectrum at Ku-band and frequency spectrum in any beam at L-band. The satellite transponders will be capable of supporting L-band communications in any portion of the 29 MHz allocation in any beam.

15 Transponder capacity is also provided for Ku-band uplink to Ku-band down-link for signalling and network management purposes between FESSs and NCCs. The aggregate effective isotropic radiated power (AEIRP) is defined as that satellite e.i.r.p. that would result if
20 the total available communications power of the communications subsystem was applied to the beam that covers that part of the service area. Some of the key performance parameters of the satellite are listed in Figure 2.

25 The satellite network system interfaces to a number of entities which are required to access it for various purposes. Figure 3 is a context diagram of the satellite network system illustrating these entities and their respective interfaces. Three major classes
30 of entities are defined as user of communications services, external organizations requiring coordination, and network management system.

35 The users of satellite network communications services are MET users who access the satellite network system either via terrestrial networks (PSTN, PSDN, or Private Networks) or via METs for the purpose of using the services provided by the system. FES

Owner/Operators are those organizations which own and control FESs that provide a terrestrial interface to the satellite network. When an FES becomes a part of the satellite network, it must meet specified technical performance criteria and interact with and accept real-time control from the NCCs. FES Owner/Operators determine the customized services that are offered and are ultimately responsible for the operation and maintenance of the FES. Customers and service providers interact with the Customer Management Information System within the Network Management System.

The satellite network system interfaces to, and performs transactions with, the external organizations described below:

Satellite Operations Center (SOC): The SOC is not included in the satellite network ground segment design. However, the satellite network system interfaces with the SOC in order to maintain cognizance of the availability of satellite resources (e.g. in the event of satellite health problems, eclipse operations, etc.) and, from time to time, to arrange for any necessary satellite reconfiguration to meet changes in traffic requirements.

NOC: The satellite network system interfaces with the satellites located therein via the NOC for a variety of operational reasons including message delivery and coordination.

Independent NOCs: The satellite network system interfaces with outside organizations which lease resources on satellite network satellites and which are responsible for managing and allocating these resources in a manner suited to their own needs.

Other System NOCs: This external entity represents outside organizations which do not lease resources on

satellite network satellites but with whom operational coordination is required.

The satellite network management system (NMS) is normally located at an administration's headquarters and may comprise three major functional entities; Customer Management Information System (CMIS), Network Engineering, and System Engineering (NE/SE). These entities perform functions necessary for the management and maintenance of the satellite network system which are closely tied to the way the administration intends to do business. The basic functions which are performed by CMIS, Network Engineering, and System Engineering are as follows:

Customer Management Information System: This entity provides customers and service providers with assistance and information including problem resolution, service changes, and billing/usage data. Customers include individual MET owners and fleet managers of larger corporate customers. Service providers are the retailers and maintenance organizations which interact face to face with individual and corporate customers.

Network Engineering: This entity develops plans and performs analysis in support of the system. Network Engineering analyzes the requirements of the network. It reconciles expected traffic loads with the capability and availability of space and ground resources to produce frequency plans for the different beams within the system. In addition, Network Engineering defines contingency plans for failure situations.

System Engineering: This entity engineers the subsystems, equipment and software which is needed to expand capacity to meet increases in traffic demands and to provide new features and services which become marketable to subscribers.

The satellite network system comprises a number of system elements and their interconnecting communications links as illustrated in Figure 4. The system elements are the NOC, the NCC, the FES, the MET, the Remote Monitor Station (RMS), and the System Test Station (STS). The interconnecting communications links are the satellite network Internetwork, terrestrial links, the MET signaling channels, the Interstation signaling channels, and the MET-FES communications channels. The major functions of each of the system elements are as follows:

NOC. The NOC manages and controls the resources of the satellite network system and carries out the administrative functions associated with the management of the total satellite network system. The NOC communicates with the various internal and external entities via a local area network (LAN)/wide area network (WAN) based satellite network Internetwork and dial-up lines.

NCC. The NCC manages the real time allocation of circuits between METs and FESSs for the purposes of supporting communications. The available circuits are held in circuit pools managed by Group Controllers (GCs) within the NCC. The NCC communicates with the NOC via the satellite network Internetwork, with FESSs via Ku-to-Ku band interstation signaling channels or terrestrial links, and with mobile terminals via Ku-to-L band signaling channels.

FES. The FES supports communications links between METs, the PSTN, private networks, and other MTs. Once a channel is established with an MET, call completion and service feature management is accomplished via In-Band signaling over the communication channel. Two types of FESSs have been defined for the satellite network system; Gateway FESSs and Base FESSs. Gateway

FESSs provide MTS, MRS, MTCRS and NR services. Base FESSs are for like services and/or value added services.

MET. The MET provides the mobile user access to the communications channels and services provided by the satellite network system. A range of terminal types has been defined for the satellite network system.

RMS. The RMS monitors L-band RF spectrum and transmission performance in specific L-band beams. An RMS is nominally located in each L-band beam. Each RMS interfaces with the NOC via either a satellite or terrestrial link.

STS. The STS provides an L-band network access capability to support FES commissioning tests and network service diagnostic tests. The STS is collocated with, and interfaced to, the NOC.

Communications channels transport voice, data and facsimile transmissions between METs and FESSs via the satellite. Connectivity for MET-to-MET calls is accomplished by double hopping the communications channels via equipped FESSs. Signaling channels are used to set up and tear down communications circuits, to monitor and control FES and MET operation, and to transport other necessary information between network elements for the operation of satellite network. The system provides Out-of-Band and Interstation signaling channels for establishing calls and transferring information. In-Band signaling is provided on established communications channels for supervisory and feature activation purposes. A detailed description of the satellite network signaling system architecture is provided in L. White, et al., "North American Mobile Satellite System Signaling Architecture," AIAA 14th International Communications Satellite Conference, Washington, DC (March 1992), incorporated herein by reference.

The satellite network Internetwork provides interconnection among the major satellite network ground system elements such as the NOCs, NCCs, and Data Hubs, as well as external entities. Various leased and dial-up lines are used for specific applications within the satellite network system such as backup interstation links between the NCC and FESSs and interconnection of RMSs with the NOC.

The primary function of the NOC is to manage and control the resources of the satellite network system. Figure 5 is a basic block diagram of the NOC and its interface. The NOC computer is shown with network connections, peripheral disks, fault tolerant features, and expansion capabilities to accommodate future growth. The NOC software is represented as two major layers, a functional layer and a support layer. The functional layer represents the application specific portion of the NOC software. The support layer represents software subsystems which provide a general class of services and are used by the subsystems in the functional layer.

The application specific functions performed by the NOC are organized according to five categories: fault management, accounting management, configuration management, performance management, and security management. The general NCC Terminal Equipment (NCCTE) configuration showing constituent equipment includes: processing equipment, communications equipment, mass storage equipment, man-machine interface equipment, and optional secure MET Access Security Key (ASK) storage equipment. The Processing Equipment consists of one or more digital processors that provide overall NCC control, NCS call processing, network access processing and internetwork communications processing.

The Communications Equipment consists of satellite signaling and communications channel units and FES

terrestrial communication link interface units. The Mass Storage Equipment provides NCC network configuration database storage, call record spool buffering an executable program storage. The Man-Machine Interface Equipment provides operator command, display and hard copy facilities, and operator access to the computer operating systems. The MET ASK storage Equipment provides a physically secure facility for protecting and distributing MET Access Security Keys.

The NCCTE comprises three functional subsystems: NCCTE Common Equipment Subsystem, Group Controller Subsystem, and Network Access Subsystem. The NCCTE Common Equipment subsystem comprises an NCC Controller, NCCTE mass storage facilities, and the NCCTE man-machine interface. The NCC Controller consists of processing and database resources which perform functions which are common to multiple Group Controllers. These functions include satellite network Internetwork communications, central control and monitoring of the NCCTE and NCCRE, storage of the network configuration, buffering of FES and Group Controller call accounting data, transfer of transaction information to the Off-line NCC and control and monitoring of FESSs.

The Mass Storage element provides NCC network configuration database storage, call accounting data spool buffering, and NCCTE executable program storage. The Man-machine Interface provides Operator command and display facilities for control and monitoring of NCC operation and includes hard copy facilities for logging events and alarms. A Group Controller (GC) is the physical NCC entity consisting of hardware and software processing resources that provides real time control according to the CG database received from the NOC.

The Group Controller Subsystem may incorporate one to four Group Controllers. Each Group Controller

maintains state machines for every call in progress within the Control Group. It allocates and de-allocates circuits for FES-MET calls within each beam of the system, manages virtual network call processing, MET authentication, and provides certain elements of call accounting. When required, it provides satellite bandwidth resources to the NOC for AMS(R)S resource provisioning. The Group Controller monitors the performance of call processing and satellite circuit pool utilization. It also performs MET management, commissioning and periodic performance verification testing.

The Network Access Subsystem consists of satellite interface channel equipment for Out-of-Band signaling and Interstation Signaling which are used to respond to MET and FES requests for communications services. The Network Access Processor also includes MET communications interfaces that are used to perform MET commission testing. In addition, the subsystem includes terrestrial data link equipment for selected FES Interstation Signaling.

The principal function of the FES is to provide the required circuit switched connections between the satellite radio channels, which provide communications links to the mobile earth terminals, and either the PSTN or PN. FESs will be configured as Gateway Stations (GS) to provide MTS and MTCRS services or Base Stations to provide MRS services (described in detail below). Gateway and Base functions can be combined in a single station.

The FES operates under the real time control of the Network Communications Controller (NCC) to implement the call set-up and take-down procedures of the communications channels to and from the METs. Control of the FES by the NCC is provided via the interstation signaling channels. An FES will support multiple

Control Groups and Virtual Networks. The FES is partitioned into two major functional blocks, the FES RF Equipment (FES-RE) and the FES Terminal Equipment (FES-TE). The principal function of the FES-RE is to provide the radio transmission functions for the FES. In the transmit direction it combines all signals from the communications and interstation signaling channel unit outputs from the FES-TE, and amplifies them and up-convert these to Ku-Band for transmission to the satellite via the antenna. In the receive direction, signals received from the satellite are down-converted from Ku-Band, amplified and distributed to the channel units within the FES-TE. Additional functions include satellite induced Doppler correction, satellite tracking and uplink power control to combat rain fades.

The principal function of the FES-TE is to perform the basic call processing functions for the FES and to connect the METs to the appropriate PSTN or PN port. Under control of the NCC, the FES assigns communications channel units to handle calls initiated by MET or PSTN subscribers. The FES-TE also performs alarm reporting, call detail record recording, and provision of operator interfaces.

For operational convenience, an FES may in some cases be collocated with the NCC. In this event, the NCC RF Equipment will be shared by the two system elements and the interstation signaling may be via a LAN. Connection to and from the PSTN is via standard North American interconnect types as negotiated with the organization providing PSTN interconnection. This will typically be a primary rate digital interconnect. Connection to and from private networks is via standard North American interconnect types as negotiated with the organization requesting satellite network service. This will typically be a primary rate digital interconnect for larger FESSs or an analog interconnect

for FESSs equipped with only a limited number of channels may be employed.

5 It has been discovered that there is a general need for an integrated mobile telephone that can be used to transmit to, and receive from, to communicate in a virtual network arrangement that allows each member of the group to hear what any other user is saying. Each member of the group can also talk when needed. The system behaves like a radio multi-party line where
10 several parties communicate over the same communication channel. Public services and law enforcement agencies are typical users of this service, which is normally provided by either traditional terrestrial radio networks or by the more recent trunked radio systems. These trunked systems, generally in the 800-900 MHz band, provide groups of end users with virtual network systems by assigning frequencies on a demand basis. In this connection, however, it has been discovered that
15 an integrated mobile communication device is needed that provides this ability to communicate in a virtual network of a satellite communications system.

20 It has also been discovered the need for a nationwide and regional point-to-multipoint mobile communication service that is not limited in coverage.

25 Summary of the Invention

It is a feature and advantage of the present invention to provide an integrated mobile telephone that can be used to transmit and receive in a virtual network arrangement that allows each member of the group to hear what any other user is saying.
30

It is another feature and advantage of the present invention to permit each member of the group to talk when needed, and to provide a system that behaves like a radio multi-party line.

It is a further feature and advantage of the present invention to provide an integrated mobile communication device that can communicate in a virtual network of a satellite network.

5 It is another feature and advantage of the present invention to provide an inexpensive virtual network satellite service to the owner of the group.

10 It is another feature and advantage of the present invention to minimize the call set-up time for one shared circuit per virtual network.

15 It is another feature and advantage of the present invention to generally effectively and efficiently effectuate transmissions between mobile communication devices and the satellite network in a virtual network environment by utilizing an efficient communication protocol.

20 It is another feature and advantage of the invention to provide a nationwide and regional point-to-multipoint mobile communication service that is not limited in coverage.

25 The present invention is based, in part, on the desirability of providing point-to-multipoint circuit switched connections between mobile terminal subscriber stations and a central base station in a virtual network. Mobile users are able to listen to two-way conversations and to transmit.

30 To achieve these and other features and advantages of the present invention, a mobile communication system is provided in a mobile satellite system. The mobile satellite system includes a satellite communication switching office having a satellite antenna for receiving/transmitting a satellite message via a satellite from/to a vehicle using a mobile communication system, a satellite interface system, a
35 central controller receiving/transmitting the satellite message from/to the satellite communication switching

office issued from the vehicle via the satellite and the satellite interface system. The mobile communication system includes a user interface system providing a user interface through which a user has access to services supported by the mobile satellite system, and an antenna system providing an interface between the mobile communication system and the mobile satellite system via the satellite interface system, and receiving a first satellite message from the satellite and transmitting a second satellite message to the satellite. The antenna system includes an antenna including one of a directional and an omnidirectional configuration, a diplexer, an amplifier, a low noise amplifier, a beam steering unit when the antenna is of the directional configuration, and at least one of a compass and sensor to determine vehicle orientation. The mobile communication system also includes a transceiver system, operatively connected to the antenna system, including a receiver and a transmitter. The transmitter converts the second satellite message including at least one of voice, data, fax and signaling signals into a modulated signal, and transmits the modulated signal to the antenna system. The transmitter includes an amplifier, a first converter and associated first frequency synthesizer, a modulator, an encoder, multiplexer, scrambler and frame formatter for at least one of voice, fax, and data. The receiver accepts the first satellite message from the antenna system and converts the first satellite message into at least one of voice, data, fax and signaling signals, at least one of the voice, data and fax signals routed to the user interface system. The receiver includes a second converter with an associated second frequency synthesizer, a demodulator, a decoder, demultiplexer, descrambler and frame unformatter for at least one of

voice, fax, and data. The mobile communication system also includes a logic and signaling system, operatively connected to the transceiver, controlling initialization of the mobile communication system, obtaining an assigned outbound signaling channel from which updated system information and commands and messages are received. The logic and signaling system configures the transceiver for reception and transmission of at least one of voice, data, fax and signaling messages, and controls protocols between the mobile communication system and the mobile satellite system, and validating a received signalling messages and generating codes for a signaling message to be transmitted.

In one embodiment of the invention, a system for providing satellite communication between multiple users in a virtual network arrangement includes first and second mobile earth terminals (METs) responsively connected to and registering with the mobile satellite system. The first MET selects a virtual network identifier (VN ID) representing a virtual network group including the first and second METs to establish voice communication therewith and transmits the VN ID to a central controller. The central controller receives the VN ID from the first MET, allocates a frequency for the virtual network group, and broadcasts the message to the virtual network group including the second MET informing the virtual network group of the allocated frequency and the voice communication associated therewith. The second MET tunes to the frequency in response to the message broadcast by the central controller.

In another embodiment of the invention, a method of providing satellite communication between multiple users in a virtual network arrangement includes the steps of first and second mobile earth terminals (METs)

registering with the mobile satellite system, the first MET selecting a virtual network identifier (VN ID) representing a virtual network group including the first and second METs to establish voice communication therewith. The method also includes the steps of the first MET transmitting the VN ID to the central controller, the central controller receiving the VN ID, allocating a frequency for the virtual network group, and broadcasting the message to the virtual network group including the second MET informing the virtual network group of the allocated frequency and the voice communication associated therewith. The method also includes the steps of the second MET tuning to the frequency in response to the message broadcast by the central controller.

In another embodiment of the invention, the method also includes the steps of a third MET included in the virtual network group registering with the mobile satellite system, and the central controller broadcasting the message to the virtual network group including the third MET informing the virtual network group of the allocated frequency and the voice communication associated therewith. The method also includes the steps of the third MET tuning to the frequency in response to the message broadcast by the central controller.

According to the invention, the central controller advantageously controls the virtual network satellite communication including virtual network parameters used by the first and second METs.

The central controller advantageously collects billing information regarding the virtual network satellite communication and transmits the billing information to the mobile satellite system. The mobile satellite system optionally charges a service fee to a customer that has requested the virtual network

arrangement instead of each of the individual users in the virtual network group thereby consolidating the billing transactions and permitting a single customer to monitor communication charges.

5 In another embodiment of the invention, the method includes the steps of the first MET selecting the virtual network identifier (VN ID) representing a virtual network group including the first MET and a non-MET serviced by one of a public switched telephone
10 network and a cellular network to establish voice communication therewith, and the first MET transmitting the VN ID to the central controller. Additionally, the method includes the central controller receiving the VN ID, determining that the virtual network group includes
15 the non-MET, and broadcasting a non-MET message to either the public switched telephone network or the cellular network including the voice communication associated therewith, and either the public switched telephone network or the cellular network receiving the
20 non-MET message from the central controller and transmitting the non-MET message to the non-MET to establish the virtual network arrangement between the MET and the non-MET.

 In another embodiment of the invention, the NOC
25 manages and controls the resources of the satellite network system and carries out the administrative functions associated with the management of the total satellite network system. The NOC communicates with the various internal and external entities via a local
30 area network (LAN)/wide area network (WAN) based satellite network Internetwork and dial-up lines.

 The NOC's network management functions include measuring the usage of resources by customers to enable predictions of what changes to make in the future
35 deployment of resources. Such resources may be network elements and CPUs in the system. Data such as usage

records are collected and analysis of capacity planning is performed based on present characteristics.

Security functions are provided wherein the network is protected against unauthorized use. Security mechanisms built in to the network management include enhanced fraud security coding encryption and user passwords. Configuration management, i.e., how resources are allocated, is another function of the NOC. Fault detection and management are provided for by the NOC. Problems are isolated and reported to operations personnel who can react to the problems.

In another embodiment of the invention, a method of performing a call setup procedure in a mobile satellite system from a call initiated by a mobile communication system (MCS) to a destination served by a public switched telephone network, includes the steps of initiating the call by the MCS, the MCS formatting and transmitting an access request message via a random access channel, and receiving by the central controller the access request message, and transmitting frequency assignments to the MCS and to the SCSO. The method also includes receiving by the MCS the frequency assignment, transmitting a scrambling vector message to the SCSO, and verifying by the SCSO the identity of the MET responsive to the scrambling vector. Upon successful verification, the method includes the steps of switching by the SCSO and the MCS from call setup mode to voice mode, transmitting by the SCSO voices frames to the MCS including a voice activation disable signal to disable a voice activation timer in the MCS for at least 3 super frames, and transmitting a destination number to the PSTN. The method also includes the steps of transmitting by the SCSO an enable signal to the MCS to re-enable the call activation timer in the MCS, and establishing voice communication between the PSTN and the MCS.

In another embodiment of the invention, a method of performing a call setup procedure in a mobile satellite system from a call initiated by a destination served by a public switched telephone network (PSTN) to a mobile communication system (MCS). The method includes the steps of receiving by the SCSO a call from the destination served by the PSTN, transmitting by the SCSO to the central controller a channel request using interstation signaling, determining by the central controller an identity of the MCS responsive to the destination number, and transmitting a call announcement via a random access channel. The method also includes the steps of acknowledging by the MCS the call announcement via the random access channel to the central controller, transmitting frequency assignments to the MCS via the random access channel and to the SCSO via an interstation signaling channel, and transmitting an access security check field used to verify the MCS's identity. The method also includes the steps of receiving by the MCS the frequency assignment, and transmitting a scrambling vector message to the SCSO, verifying by the SCSO the identity of the MET responsive to the scrambling vector, and upon successful verification, transmitting by the SCSO a ring command to the MCS. The method also includes the steps of receiving by the MCS of the ring command, generating a ringing signal to a MET user, and transmitting a ring command acknowledgement to the SCSO. The method also includes the steps of receiving by the SCSO the ring command acknowledgement from the MCS, and once the call setup is complete, transmitting by the MCS voice frames to the SCSO including a voice activation disable signal to disable a voice activation timer in the MCS for at least 3 super frames. The method further includes the steps of upon detection of the MCS switching to a voice frame mode, switching by

the SCSO to the voice mode, and transmitting a voice activation enable signal to the MCS to re-enable the call activation timer in the MCS, and establishing voice communication between the PSTN and the MCS.

5 These, together with other objects and advantages which will be subsequently apparent, reside in the details of construction and operation as more fully herein described and claimed, with reference being had to the accompanying drawings forming a part hereof
10 wherein like numerals refer to like elements throughout.

Brief Description of the Drawings

Fig. 1 is a diagram illustrating an overview of the satellite network system;

15 Fig. 2 is a diagram illustrating key performance parameters of the satellite used in the satellite network system;

Fig. 3 is a diagram of the satellite network system illustrating components and respective interfaces;

20 Fig. 4 is a diagram of a satellite network system illustrating a number of system elements and their interconnecting communications links;

Fig. 5 is a basic block diagram of the NOC and its interfaces;

25 Fig. 6 is a basic block diagram of the physical architecture of the mobile earth terminal;

Fig. 7 is a basic block diagram of the functions of the mobile earth terminal;

30 Figs. 8a-8b are diagrams of the improved call setup protocol used to establish a MET originated voice call;

Figs. 9a-9b are diagrams of the improved protocol used for PSTN originated calls;

Fig. 10 is a block diagram of an improved NOC functional architecture;

Figs. 11A - 11C are diagrams of the NOC architecture in more detail;

Fig. 12 is a basic block diagram of the basic components of the NCC showing the included GC;

5 Fig. 13 is a diagram of the NCC logical architecture;

Fig. 14 is a basic block diagram of a circuit switched NAP;

10 Fig. 15 is a block diagram showing the channel unit (CU) architecture;

Fig. 16 shows the GC subsystems which manage a call in progress;

Fig. 17 is an illustration of the basic role of the GWS within the Mobile Satellite Services (MSS) system;

15 Fig. 18 depicts the basic call processing interaction between the GWS and other elements within and outside of the overall MSS system;

Fig. 19 is a functional illustration of the Gateway Switch;

20 Fig. 20 is an illustration of a virtual network associated with a group of FESSs and METs;

Fig. 21 illustrates the basic concept and elements involved in establishment of communications and control in the virtual network system;

25 Fig. 22 illustrates an example of a virtual network service subscribing organization with several communication virtual networks;

Fig. 23 is a decision tree of the order of application of the virtual network rules; and

30 Fig. 24 is a more detailed illustration of the NCC terminal equipment.

Best Mode for Carrying Out the Invention

The present invention provides point-to-multipoint circuit switched connections between mobile terminal
35 subscriber stations and a central base station. Mobile

users are able to listen to two-way conversations and to transmit.

The MET includes all of the communication and control functions necessary to support communications from a vehicle or fixed remote site using the resources of the satellite network system. Figs. 6 and 7 are basic block diagrams of the physical architecture and functions of the mobile earth terminal. The basic functional diagram of Fig. 7 is implemented by baseband processing and RF electronics of Fig. 6. A standard voice coder/decoder receives coded messages from the baseband processing and RF electronic system and decodes the message received from the satellite antenna unit for delivery to the interface unit that includes standard user interfaces. Baseband processing and RF electronics receive satellite communications responsive with low noise amplifier (LNA) and output signals for transmission using the diplexer of the antenna unit. Baseband processing and RF electronics also outputs signals for use with beam steering antennas as will be discussed below. Advantageously, the mobile earth terminal is functional with antennas that are either steerable or nonsteerable.

The functional subsystems comprising the MET are shown in Fig. 7 and include the user interface, transceiver, antenna, logic and signaling, power supply subsystems, and Position Determination subsystem. The baseline MET will have a low gain directional antenna in the antenna subsystem. The satellite network system supports communications with METs using omnidirectional and higher gain directional antennas.

The user interface subsystem provides the user interfaces through which the user has access to the services supported by the satellite network system. Depending on the service(s) the MET will be equipped with one or more of the devices or ports. The

transceiver subsystem consists of a receiver and a transmitter. The transmitter accepts voice, data, fax and signaling signals and converts them to a modulated RF signal. The transmit RF signal is routed to the antenna subsystem. The transmitter typically consists of the high power amplifier (HPA), the upconverter with its associated frequency synthesizer, the modulators and the modules for voice, Fax, or data encoding, multiplexing, scrambling, FEC encoding, interleaving and frame formatting.

The receiver accepts modulated RF signals from the antenna subsystem and converts them into voice, data, fax or signaling signals as appropriate. The voice, data and fax signals are routed to the user interface subsystem. The receiver typically consists of the downconverter with its associated frequency synthesizer, the demodulator, and the modules for frame de-formatting, de-interleaving, FEC decoding, descrambling, demultiplexing and voice, Fax, or data decoding. The transceiver communicates over one channel in each direction at any one time. Thus, the transceiver subsystem will typically consist of only one receiver and one transmitter. However, the MET may also incorporate a pilot receiver for antennas and frequency tracking purposes, or a complete receiver dedicated to the continuous reception of the signaling channel from the Group Controller.

The antenna subsystem provides the MET interface to the satellite network and is responsible for receiving the RF signal from the satellite and transmitting the RF signal generated by the MET towards the satellite. The subsystem typically includes an antenna which may be either directional or omnidirectional, a diplexer, a low noise amplifier (LNA), an optional beam steering unit (BSU) if a directional antenna is used, a device such as a compass or an inertial sensor for the

determination of the orientation of the vehicle, and an antenna for the position determination receiver.

The logic and signaling subsystem acts as the central controller for the MET. Its basic functions are to initialize the MET by performing a self test at power up and control, based on a resident system table, the acquisition of one of the METs assigned outbound signaling channels from which updated system information and commands and messages from the GC are derived. The logic and signaling subsystem sets up and configures the transceiver for the reception and transmission of voice, data, fax or signaling messages as appropriate. The logic and signaling subsystem also handles the protocols between the MET and the FES and between the MET the GC via signaling messages, and checks the validity of the received signaling messages (Cyclic Redundance Check (CRC)) and generates the CRC codes for the signaling message transmitted by the MET.

The logic and signaling subsystem also interprets the commands received from the local user via the user interface subsystem (e.g. on/off hook, dialled numbers, etc.) and take the appropriate actions needed, and generates, or commands the generation, of control signals, messages and indications to the user through the user interface subsystem. The logic signaling system also controls the beam steering unit (if any) in the antenna subsystem, and monitors and tests all the other subsystems. In case of fault detection, it informs the user about the failure and take the appropriate measures needed to prevent harmful interference to the satellite network or other systems.

The power supply subsystem provides power to all other subsystems. The external voltage source to which this subsystem interfaces depends on the type of vehicle on which the MET is mounted (e.g. 12/24 Volts DC for land vehicles).

A standard receiver such as a GPS or a Loran-C receiver is also provided for the determination of the position of the vehicle. This information is used by the logic and signaling subsystem for beam steering (if
5 used) or for applications such as position reporting. The position determination system is implemented externally to the MET and interfaced through a dedicated data port in the user interface subsystem.

The function of the Remote Monitor System is to
10 continuously monitor the activity on each GC-S channel and to monitor the activity within the downlink L-band spectrum in the beam in which it is located. An RMS will be located in every beam carrying satellite network traffic. An RMS may be a stand alone station
15 or collocated with the NCC or an FES. The RMS is controlled by the NOC and communicates via leased lines or the interstation signaling channels if collocated with an FES. The RMS detects anomalous conditions such as loss of signal, loss of frame sync, excessive BER,
20 etc. on the GC-S channels and generates alarm reports which are transmitted to the NOC via the leased line interface. In addition, it monitors BER on any channel and power and frequency in any band as instructed by the NOC.

The primary functions of the System Test Stations (STS) is to provide commission testing capability for every channel unit in a FES and to provide readiness testing for the Off-Line NCC. The STS is collocated
25 with and controlled by the NOC and will comprise one or more specifically instrumented METs. The STS provides
30 a PSTN dial-up port for making terrestrial connections to FESs to perform MET to terrestrial end-to-end testing. The STS also provides a LAN interconnection to the NOC to provide access to operator consoles and
35 peripheral equipment.

The MSS signaling system provides the communications capability between network elements required to set up and release communications circuits, provide additional enhanced services, and support certain network management functions. The network elements discussed above include group controllers (GCs), feederlink earth stations (FESs), and mobile earth terminals (METs). The seven different channel types are:

GC-S	Outbound TDM signaling channel from the GC to the METs.
MET-ST	Inbound TDMA signaling channel from the MET to the GC.
MET-SR	Inbound random access signaling channel from the MET to the GC.
FES-C	Outbound communications and inband signaling channel from a FES to a MET.
MET-C	Inbound communications and inband signaling channel from a MET to a FES.
GC-I	Interstation signaling channel from the GC to an FES.
FES-I	Interstation signaling channel from an FES to the GC.

The basic element of communication for signaling and control for the MSS signaling system is the Signaling Unit (SU). The SU consists of 96 bits organized in 12 octets of 8 bits each. The first 80 bits comprise the message, and the last 16 a parity check, computed using the CCITT CRC-16 algorithm. For transmission, the SU is convolutionally encoded at

either rate $3/4$ or $1/2$, adding an additional 32 or 96 bits respectively.

The various fields are as follows:

- 5 * Message type: A 7 bit code which identifies the meaning of the SU; in this case a request for access to the MSS system for call placement.
- 10 * MET-GC Signaling Protocol (MGSP) Header: A 8 bit field comprised of several sub-fields giving particular information related to the protocol: message type (command, response, message), message reference identification, and the number of times the message has been retransmitted.
- 15 * RTIN: Reverse Terminal Identification Number - the MET's Electronic Serial Number, by which it identifies itself in transmissions on the MET-SR channel.
- 20 * Digits 1-10: The first 10 digits of the addressed telephone number in the PSTN or private network, in hexadecimal. If the 10th digit is set to "C", an address of greater than 10 digits is indicated.
- * CRC: The 16-bit error detection code (Cyclic Redundancy Code).

25 The frame formats used in the GC-S, MET-SR and MET-ST channels are closely related, and are based on a common 360 millisecond superframe established on the GC-S channel. All timing relationships in the MSS system signaling scheme are determined from the GC-S frame structure. The GC-S is operated in the QPSK mode at an aggregate rate of 6750 b/s. The stream is

30 divided into superframes of 360 ms, comprising three 120 ms frames. Each frame is in turn comprised of a 24-bit unique word (UW), six SUs, eight flush bits and 10 unused bits, for a total of 810 bits and 120 ms. The first frame of a superframe is identified by

35 inversion of the UW.

Mobile terminals throughout the area covered by any beam receive GC-S channels with a total uncertainty of approximately 32 ms, primarily due to their geographical locations. The received superframe boundary establishes the four 90 ms "slots" in the MET-SR random access channels, which operate in the BPSK mode at 3375 b/s. The actual random access burst is comprised of a 24-bit preamble, a 32-bit UW, a 128-bit SU (96 bits rate 3/4 coded), and eight flush bits, for a total of 192 bits in 56.9 ms. This allows a 33.1 ms guard time between bursts. Mobile Terminals select a MET-SR channel and slot at random from among the permitted choices.

The MET-ST TDMA channels, which also operate in the BPSK mode at 3375 b/s, are comprised of bursts which are equal in length to the GC-S frame, and which are also timed on the received frame boundary. The TDMA burst is made up of a 24-bit preamble, a 32-bit UW, a 192-bit SU (96 bits rate 1/2 coded), and eight flush bits. The total length of the TDMA burst is 256 bits in 75.9 ms, which allows a guard time of 44.1 ms. Mobile Terminals always respond to commands received on the GC-S on a MET-ST channel which corresponds in number to the position of the command SU in the TDM frame. For example, the MET will respond to a command in SU slot 2 on MET-ST channel 2, and so forth. The response is always transmitted in the second frame time after receipt of the command, so that there is a minimum of 120 ms in which the MET can prepare its response.

The initial phase of establishing a call is handled by out-of-band signaling on the GC-S, MET-SR and MET-ST channels. This phase culminates in assignment of a pair of communication channels to the MET and FES. When these elements receive and tune to the communication channels, further signaling and control

functions are accomplished using inband signaling. The communication channels, FES-C and MET-C, use a variety of related TDM formats which are determined by the intended use of the link, i.e., voice, data, or facsimile and one of three possible primary modes: call setup (entirely signaling), communication (no signaling), or in-band signaling (an occasional subframe of 128 bits is used for signaling/control).

The same 96-bit SU described above is used to accomplish in-band signaling. The outbound TDM, inbound TDMA, and inbound random access channels provide signaling between the GC and each of the METS in the associated control group. All communications on these channels will be passed in the form of 96 bit (12 octet) messages known as signaling units. Each signaling unit will begin with a 1-octet messages type field and end with a two-octet cyclic redundancy check. The MET to GC Signaling Protocol (MGSP) serves as the layer two protocol for these channels.

Communications from the group controller (GC) to the mobile terminals is provided by the Outbound TDM or GC-S channel. The primary function of this channel is to carry frequency assignments from the GC to individual METs. In addition, the Outbound TDM channel carries network status information which is received by all METs in a particular beam and control group. The outbound TDM channel operates at a rate of 6750 bits/s with rate 3/4 FEC. QPSK modulation and nominally 6.5 kHz channel spacing (other spacings are under investigation) is employed. These parameters are identical to those of the communications channel and were chosen to reduce MET complexity.

Inbound TDMA (MET-ST) channels are used by the MET to respond to actions initiated by the GC, such as responding to the call announcement issued by the GC to check a MET's availability to receive a PSTN

originated or MET to MET call. The Inbound Random Access (MET-SR) channels are used by METs to request frequency assignments and for other MET initiated actions. The inbound random access and TDMA channels
5 each operate at a rate of 2400 bits/s with rate 3/4 FEC. DPS modulation and nominally 7.5 kHz channel spacing is employed. This modulation scheme has been selected because of its robust performance in the presence of frequency offset and timing errors. It
10 also exhibits superior performance relative to conventional BPSK in the presence of band-limiting and hard-limiting.

Each control group has associated with it a number of L-band beams over which it operates. In each of
15 these L-band beams a control group has associated with it a distinct set of outbound TDM, inbound TDMA, and inbound random access channels. The number of signaling channels of each type in each set is determined based on the level of signaling traffic
20 flowing between the GC and the METs in that control group in that L-band beam. As signaling traffic levels change, new signaling channels of each type are allocated to or deallocated from a particular set of channels. The frequencies used for outbound TDM,
25 inbound TDMA, and inbound random access channels are included in the status information carrier in the bulletin board signaling units transmitted on the outbound TDM channel.

Each MET is assigned to one of the outbound TDM
30 channels in the control group and beam to which it belongs. Each control group supports up to 16 outbound TDM channels in each beam. Each outbound TDM channel has associated with it up to 6 inbound TDMA channels. An inbound TDMA channel will only carry messages that
35 are responses to messages received on the outbound TDM channel with which it is associated inbound random

access channels will not associated with a particular outbound TDM channel. A MET chooses a inbound random access channel at random from among those associated with its control group and beam each time a message is to be transmitted. Each control group can support up to 64 inbound random access channels in each beam. Up to 64 of these channels may be used system wide to meet the signaling requirements of a fully loaded system supporting 5000 circuits.

Inband signaling channels (FES-C and MET-C) are provided between the FES and the MET. These channels are used to provide signaling for call setup and call release, and also provide the capability to pass other signaling information while a call is in progress. The FES-C and MET-C channels are operated in two separate modes in "call setup mode" only signaling messages are carried by the channel. In voice mode voice frames are carried by the channel, but the capability to inject signaling messages by occasionally dropping voice subframes exists. Frames containing inband signaling messages employ a unique word different from that used for frames containing only voice subframes.

Interstation signaling channels (GC-I and FES-I) are used to pass signaling information between the GC and each of the FESs. These channels operate at a rate of 9.6 to 64 kbit/s and are implemented using either the available 5 MHz Ku-band satellite capacity or terrestrial links. The LAP-F protocol will be employed on those links to ensure reliable transfer of variable length signaling and network management messages.

When a MET is idle (powered on and ready to receive a call) it will continuously receive an Outbound TDM channel in order to receive call announcements associated with incoming calls and obtain status information from bulletin board signaling units. Each MET will be capable of transmitting signaling

information to the GC on any of the inbound random access channels or on any of the inbound TDMA channels associated with the outbound TDM channel that it is receiving. During a call a MET will receive and transmit all signaling information via the In-Band signaling channels. No signaling information will be sent to a MET via the outbound TDM channel during a call. Any signaling messages from the GC to the MET will be sent to the MET via the FES through the GC-I and FES-C channels.

Each group controller supports at least one outbound TDM channel in each of its associated L-band beams. Each outbound TDM signaling channel is continuously transmitted and carries frequency assignments and networks status information from the GC to the METs. The outbound TDM channels are also used to poll idle METs to see if they can accept incoming calls. As this channel is the only way to signal information to a MET not engaged in communications, it must be as robust as possible under harsh fading and shadowing conditions.

Another key element in the MSS system is the need for the METs to be as inexpensive as possible. Towards this end, the outbound TDM channel will have the same rate and modulation as the communications channels. This will maximize the commonality of the receive chain of the MET for communications and signaling. Note that as the demodulation process is much more complex than the modulation process, the inbound random access and inbound TDMA channels do not really require this level of commonality with the communications channel.

The number of outbound TDM channels assigned to each set of signaling channels is determined by the traffic supported by the group controller in that L-band beam. Assignment of METs to outbound TDM channels is made based on a special identifier assigned to each

MET as commissioning. This identifier is called the GC-S Selector Identifier code (GSI). The MET selects the outbound TDM channel to be used by dividing the GSI by the total number of outbound TDM channels available in the given beam. The number of TDM channels available is given in the BB of each TDM channel. The remainder of the four bit binary division process will form the number of the channel to be used. Each MET will receive only the outbound TDM channel assigned to it. This method allows METs in the same logical grouping to be assigned to the same outbound TDM channel as is needed for the Virtual Network Service provided by the MSS System. It also allows the load on the outbound TDM channels to be redistributed quickly if a channel fails or a new channel is added.

The 120 ms frame length was chosen because it would support 6 messages per frame and correspond to the slot size requirement (>120 ms) of the inbound TDMA channel. This allows a direct correspondence between outbound TDM frames and inbound TDMA slots for the purposes of TDMA synchronization and scheduling responses to outbound messages. Eight flush bits are included at the end of each frame to allow the decoder to reset to a known state at the beginning of each frame. This allows more rapid reacquisition following channel fade events. The modulation scheme and transmission rate for this channel will be the same as for the transmission channel, namely QPSK modulation at a transmission rate of 6750 bps. Signaling units within each frame will be coded with a rate $3/4$ constraint length $K=7$ convolutional code.

The outbound TDM superframe has a duration of 360 ms and is made up of three outbound TDM frames. The superframe duration is the basic time interval over which message repetitions are done. Repetitions are used to increase the reliability of outbound TDM

signaling units. Messages can be repeated in consecutive superframes. Studies by AUSSAT have shown that L-band fade events typically have durations ranging between 10 ms and 100 ms (2). Because the 120 ms frame would not provide adequate separation between message repetitions, the 360 ms superframe is used to reduce the chance of losing two copies of a message during the same L-band fade event. This repetition method is similar to that used in the AUSSAT system. Different numbers of repetitions may be used for different message types to provide different levels of reliability. The number of repetitions used for a particular message type will be a part of the signaling protocols and can be varied by the system operator. In addition to message repetitions, interleaving will be used to protect against burst errors. The interleaving is provided over a TDM frame and provides improved performance in the presence of short burst errors.

The bulletin board is a set of signaling unit (SUs) that are periodically transmitted by the MCC on all outbound TDM channels. The bulletin board contains global information such as current network status, signaling channel frequencies and inbound random access channel congestion control parameters. Every MET processes the information in the bulletin board METs, on startup, and acquires the entire bulletin board before attempting to use the MSS system. At least one bulletin board SU is transmitted in every outbound TDM frame. Bulletin board SUs are also sent as "filler" SUs, i.e., sent when there are no other SUs pending on the outbound TDM channels. Bulletin board SUs do not occupy any fixed position in the outbound TDM frame.

Bulletin board SUs are grouped into pages of related SUs. Each Bulletin Board page has an update number associated with it, which will be sent with each SU of that page. This number will be incremented by

the NCC whenever the information in that page is updated. METs are required to build a local data structure that contains the contents of the bulletin board. Whenever a change in update number is detected
5 for any page, the MET will update the entire data structure for that page with the contents of the bulletin board SUs that follow.

The inbound TDMA channel is used by the METs to transmit responses to call announcement messages and
10 for responses to other messages received on the outboard TDM channel. Each of the inbound TDMA channels is assigned to a particular outbound TDM channel. The number of inbound TDMA channel assigned to a particular outbound TDM channel depends on the
15 traffic supported by that outbound TDM channel and is selectable by the network operator. The TDMA channel is divided into slots of 120 ms duration. Inbound messages consist of 96 bits before coding and 128 bits after rate 3/4 convolutional coding. The resulting
20 burst will occupy 80 ms of the slot, allowing 40 ms of guard time.

This guard time arises due to the uncertainty in round trip transmission time between the satellite and a mobile terminal. Mobile terminals derive their
25 inbound frame timing (for both the TDMA and random access channels) from the outbound TDM frames. Inbound TDMA slots have the same duration as an outbound TDM frame. At a MET each TDMA slot boundary occurs at an outbound TDM frame boundary. If MET A is nearer to the
30 satellite than MET B, MET A will receive the outbound TDM channel Δt sooner than MET B, where Δt corresponds to the difference in propagation times to the satellite for the two terminals. As a result, if both METs synchronize their transmit timing to their reception of
35 the outbound TDM channel, MET B's responses to messages will take $2\Delta t$ longer to reach the satellite than MET

A's responses. As additional guard time of 1 symbol time also must be included to account for the $\pm 1/2$ symbol synchronization uncertainty in the MET. This results in a total guard time requirement of $2\Delta t + 1$ symbol time.

5 TDMA scheduling is done using a fixed relationship between outbound TDM channel time slots and inbound TDMA channels and slots. The response to a message received in the nth slot of the outbound TDM frame is transmitted on the nth TDMA channel assigned to that
10 outbound TDM channel. The frequencies of the assigned inbound TDMA channels are contained in one of the bulletin board signaling units periodically transmitted in the outbound TDM channel. The response to an
15 outbound message is transmitted in the TDMA time slot that begins 120 ms after the end of the TDM frame in which the outbound message was received. This should provide adequate time for message processing in the MET.

20 The inbound random access channel is used by the METs to transmit call requests to the GC. It is also used to carry other inbound messages for MET originated actions. The number of inbound random access channels assigned to a particular control group in a particular
25 L-band beam depends on the traffic supported by that control group in that beam and is selectable by the network operator. To provide reasonable call setup times and call loss probabilities these channels are typically be operated at a throughput of approximately
30 25% or less. As the random access channel is operating at a relatively low efficiency, one of the prime goals in its design is that it be bandwidth efficient.

The frequencies used for the random access channels are transmitted in the bulletin board signal units.
35 For each transmission, METs choose at random among the inbound signaling channels assigned to their control

group. After transmitting a message, the MET waits a given amount of time for a response. If no response is received within this amount of time, the MET retransmits in a slot selected at random over some given number of slots. This procedure is repeated until either a response is received or a maximum number of transmissions is reached. The bursts on the random access channel are identical to those on the TDMA channel (i.e., modulation, coding, preamble, etc.).

The MET-GC Signaling Protocol (MGSP) procedures send signaling units between GCs and METs via the GC-S, MET-ST and MET-SR channels. This protocol encapsulates functions such as channel selection, channel access, slot timing, error recovery and congestion control. Higher layer functions, such as call processing, use the protocol for communicating among themselves between the METs and GCs.

A transaction consists of a command message that is sent from an originating application to a destination application, to which the destination application replies with a response message. Each command and response consists of a signaling unit. The MGSP performs functions such as channel selection, error recovery using retransmission, and repetition of SUs to improve channel reliability. The MGSP at a MET also implements congestion control procedures for the MET-SR channels. Only one outstanding transaction exists between a MET and a GC in a given direction. However, two simultaneous transactions, one in each direction, are supported between a GC and a MET. MGSP also provides a only-way message service, that does not require a response from the receiver.

The improved call setup protocol used to establish a MET originated voice call is shown in Figs. 8a-8b. When a MET user initiates a call, the MET formats and transmits an access request message via a random access

channel. This message includes the call type and the destination phone number. The group controller chooses an FES to handle the call and sends frequency assignments to the MET via the TDM channel and to the FES via the interstation signaling channel. The FES frequency assignment also includes the call type, the destination phone number to allow the FES to complete the call, and an access security check field used to verify the METs identity. The access security check field is generated by the group controller using the MET frequency assignment and the MET key which is known only to the MET and the group controller.

After the MET receives the frequency assignment, it transmits a scrambling vector message to the FES. This message contains the initial vector to be preloaded into the FES scrambler at the beginning of each voice channel frame. Letting the MET randomly pick this vector provides some degree of privacy on the Ku to L-band link. The scrambling vector message also contains an access security check field generated by the MET using its frequency assignment and its key. The FES compares this field with that received from the group controller to verify the identity of the MET. When the FES receives the scrambling vector, the FES will check the validity of the METs identity. If the check fails, the FES will initiate a call release.

After receiving the scrambling vector message and successful authentication of the MET (see U.S. application serial no. 08/565,036, filed November 30, 1995, entitled FRAUD DETECTION AND USER VALIDATION SYSTEM FOR MOBILE EARTH TERMINAL COMMUNICATION DEVICE, "incorporated herein by reference), the FES and the MET switch from call setup mode to voice frame mode and the FES completes the call to the terrestrial network user. The FES transmits voices frames to the MET to effectuate voice communication. We have discovered

that the coder/decoder which is used in the MET imposes certain constraints described below that require the signalling architecture to be adapted thereto.

Specifically, it has been determined that the voice
5 coder/decoder performs the following functions that impact on the signalling architecture in the context of our mobile satellite system. The voice coder/decoder receives coded messages from the baseband processing and RF electronic system and decodes the message
10 received from the satellite antenna unit for delivery to the interface unit that includes standard user interfaces. The voice coder/decoder processes speech to produce 6400 bps output. The inherent speech coding rate is 4150 bps, to which 2250 bps of error correction and detection is added. The coder/decoder encodes
15 160+/-4 samples of speech and converts it to 128 bits. The encoding function is called approximately every 20 ms to produce the 6400 bps bit stream. The coder/decoder decodes 128 bits of speech and produces
20 160 +/- 4 samples of speech. The encoder/decoder also performs voice activity detection.

In accordance with the coder/decoder functions and operations, the coder/decoder includes a voice activation timer or synchronizer that is used to
25 determine and insure that a caller is present during the call setup process. The encoder determines that the voice communication is active when valid data appears at the output within two sub-frames or approximately 40 ms. The encoder determines that the
30 voice communication is not active when no voice activity occurs for 3 sub-frames or approximately 60 ms. The decoder sets the voice activity to active when voice activity is detected, and to inactive when no voice activity is detected.

35 In accordance with the above constraints of the coder/decoder, it has been determined that the protocol

used by the mobile satellite system must be adapted for use with the standard encoder/decoder used for voice communication. In particular, it has been determined that the inherent delays in the mobile satellite system are incompatible with the voice activation timer used in the coder/decoder. In this connection, it has been determined that it is beneficial to eliminate usage of the voice activity timer during the voice mode prior to completion of call setup. Once call setup has been completed, the voice activity timer can then be re-enabled and used for its intended purpose, i.e., to determine whether the call is still active or whether the call has terminated, thereby freeing up satellite resources more expediently.

Accordingly, once voice frames have been transmitted from the FES to the MET in the voice mode, and once the FES transmits the destination number to the PSTN, the FES also transmits a voice activation disable signal to the MET to disable the voice activation timer in the MET. The voice activation timer is then disabled for at least 3 super frames. After the FES has completed call setup with the GC, the FES transmits a signal to re-enable the call activation timer in the MET.

The PSTN provides ringing tones to the FES indicating that the call is being placed to the destination, and the FES in turn transmits the ringing tones to the MET. When the destination telephone answers the MET originated call, an off-hook signal is transmitted from the PSTN to the FES, and the FES in turn transmits same to the MET indicating that the call has been answered by a user connected to the PSTN. Voice communication between the MET and the PSTN destination via the FES is then commenced until either party terminates the MET originated call.

The improved protocol used for PSTN originated calls is shown in Figs. 9a-9b. When a call from a terrestrial network user arrives at an FES, the FES makes a channel request using interstation signaling. This request contains the phone number received from the terrestrial network user. The group controller determines the MET identity based on the phone number and transmits a call announcement via the TDM channel. The MET acknowledges this announcement via the TDMA channel. This exchange allows the group controller to verify that the MET is available before assigning bandwidth to the call. Frequency assignments are then made and the scrambling vector is transmitted by the MET once the MET tunes to the assigned frequency.

Upon successful reception of the scrambling vector, the FES checks the validity of the MET's identity. If the check fails, the FES initiates a call release procedure. If not, the FES transmits the ring command to the MET. Upon reception of the ring command by the MET from the FES, the MET generates a ringing signal to the MET user and transmits a ring command acknowledgement. The ring command acknowledgement is repeated by the MET until the MET is taken off-hook by the MET user or until the call is cleared. Upon receipt of the acknowledgement from the MET and once the call setup is complete, the MET begins transmitting voice frames to the FES and also transmits a voice activation disable signal as described in connection with MET originated call setup procedure. Once the MET is taken offhook the MET switches to the voice frame mode. Upon detection of the MET switching to the voice frame mode, the FES stops transmitting null signal units, switches to the voice mode, transmits a voice activation enable signal and commences voice communication between the MET and PSTN.

MET to MET calls are set up using a double hop connection through an FES. These calls are set up by the group controller and the FES as a MET to PSTN call setup concatenated with a PSTN to MET call setup. As a result the METs require no additional call processing for MET to MET calls. That is, the procedures at the MET for receiving a MET-MET call are the same as procedures for reception of PSTN-MET calls, and the procedures at the MET for originating a MET-MET call are the same as procedures for origination of MET-PSTN calls.

Advantageously, the MET combines three different features for the delivery and transmission of voice and data. These three features include: the ability to initiate and transmit a data call, the ability to initiate and transmit a facsimile digital call, and the ability to roam between satellite and terrestrial based wireless communication systems. The following documents, representing applicable transmission protocols, are hereby incorporated by reference: EIA/IS-41B Cellular Radio Telecommunications Inter-System Operations; EIA/TIA-553-1989 "Cellular System Mobile Station - Land Station Compatibility Standard"; EIA/TIA-557; EIA/IS-54B.

The improved NOC functional architecture is shown in the block diagram of Fig. 10. The NOC collects information pertaining to the utilization of resources and distributes information to appropriate destinations such as CMIS and NE/SE. The NOC is involved in network security to prevent unauthorized use. The blocks shown in the figure broadly represent the functions that the NOC performs or oversees. The network management is a framework for the NOC basic functions. The configuration management implements and allocates resources in cooperation with plans formulated with NE/SE. The operator interface serves a fault

management function. Problems in the system are isolated and reported to give operations personnel the ability to see when problems occur and react to them. The operator interface is a man-machine interface (MMI) to present alarms and events to the operators. Information as to system configuration is also made available. Call records management serves as an accounting functionality. This function accepts MET registration records and other information sent by external entities for storage in appropriate NOC database tables. Usage data sent by the individual GCs and FESs are assembled into Call Records. Data management serves as a data base repository for transmission and receipt of information gathered by the other components of the network operations center.

Figs. 11A - 11C set forth the NOC architecture in more detail, the elements shown corresponding to the blocks of Fig. 10. As shown in Fig. 11A, the network management block contains Polycenter Processes modules that serve alarm manager, exporter, historian and operator control functions. The historian records performance of the network over time, collecting at suitable intervals statistics regarding resource utilization, calls in progress. The management information repository (MIR) server interfaces with the exporter. Network update requests are received from the router. When transactions come in from NE/SE or CMIS, they need to be distributed to different parts of the system. Updates are distributed to the MIR server so that it can update the internal data base. After all elements of the system are set up, network updates are communicated back to the router for network implementation. Exporter transmits collections of information, including performance traffic data, to the database in the data management block. The NE/SE system is described in detail in U.S. application

serial number 08/601,749 filed on February 15, 1995, incorporated herein by reference. The CMIS system is described in detail in U.S. application serial number 08/598,556 filed on February 8, 1996, incorporated
5 herein by reference.

The alarm rule manager sets thresholds for adverse conditions and executes set up procedures for the event management block. For example, if customer service center sends out a commissioning request and the
10 commissioning fails, an alarm is generated and the NOC sends a message to CMIS describing the failure and the cause of the failure. The watchdog looks for events, such as the system disk becoming fully utilized and other fault conditions, and sends an alarm to NMS to
15 operator screen. The performance data collector samples resource utilization, collects statistics and provides feedback. NOC process control is involved with custom processes such as NOC startup and shutdown.

Configuration updates are received by the
20 configuration management block, shown in Fig. 11A. A routing table is used to distribute messages to the appropriate components of the NOC.

The data management block, illustrated in Fig. 11B, includes servers to interface with the NOC main data
25 base (DB). The RTR router receives RTR requests from either satellite resource manager or configuration management. The NOC configuration DB server decides from polling NOC components whether the request for update is to be accepted. If so, the NOC data base
30 (DB) is updated and confirmation is sent to other components to update local data bases. The request is basically distributed to all other components to vote on the appropriateness of the requested change. For each transaction there is a specific set of data bases
35 that are to be updated. DC Comm exports information from the database to NE/SE and CMIS. As read

transactions do not need to go through this voting to update process, accessing for reading is easily available to any of the system components. Performance data, collected in the network management collector, previously described, is periodically exported directly to the data management DB, as no updating of other module databases is needed. Such data is not related to the overall configuration.

The call records management block is shown in Fig. 11C. The functionality of this component accounts for customer usage to enable billing preparation by the configuration management information system (CMIS). Call detail records (CDRs) relating nonsatellite usage are received from the gateway switch (GWS) and call performance records (CPRs), or call usage records (CURs), relating satellite usage are received from the group controller (GC). These records are logged into files at the GWS and CUR/NRPR servers to be forwarded to CMIS and saved as backup in the data base. The call trace router sends RTR requests for call tracing and trapping to and from the GC. Call tracing requests are sent to the trace operator, shown in the operator interface block of Fig. 11C. Call trace information is received by the call trace router from the trace operator.

The operator interface includes the session manager. After logging in to the session manager, each of the functions represented by the other blocks within the operator interface block is available. When the system is started or restarted, the encryption/decryption code is established. The MT ASK (Access Security Key) block, essentially a separate data base, contains specific keys specific to each telephone and is checked in real time for each call. The mobile telephone (MT) key is set up when the new MT is added to the system. MT ASK is also used for

storing CMIS and GC encryption keys used for encrypting request transactions. The operator message (Op. Msg.) block is an interface for E-mail. Resource allocation MMI permits the NOC operator to modify the system for day to day operations, such as taking resources off line or on line. The DB access permits the operator to read the data base DB. Bulletin Board records containing transmit and receive frequency information about the METs are available to the operator from the Site Manager location.

The event management block, involved with fault management, is shown in Fig. 11B. All messages are received in the event logger, logged to a file, sent to a printer and displayed at the NOC MMI. Where necessary, files are forwarded to external organizations such as CMIS or NE/SE. CGS (communications ground segment) event data are sent to the CGS event sink. The COTS (Commercial off the shelf) software sink receives other events, such as VMS events. The watchdog event sink receives events from the watchdog block in the network management block, described above. The operator communication (OPCOM) generator converts VMS events into a common format.

Fig. 12 illustrates the Network Communications Center (NCC) and the elements contained therein. The Group Controller (GC) resides in the Network Communications Center (NCC) system element within the CGS and provides call control and satellite resource management for:

- Circuit-switched voice, FAX, and data calls;
- Integrated Voice and Data MT (IVDM) voice calls;
- Satellite trunked radio calls.

The GC controls setup, monitoring, and cleardown of calls between MTs, IVDMs, VN MTs, and terrestrial users. It also provides AMS(R)S Provisioning, Control

Group Reconfiguration, MT and FES PVT and Commissioning support, and Performance and Status Monitoring.

The primary function of the GC is the management of customer Control Groups. Control Groups identify groups of MTs/IVDMs which have access to CGS, the satellite and network resources that have been allocated to them for sending/receiving calls, and the service permissions and calling restrictions that apply to each MT/IVDM. Control Groups also contain Virtual Networks (VNs) discussed below, which define the routing options that apply to each MT or IVDM in the Control Group and Circuit Pools, which control the allocation of use of satellite circuits for circuit-switched calls.

Fig. 13 illustrates the NCC logical architecture. The Group Controller consists of five top level components which perform the following functions:

1. Call Management

This component performs:

- Call setup/monitoring for:
 - a. MT-to-MT, MT-to-PSTN/PN, PSTN/PN-to-MT calls
 - b. MT initiated VN Calls
 - c. Dispatch initiated VN, Private Mode, Broadcast, and Priority 1 calls.
- MT Management, including:
 - MT Logon, GC-S Change, MT Shutdown, and MT Parameter Update, Visitor Registration;
- Preemption of calls for AMS(R)S provisioning of satellite bandwidth and power.
- MT Commissioning and PVT.

2. Resource Management

This component performs resource management and reconfiguration, including:

- allocation/deallocation of satellite resources during call setup/cleardown

- incremental/complete reconfiguration of local Control Group databases
- address screening
- MT authorization
- 5 - call routing
- Virtual Network configuration

3. Configuration Management

This component performs executive control for:

- Control Group configurations;
- 10 - AMS(R)S requests

4. MT ASK Management

This component performs:

- secure MT ASK database management
- real-time check field generated for call
- 15 processing
- ASK generation after completing commissioning/PVTs for Enhanced Fraud

5. Utilities

20 This component is the common utility set for the GC including:

- MGSP
- Call Record Management
- Performance and Traffic Statistics generation
- Congestion Control
- 25 - Memory Management
- X.25 interface.

30 The NCC provides real time call processing for users of the CGS by assigning resources on a per call basis. The NCC operates under the administrative control of and is monitored by the NOC. The NCC manages access of users of the space resources allocated to the NCC by the NOC. The NCC provides system monitoring and testing functions to support FES and MT commissioning and periodic performance

35 verification testing. A single NCC provides these

functions for an entire network carrying the full traffic load. In the event that the NOC is not available, the NCC contains a backup operator interface capable of monitoring and controlling the ongoing provision of services to customers and which is capable of providing emergency AMS(R)S provisioning.

Logically, the NCC is divided into two functional groupings, namely RFE and processing/management functions. Physically, the NCC is similarly divided into RFE and terminal equipment which performs the processing and management functions. The NCC terminal equipment is composed of an integrated set of hardware that is shared with the NOC and FES elements. From the NCC perspective, the hardware is composed of three sets of equipment which include the Circuit Switched Management Processor (CSMP), Network Access Processors (NAPs), and Channel Units (CUs). The NAP functions for the NCC consist of Network Access Processors for Signaling (NAP-S), Network Access Processors for Communications and Testing (NAP-C(Test)), and Bridges Modems for Interstation Signaling Channel Units. Both the NAP-S and NAP-C(Test) have channel units associated with them. The NAPs, Bridges and Channel Units together form the NAP-CU HWCI. There are two styles of NAPs, namely, the Circuit Switched NAP and the Data NAP. The Circuit Switched NAP performs the out-of-band signaling (NAP-S) functions or communications (NAP-C) functions.

A block diagram of the circuit switched NAP is shown in Fig. 14. The NAP is PC-based and contains a processor card, and SDLC card forming the interface with up to 24 channel units, an ethernet card providing the interface to ethernet B in the CSMP, and a distribution card. The distribution card provides a DS-1 interface between the gateway or base switch in the FES and the communications channel units, and a

frame clock distribution function between the RF equipment and the out-of-band signaling channel units. NAPs are used in pairs for redundancy with an on-line and an off-line NAP or NAPs A & B. Each NAP monitors the condition of the other and takes over processing when a failure is detected or by operator (NOC or backup NCC) command via the system common software CSCI Site Manager function. The NAP-S and NAP-C connect to a channel unit of the same type which forms the interface to the RFE for signaling and communications. The CUs are hardware identical and take on their operational personality (S or C) with a software download when they are initialized.

A block diagram of the CU is shown in Fig. 15. The CUs are composed of two major sections: the Baseband Signal Processor Unit (BSPU) and the Channel Signal Processing Unit (CSPU). The CU interfaces to the NAP are shown on the left and the interfaces to the RFE are shown on the right. The sub-element processor types are noted in the diagram.

The BSPU is composed of three major functions: the SDLC Controller (Z80235), Monitor & Control (80186EC) and the voice/modulated data processing (twin TMS320C31). The SDLC Controller provides the interface between the main and redundant NAPs. The Monitor & Control function provides the central control and status focus. This processor also supports the software downloads to a given CUs set of processor sub-elements. The pair of TMS320C31 processors provide the functional processing for echo cancellation, rate adapting and detection, mu-law linear decompression, CODEC, voice, voice modulated data, FAX.

The CSPU is composed of a DSP, I/Q channel A/Ds & D/As, L-Band transmit synthesizer and L-Band receive synthesizer. The major functions performed by the DSP include data framing, encoding/decoding, interleaving,

scrambling/descrambling. The DSP operates on digital data from the receive synthesizer A/Ds and supplies digital data to the D/As for transmission via the transmit synthesizer. As noted earlier, there are up to 24 CUs controlled by a single NAP pair (i.e., main/redundant).

The NCC element is composed of a GC CSCI hosted on the CSMP, a NAP CSCI hosted on the NAP processor and the CU CSCI hosted on the set of CU processors as shown in Fig. 15. The NCC element also requires some portions of the SCS CSCI which is hosted on the CSMP. Both the NAP CSCI and the CU CSCI require a communications version and a signaling version of these SCS CSCIs. Both versions execute on the same physical H/W configuration type. The functions of the NCC element are implemented by a set of software processes as follows:

<u>CSCI</u>	<u>Process</u>	<u>Major Function</u>
GC CSCI	Call	Call Processing
	Config	GC Database Configuration Management
	Monitor	Call record/statistics manager
	ASK Config	ASK Configuration Database manager
	Check Field	Check Field Generation
	GC Router	GC message router
	GC Router Config	GC router DB Configuration Manager
	Config Requester	Configuration access by call processing
	ASK Requester	ASK database access SCS CSCI
	VAX, NAP message	Distribute NAP oriented messages

		VAX, VAX message	Distribute VAX to VAX messages
		Process Control	Monitors VAX processes
5		Site Manager (NR)	Non-real time network management
		Site Manager (R)	Real time network management
	NAP CSCI	BB-PDU	Bulletin board processing
10		NAP-PM	Collect/report performance data
		NAP-I/O	Process I/O in and out of NAP
	CU CSCI	CU-CM	Perform MT PVT & commissioning tests
15		CU-SM	Perform signaling channel functions
		CU-LIB	Common CU support functions

20 The SCS CSCI is primarily responsible for network management functions. Software and hardware objects are managed and status and events reported to the NOC.

25 The NAP CSCI performs both call processing and network management functions. Interaction with the GC is established for receiving the GC-S signaling units for transmission via the SCU to the MTs. The NAP also returns to the GC the SUs received from MTs via the MT-SR and MT-ST channels.

The GC CSCI includes the following databases:

MT Database

- 30 - MT Basic Data Table
- MT VN Memberships Table
- MINData Table
- MT Restrictions Table
- DN Data Table
- 35 - MT VN Memberships Table
- MT Class Table

Virtual Network Database

- VN Data Table
- Routing Lists Table
- VN NPA Table

5 Circuit Pool Database

- Circuit Pool Table
- Freq. Segment Table
- Frequency Table
- CP Beam Table
- 10 - CP Queue Table
- Power Table
- Beam Table

FES Status Tables

- FES Table
- 15 - CUP Table

Call Process Event TimersControl Group Operational Parameters TableHash Tables

- MT Database Hash Tables (RTIN, MIN and DN)
- 20 - Virtual Network DB Hash Table
- Routing List DB Hash Tables
- Circuit Pool DB Hash Table
- Net DB Hash Table
- FES Status DB Hash Table

25 Virtual Network Counters TableTDM Change Requests Table

- Circuit Pool Status Counters Table
- Circuit Pool Counters Table
- Circuit Pool Queue Table
- 30 - Spacecraft Power Table
- MTs-on-Beam Table
- MTs-commissioned Table

- MT-SR Message Retries Table
- MT-SR Congestion Events Table
- GC-S Message Retries Table
- IS Signaling Channel Stats Table

5 Call Record/Activity Tables

- Call ID Activity Table
- RTIN Activity Table
- MTS Call Record
- MT Management Call Records

10 In the preferred system configuration, the Group Controller resides on one VAX ft 810 and executes in multiple concurrent asynchronous VMS processes which timeshare the CPU. The functionality of each GC process is as herein described.

15 The GC is made up of the VMS processes listed below. There are two Process Groups: the GC Controller (GCC) group, and Control Group Management (CGM) group. The GCC and CGM Process Groups are described below.

20	<u>Process Name</u>	<u>Priority</u>	<u>Process Group</u>
	Configuration Process	Non-real-time	Control Group Mgmt
	Call Process	Real-time	Control Group Mgmt
25	Monitor Process	Near real-time	Control Group Mgmt
	Check Field Generator Process	Real-time	GC Controller
30	ASK Configuration Manager Process	Non-real-time	GC Controller
	Router Process	Real-time	GC Controller
35	Router Configuration	Non-real-time	GC Controller

Highest priority is given to the real-time processes for call handling. Second priority is given to near-real-time processes, which support call handling by forwarding call records and supplying call traffic and performance data to the NOC. Third priority is given to the non-real-time processes which support ASK and Control Group reconfiguration at the GC.

The GC processes are event-driven; between events, a process waits for input on a queue. To reduce system load, waits are non-CPU-intensive. The highest priority processes are driven by call events; the lowest priority processes are driven by NOC requests, Call Process requests, and internal timers set to configurable monitoring intervals. In addition to input from its queue, a process may use memory tables or disk files, as shown on the Process Diagrams, for data required to process an event.

The GC architecture accommodates a move to multiple processors. The GC is divided into GC Controller (GCC) processes, and Control Group Manager (CGM) processes. In a distributed environment, there would be one GC Controller, consisting of the GC Router and both ASK Manager processes, supporting one to 16 Control Group Managers. CGMs function independently and can be distributed on multiple processors. A CGM can manage 1 to 16 Control Groups, so there can be one CGM for all Control Groups (the current configuration) or up to 16 distributed CGMs (one CGYM for each Control Group). All processes for a CGM must be co-resident. The GCC can share a processor with one or more CGMs, or can reside on a separate processor. The ASK Manager is stand-alone, and can be hosted on a separate processor in any GC configuration.

GC Subsystems illustrated in Fig. 16 comprise the component subsystems in the Group Controller and

indicate where call processing and network management interfaces occur.

Configuration Process

5 The Configuration (Config) Process has multiple
configuration control tasks. The Config Process
controls the GC processing of Control Group
reconfigurations. It receives database transactions
from the NOC via the DEC COTS product Reliable
Transaction Router (RTR), prepares the update, loads
10 the new data into memory, and coordinates with the Call
Process to complete the update. The processing and
synchronization of the Config and Call processes during
a configuration change is designed to minimize
interference with active calls. ASK reconfigurations
15 are handled by the ASK Configuration Manager.

 The Config Process performs dual RTR roles. It
performs as a server in NOC-initiated updates (#1,
above) and a requester (client role) in GC-initiated
database updates. As an RTR requester, the GC
20 initiates RTR transactions to distribute changes that
originated in the GC Call Process. One example of a GC
initiated update is the change of a MT state following
commissioning; another is the GC's initiation of a
bulletin board update for congestion control.

25 Config receives AMS(R)S circuit requests, sends
circuit blocking commands to the Call Process, and
returns the requested circuits to the NOC when they
become available.

 The Config Process has one RTR queue for
30 reconfiguration messages from the NOC, including
AMS(R)S requests. It also has a VMS mailbox for the
CGS Software Backplane Process Control interface, and a
mailbox for internal timer notification.

Call Process

The Call Process is the heart of the real-time GC processing. It incorporates the Finite State Machines (FSMs) for Call Processing, MT Management, AMS(R)S Provisioning, and PVT/Commissioning. It also contains resource database access routines, error handlers, timers and utility functions that support the FSMs.

The input queues are prioritized as indicated on the GC CGM Inter-process Communications Diagram.

Incoming messages from each queue are processed in order. When an FSM message/event is processed, the Call Process maps the message or event to its state data, performs the state transition processing, and establishes the next state. Errors occurring in a state transition are handled by error routines associated with the current state in the FSM. State data is maintained in the Active Call Record Table, which allows shared read-access for use by support functions in the Monitor process

The Call Process has one input queue established via the CGS Backplane for signaling units, and Access security Check Fields (generated by the ASK Manager). It also has VMS mailboxes for the CGS Software Backplane Process Control interface, internal time notification, internal messages (such as Circuits Available), AMS(R)S requests, and control group reconfiguration requests from the Configuration Process.

Monitor Process

The Monitor Process provides the following Call Process support functions:

1. Forward Call Records to the NOC
2. Buffer Call Records on disk
3. Save the MT Access Event History on disk
4. Generate call traffic statistics

5. Respond to Call Search Requests
6. Respond to Call Record Leftover Requests

Items 1-3 above are performed when a Call record is terminated. The monitor process receives the Call
5 Record from the Call Process, in a Call Termination message. This process forwards the final Call Record data to the NOC, increments counters for call statistics, stores the Call Record on disk for backup in case the NOC goes down, and stores the MT Access
10 Event History on disk. the MT Access Event History buffers that last ten accesses by MT by storing the time stamp of the end of the call, termination reason, and access type (such as MT Management, Call, NR, etc.).

15 Statistics (Item 4) are generated by the Statistics Manager and polled by the Site Manager (DECMcc Agent) at configurable time intervals. These data are derived from the Call Process (via the terminated Call Records), and stored in shared memory tables for the
20 Site Manager (DECMcc Agent).

Call Search requests (Item 5) are sent by the NOC to request the current Call Record (if one exists) of a specific MT, and its Access Event History. The Monitor has read-access to the Active Call Record Table
25 maintained by the Call Process for retrieving the call ID and call record, if it exists, for a MT.

Call Record Leftover requests (Item 6) are sent by the NOC when they are back online after some period of down-time. The request contains the ID of the last
30 Call Record received by the NOC. The Monitor Process retrieves later records which it buffered on disk while the NOC was down.

The Monitor process has one input queue, established via the CGS Backplane, to receive Call
35 Record Requests and Call Search Requests requests from

the NOC. It has a VMS mailbox to receive terminated call records from the Call Process, a mailbox for the CGS Software Backplane Process Control interface, and a mailbox for internal timer notification.

5 GC Router Process

 This process routes Call Process messages which do not have a Control Group ID. The GC Message Router Process has one input queue established via the CGS Backplane to receive incoming SUs for internal routing.
10 It also has a VMS mailbox for the CGS Software Backplane Process Control interface, and a mailbox to receive reconfiguration messages from the GC Router Configuration Process.

GC Router Configuration Process

15 This process is an RTR server process to accept reconfiguration transactions from the NOC. This server is only notified of updates when the change affects the Control Group ID of a MT/MIN, IVDM. It cooperates with the router process in the same manner that the Config
20 Process cooperates with the Call Process to complete a transaction.

Router

 This Process has an RTR input queue. It also has a VMS mailbox for the CGS Software Backplane Process
25 Control interface.

ASK Configuration Manager Process

 The ASK Configuration Manager Process configures the ASK database, based on NOC inputs. The ASK Config Process has one RTR input queue. It also has a VMS
30 mailbox for the CGS Software Backplane Process Control interface.

Check Field Generator Process

The Check Field Generator generates MT Check Fields in response to Call Process requests. It also receives ASK reconfigurations from the ASK Config Process, which it stores in the memory-resident ASK database. This process has one input queue established via the CGS Backplane to receive check field requests from the Call Manager. This interface is via the Message Layer because the ASK Manager may not be co-resident with the Call Process it serves. It also has a VMS mailbox for the CGS Software Backplane Process Control interface, and a mailbox to receive configuration messages from the ASK Config Process.

GC Queues Inter-Process Communications SequenceExample: MT-PSTN Call

1. When a MT Access Request is received on the real-time CALL event queue, the CALL process sets up the call record, establishes a MT Activity Table entry for the call and determines whether the dialed digits in the Access Request SU are complete.

2. If additional digits are required, the CALL process sends out a request to the MT (see following Note 1 and the following referenced notes) and sets a timer for the expected response.

3. When the additional digits are received, the CALL process cancels the Additional Digits Request timer.

4. The CALL process validates the MT, performs address screening, service permission checks, and routing. If all checks succeed, it allocates circuits and updates the OFFLINE GC CALL UPDATES process.

5. The CALL process requests the Access Security Check Field from the CHECK FIELD process. It sets a timer for the expected response. When the Check Field

is received, the CALL process cancels the timer for the request.

6. The CALL process sends out Channel Assignments to the MT and FES. It sets a timer and waits for the Setup Complete message.

7. When the Setup Complete is received from the SLSS, the CALL process cancels the Setup timer, updates the OFFLINE GC CALL UPDATES process, and sets a timer for the Call Status Monitoring interval.

8. When the Call Status Monitoring timer expires, the timer in the CALL Process notifies the Call Manager which sends out a Call Status Request and sets a timer for the response. When the Call Status Reply is received, the CALL process resets the monitoring interval timer.

9. When the Channel Release is received, the CALL process cancels the Monitor timer and closes out the call by releasing resources, clearing the activity table, and sending a call termination event to the MONITOR process.

10. The MONITOR process closes out the call record, updates the OFFLINE GC CALL UP-DATES process, performs any Statistics generation required, sends the call record to the NOC, and Buffers the call record to disk.

Note 1: All messages to/from the MT are sent via the NAP-S.

Note 2: If the response has not been received before the timer expired, the timer in the CALL process would have notified the Call Manager, which would have performed appropriate error handling.

Note 3: The CALL process can process other calls while it awaits for a response from another process on any given call.

GC Queued Inter-Process Communications Example
Incremental Reconfiguration

5 1. When a distributed database transaction from the NOC is received on the GC's RTR queue, the CONFIG process reads the transaction and prepares an update to the Local GC Configuration database. When the preparation and validation are complete, the CONFIG process waits for a vote request from the NOC. The CALL process cannot access the new data until the distributed transaction is complete.

10 2. When the CONFIG receives a vote request via RTR, it returns the GC vote. The GC will return VOTE/COMMIT if its local database validation and update preparation were successful, or VOTE/ABORT if an error occurred while processing the update. After casting the GC vote, the CONFIG process waits for a return code from RTR, indicating the final status of the transaction. Final status is determined by RTR from the votes cast by all participants.

20 3. If the final status of the transaction is COMMIT, then CONFIG sends a message to CALL informing it of the reconfiguration. CALL updates its links to the reconfigured data and acknowledges the completion of the update. CALL can now access the data.

25 4. When the update is complete, the CONFIG process sends a Reconfiguration Event to the NOC via the DECMCC AGENT process.

30 Both the Online and Offline GC's participate in a Control Group reconfiguration since the Offline GC serves as another RTR partner in each distributed Control Group transaction. The processing is the same cases.

NCC On/Off Line Switchover Process

35 As noted earlier, the fully expanded CGS system includes a second NCC or alternate NCC. This separate

physical copy of the NCC maintains near real-time communication with the active on-line NOC and the active on-line NCC via the MSS Internetwork using the TCP/IP protocol. The MSS Internetwork communication path allows the alternate NCC to be geographically separated from the on-line NOC and the on-line NCC. The near real time communication allows the off-line NCC to maintain a "hot" standby status such that it could become the active on-line NCC with a minimum amount of elapsed time and "lost processing" once the switch between NCCs is initiated.

In order to maintain an up-to-date status at the off-line NCC, the applicable database updates at the on-line NOC will be issued as RTR transactions to maintain lock-step database concurrence across the two NCCs. The categories of message sent to the off-line NCC include:

- MT Customer Configuration
- Virtual Network and Routing Configurations
- FES Configuration
- Channel Unit Pool Configuration
- Satellite Resource Configuration
- Control Group Operation Parameters
- Bulletin Board Data

To maintain lock step with ongoing real time call processing, the off-line NCC receives call processing information from the on-line NCC on a call-by-call basis. The major categories of information moving from the off-line NCC to the on-line include the following:

- Call records with frequencies allocated to a call setup
- Call records for a call after setup is complete
- Call record for a call after the frequencies have been released.

The off-line NCC uses this information to maintain call records and frequency allocations dynamically such

that the off-line NCC can immediately assume control of the in-process active call suite and is completely aware of the current in-use frequencies to continue with new call setups and "old" call releases.

5 The on-line to off-line NCC switch over may occur as scheduled activity (e.g., periodic maintenance, major NCC H/W or S/W configuration upgrade, etc.) or as a result of a failure of the current on-line NCC.

 The scheduled switch over process is the following:

- 10 - The on-line NOC or local NCC operator alerts the on-line NCC to initiate processing phase out and suspend active communication with its associated CGS internal element.
- 15 - The on-line NCC alerts the off-line NCC that all processing has been suspended and all elements associated with the NCC are waiting for a communication restart.
- 20 - The off-line NCC commands the on-line NCC to go to passive standby under its own local operator control. At this point the previous off-line NCC is now the new active on-line NCC.
- The new on-line NCC begins a communication restart sequence with its associated CGS elements.

25 This completes the scheduled switch over from an active on-line NCC to the off-line NCC.

 The fail over process is initiated by the on-line NOC. The process flow is the following:

- 30 - The on-line NOC commands the on-line NCC to go to passive standby under local operator control. This is an insurance command to attempt to eliminate the failed NCC from active participation in CGS processing.
- 35 - The on-line NOC commands the off-line NCC to go active.

- The on-line NOC commands all NCC associated elements to suspend communication with the old on-line NCC and wait for an NCC communications restart command.
- 5 - The on-line NOC commands the new on-line NCC to begin a communications restart with all of its associated elements.
- The new on-line NCC begins a communications restart sequence with all of its associated
10 elements.

This completes the fail over sequence. If the original active on-line NCC is not capable of fulfilling its role in the fail over sequence, the switch over will be accomplished via NOC operator to NCC operator
15 communication to suspend the operations of the original on-line NCC and then via NOC MMI to command the on-line NOC MMI to command the on-line NOC to pick up the remainder of the failover sequence.

The Gateway Switch (GWS) is the communications hub
20 for Feederlink Earth Stations (FESS) to provide call processing services to MT users and handles cellular Intersystem Handoff (IHO), Automatic Roaming (AR) and Call Delivery (CD).

The GWS provides the following interfaces:

- 25 • Public Switched Telephone Network (PSTN)
- Private Network (PN)
- Cellular Terrestrial Network (CTN)
- Network Operations Center (NOC)
- Station Logic and Signaling Subsystem (SLSS)
- 30 • Network Applications Processor (NAP)

The GWS acts as a gateway between the users of the satellite system and the Public Switched Telephone Network (PSTN), Private Networks (PN), and Cellular Terrestrial Network (CTN). Within the FES, the GWS
35 connects through Communication Channel Units (CCU) and

the satellite system for bearer channel connections to Mobile Terminals.

5 The GWS also connects through a Station Logic and Signaling Subsystem (SLSS) for a control path to and from the Network Control Center (NCC). The GWS views the MSS call processing resources as cell site(s). The cell site emulation performed by the GC, SLSS, NAPs, and CUs allows the satellite system to be configured into the DMS-MTX as an analog cell site.

10 With respect to the MSS, the basic functions of the GWS are:

- manage the PSTN/PN interfaces
- manage CTN interfaces
- receive and process connections and feature control
15 messages from the SLSS processes
- provide various operational and administrative support for the switching operations of the network
- provide various Call Service Features to the MT
user

20 The basic role of the GWS within the Mobile Satellite Services (MSS) system is shown in FIG. 17. As indicated, the GWS acts as a gateway between the users of the satellite system and the Public Switched Telephone Network (PSTN) or Private Networks (PNs).
25 Within the FES, the GWS connects through Communication Channel Units (CCUs) and the satellite system for bearer channel connections to Mobile Earth Terminals (METs). The GWS also connects through a Station Logic and Signaling Subsystem (SLSS) for a control path to
30 and from the Network Control Center (NCC).

In contrast to the hardware interfaces shown in FIG. 17, FIG. 18 depicts the basic call processing interaction between the GWS and other elements within and outside of the overall MSS system. As indicated,
35 standard Call Processing (CP) software within the GWS

interfaces with a Call Control Element (CCE) process in the SLSS and with a Group Controller (GC) processing the NCC.

With respect to the MSS, the basic functions of CP in the GWS are: to manage the PSTN/PN interfaces, receive and process connection and feature control messages from the CCE and GC processes, and provide various operational and administrative support for the switching operations of the network.

In addition to the internal interfaces of the MSS, the GWS CP also interfaces CP control elements of the PSTN or the PNs. In the most basic applications the various CP processes only exchange addressing (dialing) information for call routing. In more advanced applications involving SS7 or ISDN networks, the CPs exchange information for advanced features such as calling number identification, terminal characteristics, calling restrictions, subaddressing, routing requirements, etc.

Note that since the GWS is expected to be a variant of a public network switching system, there will be functional similarities between the GWS CP and the PSTN CP and PN CP.

The GWS physically resides as part of the Feederlink Earth Station (FES) (see FIG. 17). The FES is the network interface point for the interconnection of satellite resources and terrestrial resources. The GWS can best be envisioned as an end-office, connecting to Mobile Earth Terminals (METs) in lieu of subscriber telephones. The METs are special purpose terminal sets communicating, via satellite, to the Feederlink Earth Station.

The METs, in conjunction with other functionality of the FES, can provide circuit switched voice, data and facsimile services. A highly compressed method of voice encoding is used over the satellite channel.

Likewise, the satellite channel can accommodate 4800 bps digital data which is converted to voiceband modulated data (in a Hayes compatible modem format) in the CCU which interfaces to the GWS. In addition, the system supports facsimile traffic complying with the Group 3 standard. Notwithstanding the above, services appear at the GWS via 64-kbps (DS-0) bearer channels contained within T-1 physical links. Signalling related to MET originated calls is handled via separate signaling links from the SLSS as described subsequently.

The GWS supports the MSS network provision of Mobile Telephony Service (MTS). MTS is defined as voice, circuit switched data, and Group 3 FAX. At the highest functional level, the following telephony functions shall be supported in the MSS.

- Establish, maintain and disconnect Mobile Earth Terminal (MET) circuit switched connections.
- The generation and reporting of Automatic Message Accounting (AMA) events to be used for subscriber billing and operations purposes.
- Support of Operations, Administration and Maintenance (OA&M) functions and interface to external support systems.
- Support and interface to voice messaging systems for the network provision of value-added features.

Circuit switched connections may be any one of the following:

- MET to MET
- MET to/from PSTN (IEC or LEC)
- MET to/from Private Network
- MET to Alternate Operator Services
- MET/PSTN/PN to Voice Messaging System

AMA records of call events shall be maintained and reported by the GWS. The basis for this functionality

is LSSGR AMA compliant with some unique MSS data collection required.

The functionality of the Gateway Switching Subsystem has been specified, to the extent possible, to be a generic PSTN, digital switching system. It is desirable to minimize the non-recurring engineering effort imposed on potential switch vendors. Toward this objective, the functional requirements are functionally similar to Bellcore's LATA Switching System, Generic Requirements (LSSGR) document, incorporated herein by reference.

The one area recognized as requiring customized engineering is the interface to the satellite resources, as described below.

The GWS interfaces are grouped into four categories: the Telephone Network Interfaces, Mobile Access Interfaces, the Operations Support Interfaces and the Ancillary Equipment Interfaces. Communications Channel Unit connections are bearer circuits (64-kbps DS-0) carrying voice, circuit switched data or facsimile. The connections to the Station Logic and Signaling Subsystem and the Network Control Center are signalling interfaces.

Operations, maintenance and administration interfaces are to the Network Operations Center. Ancillary interfaces, for example, to Voice Messaging systems are also provided. Telephony network interfaces are shown to the left side of the GWS. PSTN interfaces will be to both the Local Exchange Carrier (LEC) and one or more Inter-Exchange Carriers (IEC). Multiple Private Networks must also be accommodated.

Alternate Operator Services (AOS) provided by other companies may be used initially for the support of Calling Card/Credit Card billing and operator assisted calling. This function may also be accommodated using

so-called "robot operators" which are a specialized version of an Interactive Voice Response (IVR) system.

Trunk access to the PSTN is required. Physical access shall be via T-1 facilities. Extended Superframe format T-1s with ANSI recommended alarms and performance reporting is highly recommended. PSTN access shall support in-band, multi-frequency signaling to and from one or more IECs and the LEC.

Trunk access is also required to Private Networks. Again, physical access shall be via T-1 facilities with analog interfaces, if required, being accommodated with channel banks outside the scope of this specification. Again, ESF format T-1s are recommended.

Alternate Operator Services may be used in the network for the provision of operator assisted calls and credit card billing validation. Physical access to the AOS service provider shall be via T-1 facilities. Collectively, the resources required to support satellite communications are referred to as the Satellite Resources. These resources include the Communications Channel Units, Signaling Channel Units, the Station Logic and Signaling Subsystem and the Network Control Center. Functionally, a GSM 'A' interface is recommended because it best accommodates the fundamental requirements of the satellite interface.

The GSM Recommendation 'A' interface provides the two fundamental characteristics necessary to support the MTS requirements; 64-kbps bearer channels and out-of-band signaling channels. Out-of-band signalling is required to support the interactive nature of call processing between the GWS and the NCC. The NCC has responsibility for three primary functions, as related to the Gateway Switching Subsystem and call processing functionality.

- Management and allocation of the Satellite Resources
- Interworking with Cellular networks for Mobility Management
- 5 • Real-time management and administration of the subscriber database

Because of this parsing of functionality, the GWS must interwork with the NCC (via the SLSS) on all call attempts. As originating attempts are presented at the Communications Channel Units, signalling and subscriber information, necessary for the handling of the call attempt, will be communicated across the SLSS signaling interface.

Likewise, terminating attempts from the PSTN or private networks, to a MET subscriber cannot be handled until the GWS and NCC have communicated to identify the satellite resources to be used, and any subscriber-related data necessary in processing the call.

The Communications Channel Unit interface shall be via DS1 cross connect facilities. Each DS1 cross connect signal provides 24, 64-kbps (DS-0) PCM channels. Communications Channel Units have no fixed association with MET terminals or subscribers. This association is supplied to the GWS on a per call basis by the NCC.

Note: A DS1 cross connect signal is functionally equivalent to a T-1 signal that is used for equipment interconnections between equipments in a building.

Because of the integral role that GWS/NCC communications (via the SLSS) plays in call processing, the SLSS interface must be redundant, be traffic dimensionable, provide for reliable communication of messages, provide reliable communication subsystem recovery in the event of hardware or software failures, and support the OSI model for open systems interconnection. Signalling System 7 (SS7) is

recommended as the most robust signaling protocol available to satisfy these requirements.

The primary function of the Network Operations Center (NOC) is the non real time management and control of MSS resources. The GWS is required to interface with the NOC for the following functions.

- System surveillance and monitoring
- Error logging and tracking
- Control of diagnostic testing and result analysis
- Management of network restoration procedures
- Accumulation of AMA call events
- Database management and administration
- Accumulation and reporting of network performance statistics
- Accumulation and reporting of network configuration data
- Security Management

The Gateway Switching Subsystem shall interface to the NOC for its internal Memory Administration, AMA Teleprocessing, Network Management, Measurements and Statistic reporting and System Status Monitoring and Surveillance.

The NOC interface(s) shall meet OSI requirements for Open Systems Interconnection, such as X.25. The interface(s) shall support multiple physical or logical channels for each function. If multiple logical channels are provided on a single physical interface, each logical segment of the interface shall be dimensionable based on the data through-put demands placed on it.

The Traffic Data Collection System is referenced as the interface for the communication of traffic measurements and statistics to the NOC. This interface is specified in LSSGR FSD 45-09-0100. The GWS interfaces with the NOC to provide remote memory

administration functionality. The Memory Administration Interface shall be provided per the requirements stated in LSSGR FSD 45-01-0701.

5 The GWS AMA Teleprocessing Interface is provided in the form of an AMA Transmitter (AMAT), permitting the store, poll and forward transmittal of GWS collected AMA records to the NOC. This interface meets generic requirements of an AMAT. Network management messaging is defined in Bellcore LSSGR, FSD 45-18-0403 and FSD
10 45-09-0100.

Remote Switching Maintenance Interfaces is provided in either synchronous or asynchronous form. Bellcore LSSGR FSD 35-08-0100 and FSD 35-08-0200 provide details of those interfaces. The synchronous interface is
15 preferred. This interface supports a Voice Messaging System with the capability of delivering original called number identification for forwarded numbers so the voice messaging system can provide personalized greetings.

20 The Gateway Switch consists of multiple items illustrated in FIG. 19. The DMS-MTX SNSE is the main component of the GWS. This component provides the control to perform call management and system control functions. The SNSE was chosen for the optimal cost and size. This configuration supports a 16K port
25 switch. The delivered hardware is Motorola 68020/20MHz based. The SNSE consists of the following sub-components:

- Message Switch (MS) - This component is
30 commonly referred to as the DMS-BUS. The DMS-bus is the messaging hub of the system. The message switch is a fully duplicated entity that provides message routing between system components. A 32 bit MC68020
microprocessor, supported by 6 megabytes of memory,
35 manages the overall performance of the DMS-bus.

• Enhanced Network (ENET). The third shelf of the SCC cabinet contains the ENET. The ENET is a conventional matrix timeswitch designed to achieve high density at low power consumption. The ENET provides a duplicated, junctorless, nonblocking network. The ENET Cross-points are optimized for a 16K channel network.

• Computing Module (CM) - The bottom shelf of the SCC cabinet contains the CM. The CM is fully duplicated, synchronized, computing module. The CM utilizes the 32 bit Motorola MC68020 microprocessor. There are 216 megabytes of call and program store capacity (maximum growth) in each CM.

• System Load Module (SLM) - The bottom shelf of the SCC also contains the SLM. The SLM provides for rapid loading of office images and updates. It consists of a 600 megabyte hard disk and a 150 megabyte high-speed streaming tape drive to permit fast memory loading. There are two SLMs. Each is directly connected to its corresponding CM.

The Intelligent Cellular Peripheral (ICP) is a dual shelf (ICP 0 and ICP 1) peripheral designed to provide the necessary functions for supporting a call processing interface for cell site communications. The dual shelves operate in hot standby mode. That is, one shelf is active, providing the necessary processing and control functions, while the adjacent shelf is in hot standby mode, able to take over if a fault occurs on the active shelf. The call processing interface handles all signaling between the DMS-MTX and the NAP/SLSS to support incoming and outgoing calls, and intersystem handoff. The ICP interface to the NAP/SLSS is done via cell site emulation. The satellite resources (GC, SLSS, NAP, CU) emulate cell site(s) for the ICP. Each "cell site" communicates to the ICP via LAPD communications on a DS0 of the T1 connecting the

satellite resources to the GWS. The ICP views the satellite resources as multiple analog cell sites.

The communicating to and from a cell site is done using a Layer 3 proprietary Northern Telecom cell site protocol. In addition to providing the necessary mechanism to allow the MSS to interconnect to the GWS and provide call processing services, the emulation of a cell site presents some situations that are applicable to cellular telecommunications, but do not have any meaning to satellite telecommunications. These situations are handled by the SLSS and NAP in a manner to satisfy the ICP protocol.

The following list outlines the hardware support that an ICP provides for connecting to the MSS.

- 10 T1s per ICP
- 240 DS0 Channels
- 2 DS0s per Cell Site used for LAP-D Communication (1 Active, 1 Standby)
- 118 DS0 Voice Connections per Cell Site (Maximum)

The ICP connects to the DMS-MTX via one DS 512 fiber link. The DMS-MTX can accommodate seven ICPs providing 1512 channels between the GWS and the NAP/SLSS.

The Digital Trunk Controller (DTC) is a dual shelf (DTC 0 and DTC 1) peripheral designed to provide the necessary functions for supporting trunk terminations to the outside networks. The dual shelves operate in hot standby mode. That is, one shelf is active, providing the necessary processing and control functions, while the adjacent shelf is in hot standby mode, able to take over if a fault occurs on the active shelf. The DMS-MTX will accommodate thirteen DTCs to provide for 255 T-1 connections. (150 CTN, 105 PSTN/PN - max configuration).

The DTC provides the following:

- T1 trunks to process incoming and outgoing call processing (DID and DOT trunks)
- T1 trunks to provide an interface to private network PBXs.
- T1 trunks to Voice Mail systems (Option)
- T1 trunks for Intersystem Handoff voice connections to the CTN (AMSC)
- T1 trunks to PBX to provide support for administration
- T1 trunks to a Channel Bank for four wire E&M connections

The DTC connects to the DMS-MTX via one DS512 fiber link. The DTC can support up to twenty T1s. This provides 480 channels per DTC.

The Link Peripheral Processor (LPP) in the DMS-MTX provides an interface to Northern SS7 networks to provide the following:

- CTN SS7 network to provide point to point IS-41 interface over an F-link to another SS7 CTN node.
- CTN SS7 network to provide IS-41 messaging interface to an STP over a standard A-link.

The LPP connects to the DMS-MTX via sixteen DS30 links. The Input/Output Controller (IOC) provides the interfaces for the microprocessor based Input/Output Device (IOD) controllers. The IOC relays messages to IOD controllers.

The IOC in the DMS-MTX provides the interface for the following devices:

- Maintenance and Administration Positions (MAP) - The MAP is used for overall maintenance and administration of the DMS office. The MAP is a standard VT100 format that provides access to switch table sand configuration.

- Printers - The printers connected to the IOC are utilized to dump log reports and operational measurements to paper.

- Disk Drive Units (DDU) - The DDU consists of a disk drive and power converter card. The purpose of the DDU is to provide storage for CDRs, log files, and other switch output files.

- Magnetic Tape Drive (MTD) - The MTD is a 9-track tape unit used to store data for applications. These applications include OMs, trouble diagnostic data, CDRs, customer data modification, and office data modification.

- Device Independent Recording Package (DIRP) - This is part of the IOD subsystems and operates under the control of the IOC. The main purpose of DIRP is to redirect output from switch processes to output devices such as printers and disk drives. DIRP controls the data flow from originating subsystems such as CDR, OM, of JF, and the recording devices on which the data is to be stored.

- X.25 layer 2 and Layer 3 IS-41 to the CTN - The X.25 connections provided to the CTN provide the carriage of IS41 signaling to and from other Mobile Switching Centers (MSC)s. This connection can operate at 9.6kbps, 19.2kbps, or 56kbps depending on the card and type of X.25 connection/modem.

- Call Detail Record (CDR) Interface - The CDR interface provides the mechanism for the transfer of billing records from the switch to a peripheral device at near real time. For the MSS this peripheral device is the Network Operations Center (NOC).

- Dial up Connection Interface - The Dialup Connection allows the transfer of switch data over a telephone line. These interfaces are commonly used as remote MAPs.

- Operations and Maintenance Connections - The O&M interface is provided by a connection through the IOC to an external device for the transfer of Logs and OMs from the switch to a device for processing.

5 The DMS-MTX contains additional devices used for trunking. The MCAM cabinet type contains the following DMS-MTX devices:

- Package Trunk Module (PTM) - The PTM is a system peripheral module that encodes and multiplexes incoming speech from a maximum of 30 analog trunks into 8-bit pulse code modulation format. The PTM combines information with internal and supervisory control signals for transmission at 2.56 mbs to the network.

- Service Trunk Module (STM) - The STM is a reduced size Maintenance Trunk Module (MTM). The MTM primary function is to interface service, test, and maintenance circuits. Each STM operates independent of the other and functions as a separate peripheral module. The STM accepts analog trunks, digital service circuits, or both, and processes the signals to a common PCM format. One type of STM is the Digital Recorded Announcement Machine (DRAM). The DRAM provides recorded announcements that have been stored in digital format. The DRAM can provide fully digitized voice announcements for up to thirty separate channels simultaneously. A fully configured DRAM can provide up to sixty-four separate announcements.

- Power Distribution panel (PDP) - The PDP performs the power source distribution for the DMS-MTX.

30 The DE-4E Smart Terminal is the chosen Channel Bank for CGS. This Smart Terminal is an intelligent microprocessor based EMI compliant system designed to provide point to point private lines. The single-digroup DE-4E Smart Channel Bank is capable of housing up to 24 "service adaptive" channel units. The channel

units are available for two wire or four wire circuits and various signaling including E&M type 1, 2 and 3.

The Timing Signal Generator (TSG) is used to derive system clocking for SS7 signaling. The TSG derives its timing from T-1s connected to a toll office with a stratum three or higher clock. The TSG then distributes timing to the various components. Note that the TSG is only used when SS7 signaling is required. The DCD-400 from Telecom Solutions is the chosen model for the GWS TSG.

When the TSG is not used to provide system clocking, a standard clock card in the SNSE cabinet is used to distribute clocking to the DMS-MTX.

To provide the ability to patch T-1s from the DTC and ICP to various other pieces of hardware, Channel Banks, MUXs, and MAPs for example, the MTX is equipped with two Digital Signal Crossconnection Patch Panel (DSX) patch panels, such as the DSX-29/56 model manufactured by ACD Telecommunications. The patch panel provides the following:

- 56 connections total
- Wire-wrap rear cross-connects
- Horizontal and vertical rings
- Flush 3" or 4" mountings
- Jacks numbered A 1-28, B 1-28
- Red flashing LEDs
- Bantam jack monitoring and patching

The Main Distribution Frame (MDF) is the demarcation point for four wire E&M trunks.

The GWS software and hardware will provide for the following Voice Service Features in addition to the basic call processing.

- Call Forwarding Unconditional - The GWS will control the forwarding of calls made to MT users that have activated this call forwarding feature. When this

feature is activated, calls are forwarded to the CFU number without attempting to contact the MT user.

• Call Forwarding Busy - The GWS will control the forwarding of calls made to MT users that have activated this call forwarding feature. When this feature is activated, incoming calls to a MT are forwarded if the MT is involved in another call. Note that the incoming call must be to the same MIN that the MT is currently using.

• Call Forwarding No Reply - The GWS will control the forwarding of calls made to MT users that have activated this call forwarding feature. When this feature is activated, incoming calls to a MT are forwarded if the MT either does not respond to the page request, or times out ringing.

• Call Waiting - The GWS will control this feature. If a MT user is involved in a call and receives another call to that MIN and has Call Waiting, the DMS-MTX puts the incoming call on hold and applies a 440Hz tone to the voiceband to notify the MT of the other call. If the MT user decides to toggle to the other call, the DMS-MTX connects the second call to the MT and puts the original call on hold.

• Conference Calling - The GWS will control this feature. If a MT user decides to add a third party to a call (the DMS-MTX supports a maximum of three parties in a call), the MTX puts the first call on hold, allocates a conference port and routes the second call. Once the MT user signals the MTX to conference the calls, the MTX connects all three parties together. If the MT who originated the first call was the originator of the conference, and he hands up, all parties are disconnected.

• Call Transfer - The GWS will control this feature. If a MT was called by another party and wishes to transfer the call, the MTX puts the first

call on hold and allocates a conference port and routes the second call. At this point there are three options for the MT.

- Option 1 - Hang up before the party answers. In this case the MTX will transfer the call.

- Option 2 - Wait for the other party to answer, talk and hang up without ever conferencing in the other party from the first call. At this time, the MTX will transfer the call.

- Option 3 - Wait for the other party to answer, conference in the other party. After conversing in a conference, hang up. At this time, the MTX will transfer the call.

• Call Forwarding Congestion - The GWS will control this feature. If the situation arises at the GWS where all of a particular trunk group is busy to or from a switch, the DMS-MTX has the capability to datafill a secondary route that will be used if the primary route is busy or out of service. There are two other possible call forwarding scenarios that the switch addresses. First, if there are no channel units available for a particular call, the MTX will send the call to an announcement. Next, if there are channel units available, but no satellite frequencies, the MTX will either send the call to the page timeout announcement, or reroute the call if the MT user has this feature activated for the particular MIN being called.

• Call Barring - The GWS will control part of this feature. The GWS will validate the MIN and ESN of a MT either via a lookup in the HLR or by communicating to the Home MSC of the MT via IS41. The GWS provides line options in the HLR to allow restrictions such as denied originations (DOR), denied terminations (DTM), or suspended service (RSUS, SUS) to be placed on MT users.

- Operator Assistance - The GWS will control this feature. The DMS-MTX provides the ability to route calls that request operator services to a route that will send the call to an operator switch.

5 • Alternate Account Code Charging - The GWS provides the ability for users to append a digit code (Account Code) at the end of the dialed digit string to differentiate calls made from different accounts. This string is not validated by the MTX and is strictly for
10 customer billing clarification.

 The call detail record (CDR) system is used to record comprehensive billing and other data on all calls. The CDR system accepts call information data from the DMS system. The data is then recorded on a
15 tape, disk, or sent to the NOC by using the standard Multi-Network Protocol (MNP) protocol manufactured by Northern Telecom used to transfer CDR billing data from a DMS-MTX switch to a remote billing processor at near
 real-time.

20 The CDR's are recorded on the hard disk at the GWS and sent to the NOC by the X.25 (MNP) using a V.35 interface. There is a redundant X.25 link that can be enabled in the event of a failure of the primary path to the NOC. Since the CDRs are written to the hard
25 disk at the GWS, the transfer on the backup link can begin at the point where the transfer failed in the case of a redundancy switch. This method insures that CDR's are not lost in the event of a failure in the primary path from the GWS to the NOC. The CDR fields
30 are described in Table A.

 The message protocol used for MNP contains the following Protocol Data Units (PDU):

ACS-SFO: Access request message - Start file
outgoing

This message contains the information necessary for the far end to begin establishment of a file transfer.
(35 octets)

STS-ACK: Status message - Access request acknowledge
5 This message is sent in response to the ACS-SFO message when the NOC accepts the billing file request.
(3 octets)

CNT-PRT: Control message - Set device to print mode
10 This message is sent to the NOC when the GWS is ready to transfer data. (2 octets)

CNT-RED: Control message - Set device to read mode
This message is sent by the NOC to start the file transfer. (2 octets)

STS-EOB: Status message - End of block
15 This message contains the sequence number of the previous sent data block. This message is sent by the GWS to describe the data block just sent. (8 octets)

CNT-RNB: Status message - Request next block
20 This message contains the sequence number of the received data block. This indicates that the data blocks up to the sequence number were successfully received by the NOC. (6 octets)

STS-EOF: Status message - End of file
25 This message is sent by the GWS when the entire billing file is transferred. (2 octets)

STS-CPL: Status message - Access complete
This message is sent by both the GWS and the NOC to wrap up the current session. (2 octets)

DATA: Application Data

This message is a 2K octet block of data, and is followed by the STS-EOB message. It contains billing information which is retrieved from the billing file on the disk.

The following describes the basic message flow between the GWS and the NOC for the transfer of CDRs via MNP.

Step 1: The GWS has a billing file ready to transfer. The SVC of X.25 at layer 3 has been established between the GWS and the NOC.

Step 2: The protocol messages have been exchanged for startup, and both ends have recognized the billing file. At this point, the file transfer is ready to start.

Step 3: The data blocks are sent from the GWS to the NOC. In the opposite direction, acknowledgement messages are sent back to the GWS to notify it of successful transfer of a data block. This example, shows a window size of one. This means that a CNT-RNB is expected before another data block is sent from the GWS. For applications with larger window sizes, i.e., greater than 1, the GWS will not wait for a NTR-RNB for a data block before transmitting the other data blocks contained in the window. The CNT-RNBs for each block are still expected, but can arrive back at the GWS in any order.

Step 4: When reaching the end of the billing file, the STS-EOF message is sent to the NOC to notify it of the completion of the file transfer. Subsequently, the STS-CPL message is exchanged to end the session.

Step 5: The GWS shuts down the X.25 SVC link between the GWS and the NOC.

Some MSS system users have voice communication requirements that are not met by MTS and Mobile Radio

Service (MRS). They need to communicate in a virtual network arrangement that allows each member of the group to hear what any other user is saying. Each member of the group can also talk when needed. The system behaves like a radio multi-party line. Public services and law enforcement agencies are typical users of this service, which is normally provided by either traditional terrestrial radio networks or by the more recent trunked radio systems. These trunked systems, generally in the 800-900 MHz band, provide groups of end users with virtual private systems by assigning frequencies to CUGs on a demand basis. The virtual network service is meant to be the satellite equivalent of terrestrial trunked systems ("trunking" for short), and could be pictured as a "Satellite Trunked Radio Service", or "Satellite Trunking".

The virtual network service provides the capability described in the previous paragraph in a cost effective manner:

as one shared satellite demand period circuit per virtual network is utilized rather than one circuit per mobile user, the cost per minute of a group conversation would be much less expensive to the owner of the group, and

as the call set-up time for one shared circuit per virtual network compared to an MRS multi-user conference set-up time is likely to be more acceptable to a group end user/operator, who normally expects to be able to talk as soon as the handset/microphone is taken off-hook.

A virtual network is defined as a partition of METs and FESs within a control group having particular connectivity attributes. Each virtual network has a defined set of service features to which its users may subscribe as a whole or individually. As illustrated in FIG. 20, a virtual network is associated with a

group of FESs and METs. It is possible for an FES to belong to a particular virtual network or be shared by multiple virtual networks. It is also possible for a MET to belong to a maximum of 16 different virtual networks. Interconnection between different virtual networks is supported by the MSS system.

The database files on the METs and the communications nets of a subscribing organization comprise a Virtual Network (VN) within the MSS system, and is assigned a Virtual Network identification number. All of the METs in a VN may communicate with each other.

An overview of the MSS system with the VN service is illustrated in FIG. 21. FIG. 21 illustrates the basic concept and elements involved in establishment of communications and control in the virtual network system. METs access the system via one or more L-band beams. Each beam contains one or more signaling channels for network control and call establishment and a number of communications channels for provision of virtual network services to METs.

The L-band frequencies are translated to Ku-band frequencies by the satellite 12. The Network Control Center 14 is responsible for the real time allocation of channels to support virtual network calls. The base Feederlink Earth Station 16 is responsible for re-transmission on the outbound channel of the MET transmissions received on the inbound channel, control of the virtual network call, and interfacing the virtual network call to terrestrial private networks.

Virtual network service is available to users in the virtual network group on subscription to MSS. A subscribing organization may comprise a number of METs grouped by their communication needs. A virtual private communication net is established for each of these groups or subgroups.

The base FES 16 can interconnect the virtual network call to terrestrial private networks so that a dispatcher located within the private network can participate in the conversation. A dispatch facility
5 may be directly connected to the base FES 16, or may use leased PSTN or dial-up access, or may use a Mobile Radio Service (MRSA) circuit. An example of a virtual network service subscribing organization with several communication virtual networks is depicted in FIG. 22.

10 The virtual network MET operates in a virtual network and receives voice transmissions from all other MET users in the same virtual network group, and the base FES. The MET supports virtual network service on a single demand period circuit per beam, which is
15 shared by the entire group. The MET requiring communications will be given the virtual network (VN) ID for the net and since different VN groups may be necessary for different purposes, the MET may be given a number of different VN IDs.

20 VN IDs may represent organizational groups such as fleets or sub-fleets. VN IDs may represent functional groups such as a command unit which draws on mobile users from more than one fleet or sub-fleet. VN IDs may represent geographic configurations such as an east
25 or west area, or both.

Virtual Network Configuration

Each GC receives from the NOC, via the NCC Controller, the Virtual Network configuration database from each customer network. The database is processed
30 and organized to support and optimize all real-time call processing accesses for Virtual Network attributes and configuration data. During operation the GC shall support the incremental addition to, deletion from, or modification to, the Virtual Network configuration
35 database, under direction of the NOC.

To support configuration changes each GC shall control the operating state of its Virtual Networks in accordance with NOC directives. Transitions between the following Virtual Network operational states shall be supported:

- a. Inactive/initialized. Ready to become active.
- b. Active - normal. Processing traffic normally.
- c. Active - unloading. Blocking new calls and servicing disconnects to unload traffic.
- d. Active - unloaded. Blocking new calls; traffic has been unloaded.

The NCC Controller is able to display each GC Virtual Network configuration and status tables locally via the NCCTE man-machine interface, or to transmit Virtual Network configuration and status tables upon request to the NOC via the MSS Internetwork.

Virtual Network Call Status

These tables contain call status data for each Virtual Network:

- a. Call data records:
 - i. Call Identifier
 - ii. FTIN
 - iii. RTIN
 - iv. MET supplied dial digits
 - v. Terrestrial network supplied dial digits
 - vi. MET port id
 - vii. Service type (voice, data, fax and expansion to new service types)
 - viii. Connection type (MET to terrestrial, MET to MET, terrestrial to MET.
 - ix. Control Group ID
 - x. Virtual Network
 - xi. Advanced features used
 - xii. FES Terminal
 - xiii. Circuit pool utilized.

- xiv. L-band beam accessed.
- xv. Forward link Ku-Band frequency used.
- xvi. Forward link L-Band frequency used.
- xvii. Return link L-Band frequency used.
- 5 xviii. Return link Ku-Band frequency used.
- xix. Forward link power level authorization.
- xx. Queueing flag.
- xxi. Priority for queueing.
- xxii. Date/time of access request.
- 10 xxiii. Date/time of channel assignment.
- xxiv. Date/time of setup complete.
- xxv. Date/time of channel release.
- xxvi. Call clearing reason code.
- b. Aggregate calls in progress.
- 15 c. Current call processing completion rate.
- d. Current call blocking rate.

Virtual Network Configuration Table

This table defines the configuration databases for each Virtual Network, served by the Control Group. The database provides a complete definition of each Virtual Network's service permissions, routing rules, and address screening constraints. This table also contains the NOC assigned operating state for each Virtual Network - Inactive/Initialized, Active-Normal, 20 Active-Unloading, Active-Unloaded. The GC supports foreground and background Virtual Network Configuration tables to facilitate the network configuration change procedures.

Virtual Network Functional Characteristics

30 This section describes the virtual networking capabilities offered by the MSS. Generally from a functional perspective, a virtual network involves membership rules, a dialing plan, and a set of dialing allowances and/or restrictions.

Each MET is a member of at least one VN. A MET is optionally a member of up to 15 additional VNs. One VN of which a MET is a member be denoted as the default VN for that MET. MET VN membership(s) is provided on a subscription basis. Dual-mode METs (METs capable of both cellular and MSS operation) that are registered in the MSS shall constitute a specific VN denoted VN-C. No other METs is members of VN-C.

VN MET addresses are selected from blocks of numbers allocated from the North American PSTN. Since MET numbers are selected from the North American PSTN, and no number translation is performed, MET and PSTN/PN numbers are disjoint. A MET user has the capability to select, on a call-by-call basis, the specific VN within which he/she wishes to act; this VN is denoted the "acting VN". The MET user indicates the acting VN by an optional suffix. If no suffix is presented, the acting VN is the default VN defined for the MET. The MET must be a member of any VN selected by the suffix.

Within an acting VN:

- a. MET-to-MET calls utilize 7-digit (NXX-XXXX) dialing, or 10-digit (NPA-NXX-XXXX) dialing. Other dialing plans for MET-to-MET calling may be offered as options.
- b. MET-to-PSTN/PN calls utilize 10 digit dialing, international dialing and dialing access to operators, carriers, etc., as offered by the connected PSTN/PN.

All dialed numbers are subject to screening based on the VN rules and the screening associated with the individual MET. In VN-C (for dual-mode METs registered in the MSS) registered dual-mode METs shall use their usual PSTN number.

For each VN, it is possible to define call screening (call barring) rules (restrictions and allowances) for every MET in the VN. Screening rules

for MET originated calls are definable to govern the allowance of a call originating at every MET in the VN. Screening rules are definable to govern the acceptance of a call presented to every MET in the VN. In addition to screening rules defined for all METs in the VN, screening rules are separately definable for individual METs within the VN.

For MET-originated calls, the following general rules are available based on the called number.

- 10 A MET-originated call may be permitted to:
- a. Any MET number in the VN.
 - b. No MET number in the VN.
 - c. Any PSTN/PN number.
 - d. No PSTN number.
 - 15 e. Only domestic US PSTN numbers.
 - f. Only PSTN numbers within NPAs on a specified NPA list.
 - g. No PSTN numbers within NPAs on a specified NPA list.
 - 20 h. Only to MET and/or PSTN/PN numbers on a specified list.

Order of application of these rules shall be as indicated by the decision tree in FIG. 23. For calls presented to METS, the following rules are available based on the call source (when available)

- 25 A MET-presented call may be permitted from:
- a. Any MET number in the VN.
 - b. No MET number in the VN.
 - c. Any PSTN/PN number.
 - 30 d. No PSTN/PN number.

If calling line identification presentation is available from the PSTN/PN, a MET-presented call may be permitted from:

- e. Any domestic US PSTN number.

- f. Only PSTN numbers within NPAs on a specified NPA list.
- g. No PSTN numbers within NPAs on a specified NPA list.
- 5 h. Only from MET and/or PSTN numbers on a specified list.

Order of application of these rules are as indicated by the decision tree in FIG. 23. Additional call screening rules may be provided. For example, a
10 MET restricted from making any outgoing call is restricted from Call Transfer since that feature involves outgoing call placement.

MET Features

This section provides a description of each feature available to MET users. Availability of a feature to a
15 specific MET depends on the characteristics defined for the VN in which the MET is a member and the characteristics defined for the individual MET.

Connected Line Identification Presentation (COLP)
20 is a service that is offered to the calling MET to provide presentation of the connected MET's number (when the call is established) to the calling MET. The GWS is capable of providing at least 10 digits for MET-terminated calls and at least 15 digits for PSTN/PN-
25 terminated calls to the calling MET.

COLP is provisioned on a subscription basis collectively to each METs within the VN. COLP is withdrawn on request by the subscribing authority or by MSS for administrative reasons. COLP is active on
30 subscription and inactive on withdrawal. COLP is automatically invoked by the GWS at call completion. When COLP is allowed and active, the GWS provides the calling MET with the connected MET VN number at call completion (answer) for all MET-originated incoming
35 calls.

When COLP or equivalent service is provided by the PSTN/PN, and the connected PSTN/PN number is provided by the PSTN/PN, the GWS provides the calling MET with the connected PSTN/PN number at call completion (answer) for all PSTN/PN-completed calls. When COLP is allowed and active, the connected number is not presented if:

- a. The connected MET has COLR activated, or
- b. The connected number is not available from the PSTN/PN.

Assume that a user A has an established call with user B and transfers this call with user B to user C. If user A has activated COLP, user A receives B's number when user A evokes the normal call transfer procedure. If user C has activated COLP, user C receives B's number at the transfer of user B to user C. A conference controller who has COLP activated is presented with the connected party's number when that party is either part of the initial activation of the conference or is added to an existing conference.

If the connected party has activated Connected Line Identification Restriction the connected number is not presented to the calling party. If the incoming call from a MET with COLP activated has been forwarded, the number presented to the calling party is the number of the final "forwarded to" party.

Connected Line Identification Restriction (COLR) is a service that is offered to the connected MET to restrict presentation of the connected MET's number to the calling MET or to the PSTN/PN. COLR is provisioned on a subscription basis collectively to each MET in the VN and/or individually to METs within the VN. COLR is withdrawn on request by the subscribing authority or by MSS for administrative reasons. COLR is active on subscription and inactive on withdrawal.

When COLR is allowed and active, the GWS does not provide the calling MET with the connected MET VN number for all MET-originated calls. When COLR is allowed and active, no connected MET number is provided to the PSTN/PN for any PSTN-to-MET calls.

Assume that a user A has an established call with user B and transfers this call with user B to user C. If user B has activated COLR, user A receives B's number when user A evokes the normal call transfer procedure. If user B has activated COLP, user C receives B's number at the transfer of user B to user C. If potential conferees have COLR activated, the conference controller is not presented with the connected party's number when that party is either part of the initial activation of the conference or is added to an existing conference.

If the connected party has activated Connected Line Identification Restriction (COLR), the connected number is not presented to the calling party. If the incoming call from a MET with COLP activated has been forwarded, and the "forwarded to party has COLR activated, the "forwarded to" party's number is not presented to the calling party.

The intent of sub-addressing is to allow the identification of separate ports and connected device that may be part of a MET. Examples include voice, facsimile and data ports/devices. Each usable port on a MET shall be assigned an VN number. The implication is that a MET port that is physically present but does not have an assigned number cannot be used. In the following, the term "MET sub-address(s)" is used to describe one or all of the set of (complete) VN numbers assigned to the ports of a given MET.

The general model adapted for the subaddressing description is a PBX telephone with multiple extensions associated with it. For example, a result of this

model is that the various MET subaddresses can be forwarded separately -- this (and other) results are appropriate for multi-device (multi-media) METs.

Subaddressing is provisioned and number assigned on a subscription basis individually to METs within the VN. Subaddresses is withdrawn on request by the subscribing authority or by MSS for administrative reasons. Subaddressing is active on subscription and inactive on withdrawal.

Features are subscribed to and activated for each MET subaddress separately (e.g., forwarding). It is assumed that some features (e.g., Forwarding, Hold, Transfer) will have utility for non-voice calls. Others are precluded by the nature of the communication devices (e.g., Conferencing, Call Waiting). For call completion purposes, a MET is considered busy if any MET subaddress is busy. Forwarding applies to each MET subaddress separately. However, for Call Forwarding Busy, the busy state applies as in 2 above.

Call Forwarding No Reply is interpreted to apply to a MET port that has a MET subaddress assigned but no device connected. In-channel Call Waiting indication is applicable to voice ports/devices only. Number Identification features shall apply to each MET subaddress separately. For example, CLIP can be activated for some MET subaddresses and not others. Call screening rules shall be definable for each subaddress separately.

The Call Transfer (CT) feature enables a MET user (the "served user" or "A") to transform an established call into a new call between the other party on the established call (user "B") and a third party (user "C"). The "normal" Call Transfer procedure is offered as a feature to MET users. The GWS may offer an additional "single step" Call Transfer procedure (see below) to MET users.

"Normal" call transfer (sometimes called "screened transfer") establishes a call between the served user and the third party that may be subsequently transformed into a call between the other party and the third party. Optionally, the GWS may offer "single step" ("unscreened") transfer where the transfer occurs without an established call between the served user and the third party.

CT is provisioned on a subscription basis collectively to each MET in the VN and/or individually to METs within the VN. CT is withdrawn on request by the subscribing authority or by MSS for administrative reasons. Each of the CT types offered is subscribed to separately. The "normal" call transfer procedure shall normally operate as follows:

- a. An established call exists between A and B.
- b. A invokes the "normal" CT procedure, providing the number for C.
- c. B shall be placed on hold and a call shall be established between A and C.
- d. During the established call, A invokes completion of the "normal" CT procedure.
- e. B shall be connected to C; connection are removed between A and the other parties.

If, during the "normal" CT procedure, the call to C cannot be established, A shall be able to retrieve the connection to B. The "single step" call transfer procedure, if offered, normally operates as follows:

- a. An established call exists between A and B.
- b. A invokes the "single step" transfer procedure, providing the number for C.
- c. A call is established between B and C. A is disconnected.

After the "single step" CT procedure has been invoked, B is considered the originating party of the attempted

call to C; for example, B is informed of alerting at C and, if the call to C cannot be completed, B is informed.

Call forwarding allows the served or "forwarding" user to direct the GWS to send incoming calls to the served MET number to other numbers under specific conditions. Call Forwarding Unconditional (CFU) allows the forwarding user to direct the GWS to send all incoming calls to another number. Call Forwarding Busy (CFB) allows the forwarding user to direct the GWS to send incoming calls to another number if the forwarding user's MET is in the "busy" state (establishing a call or involved in an established call, on hold or invoking a feature).

Call Forwarding Congestion (CFC) allows the GWS to send incoming calls to a recorded announcement if the forwarding user's MET cannot be connected to MSS congestion. Call Forwarding No Reply (CFNR) allows the forwarding user to direct the GWS to send incoming calls to another number if the forwarding user does not reply within a subscribed time interval.

Forwarding is provisioned on a subscription basis collectively to each MET in the VN and/or individually to METs within the VN. Forwarding is withdrawn on request by the subscribing authority or by MSS for administrative reasons. Each of the forwarding types offered is subscribed to separately. MSS may offer forwarding in "packages" containing one or more forwarding types.

The served user is able to activate each of the forwarding types offered separately. Activation of forwarding requires the served user to supply the forwarded-to number. The GWS validates the forwarded-to number to the extent possible before activating forwarding. When forwarding is active and forwarding conditions are met, forwarding is automatically

invoked; incoming calls to the served user's MET is forwarded without being offered to the served user's MET.

5 A configurable limit is provided on the maximum number of forwarding invocations that result from a single original call. This is intended to prevent "infinite forwarding." The GWS may provide notification to the served user's MET when forwarding takes place. When a call is forwarded, the forwarded-
10 to MET is provided an indication that the incoming call is offered as a result of forwarding. The GWS provides the originally called number and the condition for the last forwarding operation to the forwarded-to MET.

The GWS provides notification to the calling user
15 that the call has been forwarded. The GWS provides the capability for the served user to review the MET's forwarding status. The forwarding user's MET optionally receives an indication that an incoming call has been forwarded. This may involve a separate
20 subscribed service.

Call waiting (CW) is a service that is offered to a called MET that provides that MET indication of an incoming call, if busy. If it can be determined that the active call is a voice call, in-channel indication
25 (tone) is provided. Otherwise, in-channel indication is not be provided. The number of waiting calls at a busy MET is limited to one. Additional incoming calls receive busy indication.

CW is provisioned on a subscription basis
30 collectively to each MET in the VN and/or individually to METs within the VN. CW is withdrawn on request by the subscribing authority or by MSS for administrative reasons. CW is active on subscription and inactive on withdrawal. A procedure is provided to allow
35 activation or inactivation on a call-by-call basis.

CW is invoked by the GWS automatically when a call is presented to a busy MET unless a waiting call exists at that MET. The MSS network may not be aware of the state where the MET users is entering digits for a call but has not yet invoked "send." During this state call attempts may ring rather than invoke CW or busy forwarding. Call Forwarding Unconditional takes precedence over CW. CW takes precedence over CFB. CW is presented if the called MET has CFNR activated.

The Call Hold (CH) service allows a served MET user to interrupt an existing active call and subsequently resume (retrieve) the active call. The bearer channel remains assigned to the served user to allow the origination or termination of other calls. The retrieve re-establishes the original (held) call on the bearer channel. CH is provisioned on a subscription basis collectively to each MET in the VN and/or individually to METs within the VN. CH is withdrawn on request by the subscribing authority or by MSS for administrative reasons. Call Hold is invoked by the served MET user by use of a control procedure.

The served user has the capability to invoke or hold any time after a call has been answered and before call clearing has begun. Call Hold allows either MET or both METs in an active call to invoke Call Hold. That is, it is possible for each party to have the other on hold. If a user invokes hold while held and makes an additional call, a new channel will be assigned.

Provision shall be made for providing the held MET user with in-channel indication ("comfort" tone, music, etc.) that the held state persists. This indication will also inform the user who retrieves a held call that has been placed on hold by the other party. If a MET becomes idle with a call on Hold, an indication is provided to that MET that the call remains on Hold.

Conference Calling (CONF) is a service that provides the served MET user the capability to establish simultaneous communications with more than two and up to five parties. Since MET voice traffic is presented to the GWS in a packetized, compressed encoding, it is not required that the GWS provide the capability to conference more than one MET. Thus, GWS provides the capability for conferencing among a single MET and up to five PSTN/PN parties.

CONF is provisioned on a subscription basis collectively to each MET in the VN and/or individually to METs within the VN. CONF is withdrawn on request by the subscribing authority or by MSS for administrative reasons. CONF is active on subscription.

CONF is invoked by the served MET user by use of a control procedure. The served user has the capability to request the conference as a new call or request that the conference be based on existing held calls. The served user has the capability to include the maximum number of conferees in the conference request or to accept a pre-defined default. Upon completion of the conference request, a conference is established among the served MET and the other parties.

After the initial conference establishment, the served user (the conference controller) has access to the following party management functions:

- a. Add new party -- the conference controller has the capability to add a held call or establish a new call which may be added to the conference.
- b. Drop party -- the conference controller has the capability to remove conferees from the conference. If the conferee is not explicitly identified, the last party added is removed. If, after the party is dropped, a single conferee remains, the GWS may establish a two-party call.

c. Split party -- the conference controller has the capability to remove a specified party from the conference and establish an active (two-party) call with the specified party. From the perspective of the conference controller, the conference is on Hold. The conference controller has the capability to resume the conference after a split (i.e., return both parties to the conference).

A mechanism for supplying Conferee IDs for conference management features above (e.g., dropping a specific conferee) is provided. The conference controller has the capability to disconnect the conference. All conferees and the conference controller are dropped and the conference resource (bridge) is released.

Alternate Account Charging (AAC) allows a MET user to charge a call to an account other than the usual or default account. Alternate account charging provides the MET user the capability to supply an Alternate Account Number during call setup request. GWS records the Alternate Account number in the CDR. GWS is not required to verify or otherwise validate the Alternate Account Number.

AAC is provisioned on a subscription basis collectively to each MET in the VN and/or individually to METs within the VN. AAC is withdrawn on request by the subscribing authority or by MSS for administrative reasons. AAC is activated upon subscription. AAC is optionally invoked by the MET user at call setup request. The invocation includes the Alternate Account Number.

Call Queueing and Priority (CQP) are intended to be applied to MET-originated calls in the event of MSS network congestion. Note that the management of satellite resources is a function of the MSS Network

Control Center (NCC) and not a function of the GWS. However, upon notification of satellite resource congestion by the NCC (via the SLSS), the GWS queues calls affected by that congestion. Similarly, upon
5 notification by the NCC that congestion no longer exists, the GWS attempts to service queued calls as detailed below.

Priority and queueing are not intended to be applied in the event of a buy MET. Call Priority and
10 Queueing may also occur as a result of congestion for PSTN/PN access. Congestion of MSS satellite signalling channels occurs as well as traffic channel congestion. Signaling access queueing occurs external to the GWS.

GWS supports traffic access queueing for MET-
15 originated calls when traffic congestion is indicated by MSS. Determination of satellite congestion conditions is not a function of the GWS. GWS supports traffic access queueing for MET-originated calls when PSTN/PN access congestion exists. Traffic access
20 priority is assignable to a VN and to individual METs. Call setup requests are queued under congestion conditions and are processed first-in, first-out within individual priorities.

CQP is provisioned on a subscription basis
25 collectively to each MET in the VN and/or individually to METs within the VN. CQP is withdrawn on request by the subscribing authority or by MSS for administrative reasons. Specification of priority accompanies subscription. CPQ is active on subscription. If CQP
30 is not subscribed to, calls receive a congestion indication but will not be queued.

CQP is invoked automatically by GWS upon indication of satellite congestion by the SLSS or detection of
35 PSTN/PN access congestion by GWS. If CPQ is invoked, GWS provides the calling MET indication of congestion

and queueing. When congestion is relived, GWS serves queued calls according to priority as follows:

- a. Originating a call to the MET that originated the queued call.
- 5 b. If this call is successful, GWS shall execute call setup procedures for the queued call.

Virtual Network Manager

Virtual Network Manager controls user access to a designated virtual network and its service features,
10 provides communication circuits among member users on a call-by-call or full period basis, and manages a customer virtual network. The Virtual Network database entries for a given network shall specify the type of services, network features and call routing options
15 that are available for use by member METs and FESSs. Virtual Network Managers interact only with member METs an FESSs.

The Virtual Network Management function interfaces with the Group Resource Management function and the
20 Network Access processing function to carry out its responsibilities to receive call requests and issue satellite circuit assignments, to request, receive and return satellite circuits from/to the CG circuit pool, to return preempted circuits, and to transmit call
25 records following each call cleardown.

To provide service connections for customers, Virtual Network Management provides functions for connection period control, call processing, call routing, circuit configuration, address screening,
30 emergency preemption, and resource utilization auditing. The Virtual Network Manager maintains a record of which GC managed features are active. Features which are activated by subscription are active and perform the actions specified below for each active
35 feature.

The GC supports VN configurations for virtual network service consisting of a set of METs, each with a MET Database File, and a set of virtual network communication groups, each assigned a VN ID with a VN ID Database File. The GC performs VN Management for each call request. Each GC supports multiple customer virtual network configurations in accordance with the virtual network definition.

As each MET or FES originated access request is received, the GC identifies which Virtual Network is being accessed, according to the procedures specified below, and utilizes the associated Virtual Network database and the Customer Configuration database to process and service the request. Virtual Network management is performed for each call request in accordance with the call processing specifications.

The GC supports the provision of advanced service features to MET. When Call Forwarding or Call Waiting has been activated the following Virtual Network call processing requirements for basic service shall be superseded at the appropriate points in the protocols.

The following describes the Virtual Network process requirements in the context of FIG. 24 which is a more detailed illustration of the NCC terminal equipment. MET originated access requests received by the Network Access Processor are routed to the GC to which the receiving MET-SR signaling channel has been assigned by the NCC Controller. The GC takes the following actions based on the GC operational state.

GC Operational State	MET Request Disposition
Inactive/Initialized	Discard all requests
Active - Normal	Process all requests

GC Operational State	MET Request Disposition
Active - Unloading	Block new "Access Requests" with "Call Failure" - Services not available Discard all other requests
Active - Unloaded	Block new "Access Requests" with "Call Failure" - Service not available Discard all other requests

In the Active - Normal state the GC examines the
 "Access Request" message to determine whether a Virtual
 Network identifier has been transmitted by the MET
 along with the dial digits. If a Virtual Network
 identifier has not been included in the request, the GC
 determines the METs default Virtual Network from the
 Customer Configuration database. If a particular
 Virtual Network has been requested, the GC utilizes the
 customer Configuration database to convert the logical
 Virtual Network identifier of the message to the
 internal Virtual network identifier. The GC then takes
 the following actions based on the Virtual Network
 operational state.

Virtual Network Operational State	MET Request Disposition
Inactive/Initialized	Discard all requests
Active - Normal	Process all requests
Active - Unloading	Block new "Access Requests" with "Call Failure" - Service not available Discard all other requests

Virtual Network Operational State	MET Request Disposition
Active - Unloaded	Block new "Access Requests" with "Call Failure" - Service not available Discard all other requests

FES originated channel requests received by the Network Access Processor are routed to the NCC Controller, based on the message destination address. FESs will address channel requests to the NCC Controller so the MET Control Group membership can be determined. The NCC Controller accesses the Customer Configuration database, using the MET telephone number dial digits included in the FES "Channel Request" message, and determines the identity of the GC to which the MET belongs. The NCC Controller then forwards the message to the identified GC. The GC shall take the actions as specified above based on the GC operational state.

In the Active - Normal state the GC accesses the Customer Configuration database, using the MET telephone number dial digits included in the FES "Channel Requests" message, and determines the identity of the Virtual Network which is being accessed. The GC then takes the actions specified above based on the Virtual Network operational state.

Whenever the NCC Controller determines that the GC cannot be successfully identified in the databases using received access signaling data, the access request is denied. Whenever the GC determines that a called or calling MET is registered but the Virtual Network cannot be successfully identified in the databases using received access signaling data, the access request is denied. When calls are so denied, a

"Call Failure" message with the cause set to "Service not Subscribed" is sent to the requesting MET or FES, and the call data record is terminated with the cause indicated.

5 Upon successful identification of the Virtual Network serving the access request, the GC processes calls, using the associated Virtual Network database, in accordance with the Virtual Network management requirements specified in the following sections.

10 Whenever a call record for an access request is terminated for any reason, the appropriate Virtual Network performance statistic is updated.

 Access request processing consists of call screening actions using the Customer Configuration and Virtual Network databases, and the MET Status Table, to
15 determine whether the requested service is a valid subscribed service for the MET and the Virtual Network, and whether the MET status is in a call state compatible with the access request. In performances of
20 MTS access request processing, the GC processes dial digits for PSTN users in accordance with the PSTN numbering plan. In performance of MRS access request processing the GC accommodates independent numbering plans, using fewer dial digits than the PSTN plans,
25 which will be utilized by each private Virtual Network.

 Upon each MET or FES access request, the GC evaluates the security authentication history for the associated MET. If a configurable number of authentication failures have occurred within a
30 configurable time period from the time of access, the call is denied.

MET to Terrestrial Network Connection Requests

 In processing MET originated call requests, the GC receives MET "Access Request" and "Additional Digits"
35 messages, and shall transmit "Additional Digits

Request" and/or "Call Failure messages when required. Upon receiving a MET "Access Request" the GC accesses the MET Status Table using the RTIN to verify the calling MET is in the "Operational" state and whether
5 the MET is currently engaged in a call. The identity of the MET-SR channel receiving the request is used by the GC to verify whether the MET is currently logged on to correct L-Band beam as indicated in the MET Status Table.

10 Log-on errors result in a PVT for the MET with the event and results sent to the NOC and noted as anomalous events. When the PVT is successful the MET is logged on to the associated beam. If the MET is not in the "Operational" state the GC terminates the call
15 record and sends a call failure message to the MET with the reason set to "Services not Available". If the MET is operational, the GC accesses the MET Status Table to evaluate the current MET call state.

20 If the MET call state indicates the GC is currently awaiting circuits or a MET call announcement response, for a prior FES channel request, the GC shall abandon the prior FES request in favor of the new MET access request, terminate the call record with the reason set to "Glare" and send a call failure to the FES with the
25 cause set to "MET Busy". The GC shall proceed to process the MET "Access Request" as further described in this subsection.

30 If the MET state indicates the MET is engaged in a call-in-process, the reason is declared as an anomalous condition, the MET is sent a call failure message with "Network Busy" as the cause and the current call record is terminated with "Calling MET Busy - Anomaly" as the reason. The GC then immediately initiates a call
35 auditing action to resolve the anomalous condition existing for the prior call. This action will clear

the MET status and network resources so that subsequent service requests by the MET will be accommodated.

When a requesting MET is operational, and in the "MET Idle" call state, the GC collects additional dial digits as necessary, access the Control Group Customer Configuration data base and determine, based on the destination dial digits, whether the called destination is a MET user. If the destination is not identified in the Customer Configuration database as a MET user the GC declares the destination to be a terrestrial user. The GC accesses the operative Virtual Network Configuration database and performs the following Virtual Network service permission and address screening checks:

- a. The type of service requested (voice/2.4kbps data/4.8kbps data/fax/alternate voice-data) is supported by the Virtual Network.
- b. If the Virtual Network is configured with an explicit set of terrestrial user member telephone numbers, and the destination telephone number is included in the member list, then the call is permitted.
- c. Outgoing calls permitted.
- d. MET to terrestrial network calls permitted.
- e. International calls permitted.
- f. Calls to the specific destination NPA are permitted.

If the Virtual Network address screening and service permission checks pass, the GC accesses the Customer Configuration database using the RTIN and the destination dial digits, and perform the following MET address screening and service permission checks:

- a. The type of service requested (voice/2.4kbps data/4.8kbpsdata/fax/alternate voice-data) is authorized for the MET.

- b. Outgoing calls permitted.
- c. MET to terrestrial network calls permitted.
- d. International calls permitted.
- e. Calls to the specific destination NPA are permitted.
- f. If the MET is part of a VN group, the destination telephone number is a VN group member.

If all MET and Virtual Network address screening and service permission routing checks are successful, the GC updates the call record with the appropriate data and perform the call routing process. If a MET or Virtual Network address screening check or service permission check is unsuccessful, the GC terminates the call record upon finding the first check failure, and sends the MET a call failure message with the cause indicated as "Service not Subscribed". The call record encodes the specific failed check resulting in termination.

Terrestrial Network to MET Connection Requests

In processing terrestrial network originated call requests, the GC receives FES "Channel Request" messages, and transmits "Call Failure" messages. Terrestrial network access requests are preprocessed by the NOC Controller to identify the GC serving the called MET. Upon receiving a FES "Channel Request," the GC first evaluates the channel request message to determine whether this request is for the FES-to-destination MET connection of a MET to MET call.

If the request is not for a MET to MET connection, the GC accesses the MET Status Table, using access data provided by the NCC Controller, to verify the called MET is in the "Operational" state and whether the MET is currently engaged in a call-in-progress. If the MET is not in the "Operational" state, the GC terminates

the call record and sends a call failure message to the FES with the reason set to "Service not Available". If the MET is operational and the MET call state is any state other than idle, the GC terminates the call record and sends a call failure message to the FES with the cause set to "MET Destination Busy"

If the MET is operational and not currently engaged in an active call state, the GC accesses the MET Status Table and evaluates the access event history data for recent unsuccessful call announcements. If there have been a configurable number of unsuccessful call announcements within a configurable time limit, from the current time, the GC sends a call failure message to the FES with the reason set to "MET Destination Not Available". The call record is terminated with "Excess MET Pages" as the reason.

When the called MET is operational, not engaged in an active call state, and an acceptable number of unsuccessful call announcements have been placed to the MET, the GC accesses the operative Virtual Network Configuration database and perform Virtual Network address screening and service permission checks:

- a. The type of service indicated by the MET destination port (voice/2.4kbps data/4.8kbps data/fax/alternate voice-data) is permitted.
- b. Incoming calls permitted.
- c. Terrestrial network to MET calls permitted.
- d. International calls are permitted (if the calling number is provided - otherwise connection is permitted by default).
- e. The calling NPA is permitted (if NPA restrictions apply and the calling number is provided - otherwise connection is permitted by default).
- f. If the MET is part of a closed user group (CUG), and the origination telephone number is both provided and recognized as a CUG member, then the

call is permitted. If the calling number is not provided the connection is permitted by default.

5 If all MET and Virtual Network address screening and service permission routing checks are successful, the GC updates the call record with the appropriate data and perform the call routing process. If an MET or Virtual Network address screening and service permission routing check is unsuccessful, the GC terminates the call record upon finding the first check failure, and sends the FES a call failure message with the cause indicated as "Service not Subscribed". The call record encodes the specific failed check resulting in termination.

MET to MET Connection Requests for Originating MET

15 If the destination is identified by the dial digits as a MET user, the GC accesses the Customer Configuration database and determines if the destination MET is subscribed with membership in the Virtual Network being accessed by the origination MET. 20 If the origination and destination METs are members of the Virtual Network being accessed by the origination MET, the GC performs Virtual Network service permission and address screening checks for the destination MET using its Virtual Network Configuration databases.

25 After identifying the proper Virtual Network database(s) the GC accesses the MET Status Table and verify the destination MET is operational and not engaged in an active call state. If the destination MET is not operational the GC terminates the call record indicating "Destination MET not Available". 30 If the destination MET is in any call state other than idle, the GC terminates the call record indicating "Destination MET Busy", and the originating MET a call

failure message with the cause indicated as "Destination MET Busy".

If the destination MET is operational and idle, the GC sets a MET to MET call pending flag in the destination MET status entry of the MET Status Table, accesses the MET Virtual Network Configuration database(s) and performs the following Virtual Network address screening and service permission checks:

- a. The type of service requested (voice/2.4kbps data/4.8kbps data/fax/alternate voice-data) is supported by the origination and destination Virtual Networks.
- b. MET to MET calls permitted.
- c. Incoming calls permitted for the destination Virtual Network
- d. Outgoing calls permitted for the originating Virtual Network.
- e. Calls to any Virtual Network permitted by the origination Virtual Network.
- f. Calls to selected Virtual Networks permitted and the destination Virtual Network is in the permitted set.

If the Virtual Network service permission and address screening checks pass, the GC accesses the Customer Configuration database using the FTIN of the origination and destination METs and performs the following MET address screening and service permission checks for the originating MET:

- a. The type of service requested (voice/2.4kbps data/4.8kbps data/fax/alternate voice-data) is authorized for the MET.
- b. Outgoing calls permitted.
- c. MET to MET calls permitted.
- d. Calls to any Virtual Network permitted.

- e. Calls to selected Virtual Networks permitted and the destination Virtual Network is in the permitted set.

If the originating MET address screening and service permission checks pass, the GC performs the following MET address screening and service permission checks for the destination MET:

- a. The type of service requested (voice/2.4kbps data/4.8kbps data/fax/alternate voice-data) is authorized for the MET.
- b. Incoming calls permitted.
- c. MET to MET calls permitted.

If all MET and Virtual Network address screening and service permission routing checks are successful, the GC updates the call record with the appropriate data and performs the call routing process. If an MET or Virtual Network address screening check or service permission check is unsuccessful, the GC terminates the call record upon finding the first check failure, and sends the MET a call failure message with the cause indicated as "Service not Subscribed". The call record encodes the specific failed check resulting in termination.

MET to MET Connection Requests for Destination MET

Upon receiving a FES "Channel Request" that indicates a FES-to-destination MET connection is being requested for a MET to MET call, the GC generates a separate call record for the Destination MET using the "Call Identifier" previously assigned during the originating MET call setup and provided in the request message. The call record includes MET ID data needed to complete the connection to the destination MET. The GC proceeds to route the call.

Call Routing

When a GC successfully completes MET and Virtual Network address screening and service permission checks for access requests, the GC attempts to route the call using the routing rules and the Virtual Network Routing database. The routing process selects:

- a. The FES Terminal Equipment that will support a MET to terrestrial network call, or
- b. The FES Terminal Equipment and destination MET port that will support a MET to MET call, or
- c. The MET port that will support a terrestrial network to MET call.

The GC reports both MTS and MRS routing configurations. The GC accommodates, in any proportion, different routing rules for each member of a set of individual Virtual Networks and accommodates common routing rules for selected sets of one or more Virtual Networks.

MET to Terrestrial Connection Routing

To route a MET call to the terrestrial network, the GC accesses the Virtual Network Routing database and selects the FES Terminal Equipment based upon the destination dial digits. Each MTS Virtual Network Routing database is configured such that a variable number of the first n dial digits are processed to select the FES Gateway. The first n dial digits are comprised of the following:

- a. Domestic call or destination country code for international calls - [x] digits.
- b. The destination NPA - 3 digits.
- c. The local exchange within the NPA - 3 digits.

For MTS it is possible to associate each set of 'n' dial digits with an ordered set of FES Gateway entries. The FESs is arranged in the order of preference for routing. The number of FES Gateway entries ranges from 1 to 7.

Each MRS Virtual Network Routing database is configured such that a specific range of numbers in the associated private numbering plan are processed to select a FRS Base Station. The dial digit ranges
5 differentiate which FES base station is to be used. Each MRS dial digit number range is associated to an ordered set of FES base station entries. The FESs is arranged in the order of preference for routing. The number of numbering plan ranges are from 1 to 16 and
10 the number of FES Base Station entries range from 1 to 3.

Once the GC has identified the routing FES entry set, it accesses the FES Status Table and FES Resource Pool for the most preferred FES. It then determines
15 that FES's network availability and the availability of its communication and terrestrial interface resources to support the call. If the preferred FES is available to the network, the GC allocates communication and terrestrial interface resources from the pool for the
20 call being routed. FES resources are allocated based on the specific service type requested by the MET.

If the preferred FES is unavailable or the communication or terrestrial interface resources are insufficient to support the call, the GC accesses the
25 Customer Configuration and virtual Network Configuration databases to determine whether both the MET and Virtual Network are authorized for alternate FES routing or fixed FES routing. If fixed FES routing is required, the GC terminates the call record
30 indicating "FES not Available" and sends the MET a call failure message with the cause set to "Network Busy".

If the preferred FES is unavailable or communication or terrestrial interface resources are sufficient to support the call, and alternate FES
35 routing is authorized for both the MET and the Virtual Network, the GC sequentially repeats the procedure

above for each FES in the set, in descending order of routing preference, until an available FES is identified with sufficient resources to support the call.

5 When an available FES with sufficient communication and terrestrial interface resources is identified, either under alternate routing or fixed routing procedures, the GC proceeds to allocate satellite circuits to the call. The call record is updated to
10 show the FES selected and whether the alternate or fixed process was used. If alternate FES routing is authorized but an available FES with sufficient communication and terrestrial interface resources cannot be identified within the routing set, the GC
15 terminates the call record indicating "FES not Available or Insufficient FES Resources", as appropriate, and sends the MET a call failure message with the cause set to "Network Busy"

20 In the event the Virtual Network Routing Table does not include any routing entries for the 'n' dial digits included in the request message, the GC terminates the call record indicating "Routing not Provided" and sends the MET a call failure message with the cause set to "Service not Subscribed".

25 **Terrestrial to MET Connection Routing**

 To route a terrestrial network to MET call, the GC accesses the Customer Configuration database and identifies the MET port that is associated with the MET's destination telephone number received in the
30 channel access request message. The GC updates the FES Communication and Terrestrial Interface Status tables to reflect the resource allocation made by the calling FES prior to signaling the channel request for this call. The GC proceeds to allocate satellite circuits

to the call and updates the call record to show the destination MET port ID selected.

MET to MET Connection Routing for Originating MET

5 To route a MET call to another MET, the GC accesses the Virtual Network Routing database and selects an FES Terminal Equipment from an ordered set of FESs that have been designated to service MET to MET calls. Alternate routing is assumed automatically when more than 1 FES is included in the ordered set. The FESs are arranged in the order of preference for routing. 10 The number of FES entries ranges from 1 to 7.

Once the GC has identified the routing FES entry set, it accesses the FES Status Table for the most preferred FES, and determines the FES's network 15 availability and the availability of its communication and terrestrial interface resources to support the call. If the preferred FES is available to the network, the GC allocates MET to MET communication resources from the pool for the call being routed. FES 20 resources are allocatable based on the specific service type requested by the MET.

If the preferred FES is unavailable or communication resources are insufficient to support the call, the GC sequentially repeats the procedure above 25 for each FES in the set, in descending order of routing preference, until an available FES is identified with sufficient resources to support the call. When an available FES with sufficient communication resources is identified, the GC proceeds to allocate satellite 30 circuits for the originating MET connection. The call record is updated to show the FES selected. Subsequent FES processing generates a channel request for the FES-to-destination MET connection.

35 If an available FES with sufficient communication resources cannot be identified within the routing set,

the GC terminates the call record indicating "FES not Available or Insufficient FES Resources", as appropriate, and sends the MET a call failure message with the cause set to "Network Busy".

5 **MET to MET Connection Routing for Destination MET**

To route the FES-to-destination MET connection for a MET to MET call, the GC proceeds to allocate circuits for the destination MT connection as specified in the MET to MET Connection Routing for Originating MET
10 Section.

Satellite Trunk Circuit Management

Only when all MET and Virtual Network service permission and connectivity checks for an access request have passed and network routing facilities have
15 been determined available and reserved, the GC selects the required forward and return link trunk circuit frequencies and the FES forward link power level to service the call.

Each GC manages satellite trunk circuit resources using circuit pools. Channel center frequencies are identified in accordance with the separate L-Band and
20 Ku-Band conventions.

Circuit Allocation

The GC accesses the Customer Configuration database to determine the required circuit configuration for the
25 MET port which is being accessed by the call. The database indicates the bandwidth required for the forward and return links, the minimum MET frequency tuning increment, and the FES forward link power level
30 authorization. For MET to MET connections, the GC identifies forward and return link circuit configurations for both the originating MET and

destination MET and the following circuit and power allocation processing are performed for both METs.

5 The GC accesses the origination Virtual Network Configuration database to determine the connectivity period class authorized: demand period - free pool, demand period - reserved pool, or full period. The GC accesses the MET Status Table to identify the L-Band beam to which the MET is currently logged on. The GC then attempts to allocate the required circuit from the
10 proper frequency pool, based on connectivity class and L-Band beam requirement.

 The GC searches the pool to identify unused frequencies containing continuous spectrum sufficient to provide the MET channel bandwidth requirement. The
15 GC determines each resulting channel center frequency for inclusion in subsequent "Channel Assignment" messages. If the required circuits are available, the authorized forward link power level is retrieved from the Customer Configuration database for the associated
20 MET port and the FES nominal EIRP retrieves form the FES Configuration Table.

Satellite Trunked Circuit Queuing

 When queuing is enabled for MET originated calls, and the requested circuit pool bandwidth or power
25 resources are not immediately available, the GC accesses the Customer Configuration database to identify the MET priority associated with the Virtual network being accessed. The circuit request is then entered into the tail of the queuing system which is
30 structured with separate queuing sets for each L-Band beam being served by the GC. The individual queues within each L-band beam queue set is allocated to each MET priority level.

Call Setup Processing

When all MET and Virtual Network service permission and connectivity checks for an access request have passed, network routing facilities have been determined
5 available and satellite trunk circuits have been secured from the pool, the GC proceeds to the call setup procedure.

Off-Line NCC Virtual Network Updating

Each GC updates its counterpart GC in the Off-line
10 NCC upon each transition of a MET call into the "MET Busy - Call in Progress" state or the MET Operational and Idle" state. Other state transitions are not reported to the Off-line NCCTE GC. Each Virtual Network update includes all call record, MET Status
15 Table, Circuit Pool Status Table, FES Communication and Terrestrial Interface Pool data sets for the call being updated. The Off-line counterpart GC utilizes update reports to modify its associated tables and call records to reflect concurrency with the On-line GC.
20 Upon NOC command to assume the On-line NCC role, the GC commences Virtual network management using the call and resource states at the time of switchover.

The many features and advantages of the invention are apparent from the detailed specification,
25 and thus, it is intended by the appended claims to cover all such features and advantages of the invention which fall within the true spirit and scope of the invention. Further, since numerous modifications and variations will readily occur to those skilled in the art, it is not desired to limit the invention to the
30 exact construction and operation illustrated and described, and accordingly, all suitable modifications and equivalents may be resorted to, falling within the scope of the invention.

DICTIONARY ITEMS AND DEFINITIONS**Actual GSI**

Definition: Current GSI based on TDM changes during MET operation. This field is populated by the NOC based on actions on the CGS. The CMIS cannot create or update this field.

Call Barring Inbound/Outbound Flag

Definition: Describes the call barring entry as applying to incoming or outgoing calls. If the Call Barring List is flagged as Inbound, it applies to calls the MET is receiving. If the Call Barring List is flagged as Outbound, it applies to calls the MET is making.

Call Barring Include/Exclude Flag

Definition: Describes the call barring entry as an included (legal) call or an excluded (illegal) call. When a Call Barring List is flagged as Include, the MET may only make calls to the numbers or NPAs on the list. Any other call would be denied. Conversely, if a Call Barring List is flagged as Exclude, the MET may make calls to any number or NPA except those on the list.

Call Barring List Value

Definition: Numbering plan area or phone number in the call barring list. The values that appear in the list are the phone numbers or NPAs that the MET's restriction apply to. The types of restrictions are dictated by the flags for Include/Exclude and Inbound/Outbound Call Barring.

Call Trap Flag

Definition: Indicates call trapping has been initiated for the MET. The GC will trap MET states as they change during MET CGS activity.
5 This information will be provided to the CMIS on a call record.

Call Type

Definition: Service available on the MET. There are four service types: voice data (2400 or
10 4800 baud), fax, and alternate voice data (avd). For each service the mobile is registered, a service record is created with a single call type indicated. This call type in turn has a unique mobile
15 identification number (min) associated with it.

Carrier

Definition: Name of preferred IXC carrier. This field is a switch field used to support equal
20 access to long distance carriers.

Cellular ESN

Definition: 32 bit ESN that is used by the switch. For dual mode cellular/satellite phones it is the ESN for the cellular portion of the
25 phone and would match the ESN used by the home cellular carrier to identify that mobile terminal.

CGS Time Stamp

Definition: Time stamp was created/modified. Part of
30 the notification of success or failure of CGS action. Not created or updated by CMIS.

Channel Spacing

Definition: Multiple of frequency step size. This
35 element is a characteristic of the MET Class. CMIS will only have the MET Class

ID that a particular METs equipment maps to. NE originates this and other data that describes the MET Class and sends it to the NOC.

5 **Check String**

Definition: Constant used by the GC to validate the encryption/decryption algorithm. This element is related to the ASK.

10 **Commanded GSI**

Definition: Set by CMIS this is the original GSI stored as a NVRAM (non-volatile RAM) parameter by the MET. Required for each new MET registered for service. This element is used by the MET to tune to a GC-S channel during commissioning on the CGS. Without the GSI the MET is incapable of logging on to the CGS.

15 **Configuration File**

Definition: A file containing the contents of a working configuration that has been saved to disk under a unique name.

20 **Current Configuration**

Definition: The set of resources that exist in the configuration most recently sent to or received from the NOC. This is assumed to be the actual configuration of the traffic bearing network at any given time.

25 **Commit a Resource**

Definition: Explicit engineer action to add a fully provisioned interim resource to the working configuration.

30 **Control Group ID**

Definition: The CGS is divided into Control Groups that contain circuit pools, signaling channels, bulletin boards, METs, and VNs. A MET may

only belong to one Control Group. The control Group assignment is based on the virtual network membership. All VNs a MET is a member of must be in the same control group.

Cust Group

Definition: Identifier for a specialized routing information used at the switch (e.g., 1024 available cust groups per MSR). Dialing plans will be implemented for groups of customers through a Customer Group (Cust Group).

Data Hub Id

Definition: Used to route messages during PSTN to IVDM call setup to the proper data hub. This is only applicable for METs that are participating in the Mobile Packet Data Service.

Date Last Tested

Definition: Time stamp of most recent commissioning test. This field is populated by the NOC and cannot be created or updated by CMIS.

Default VN

Definition: VN selected if user does not specify VN during dialing. For METs that belong to only one VN, this can be populated with the VN ID the MET is assigned to by default.

EIRP

Definition: Equivalent Isotropic Radiated Power - power level required for a MET to receive a satellite signal. This element is a characteristic of the MET Class. CMIS will only have the MET Class ID that a particular METs equipment maps to. NE/SE originates this and other data that

describes the MET Class and sends it to the NOC.

Event Argument Id

5 Definition: Part of the Event Record received from the NOC. CMIS has no part in creating or updating events-they arrive unsolicited from the NOC.

Event Argument Type

10 Definition: Part of the event Record received from the NOC. CMIS has no part in creating or updating events-they arrive unsolicited from the NOC.

Event Argument Value

15 Definition: Part of the Event Record received from the NOC. CMIS has no part in creating or updating events-they arrive unsolicited from the NOC.

Event Argument VMS Type

20 Definition: Part of the Event Record received from the NOC. CMIS has no part in creating or updating events-they arrive unsolicited from the NOC.

Event Code

25 Definition: Part of the Event Record received from the NOC. CMIS has no part in creating or updating events-they arrive unsolicited from the NOC.

Event Severity

30 Definition: Network impact assessment of the trouble event.

Event Time

Definition: Time the event occurred within the network.

Event Type

35 Definition: Part of the Event Record received from the NOC. CMIS has no part in creating or

updating events-they arrive unsolicited
from the NOC.

External Date Time Stamp

Definition: CMIS generated time stamp used for CMIS
audit purposes in exchanging messages with
the CGS.

External Transaction Id

Definition: CMIS generated transaction id used for CMIS
audit purposes in exchanging messages with
the CGS.

Feature Set

Definition: Identifies MET features within a specific
VN. Fixed features are set up during order
processing and require no action by the MET
user to invoke a feature. MET activated
features must also be set up during order
processing but will only be available
through some action on the part of the MET
use during call process.

FIXED FEATURES include:

- * Calling Line Id Presentation (CLIP) -
display the calling party's number to a MET.
- * Calling Line Id Restriction (CLIR) -
prohibition from displaying the METs number when it
is calling another party.
- * Connected Line Id Presentation (COLP) -
display the number the calling MET is connected to.
- * Connected Line Id Restriction (COLR) -
prohibit display of the connected MET's number to
the calling party.
- * Sub-addressing (SA) - allows one or more
attachments to the MET to be addressed. This is
being accomplished through unique phone numbers for
service types requiring different equipment.

* Call Waiting (CW) - notification to a MET engaged in the call that another call is waiting. MET may accept the other call or ignore it.

5 * Call Barring (CB) - restricts the MET user's from making or receiving one or more types of calls.

 * Operator intervention (OI) - allows an operator to break into a call in progress for the MET.

10 * Operator Assistance (OA) - allows the MET to access an MSAT operator to receive assistance

 * Call Priority (CP) - used in conjunction with the system's call queuing function (trunk access priority) presence of this feature gives a
15 MET access to channels at times of congestion ahead of MET's with lower priority. Priority applies only to MET initiated calls.

MET ACTIVATED (dynamic) FEATURES include:

20 * Call Transfer (CT) - allows a MET user to transfer an established call to a third party.

 * Call Forwarding Unconditional (CFU) - permits a MET to have all calls forwarded to another MET or PSTN number.

25 * Call Forwarding Busy (CFB) - permits a MET to have all incoming calls attempted when the MET is busy to another MET or PSTN number.

30 * Call Forward Congestion (CFC) - permits the MET to have all incoming calls attempted when the signaling channels are congested answered with a recorded announcement intercept.

 * Call Forward No Reply (CFN) - permits a MET to have all incoming calls attempted when the MET is not answering to another MET or PSTN number. This applies if the MET is blocked, turned off or
35 not answering.

* Call Holding (CH) - allows a MET to interrupt call communication on an existing connection and then re-establish communications.

* Alternate Voice Data Operation (AVD) - allows a MET user to toggle between voice and data mode during a call. Requires that the call be initiated in voice mode. Only the MET user may toggle between voice and data. This requires a special service type in addition to the activation at set-up of the feature.

* Conference calling (CC) - allows a MET to communicate with multiple-parties including METs and PSTN concurrently.

* Three Party Service (3PS) - allows a MET to who is active on a call to hold that call, make an additional call to a third party, switch from one call to the other (privacy being provided between the calls) and/or release one call and return to the other.

* Malicious Call Trace (MCT) - enables an MSAT operator to retrieve the complete call record at a MET's request for any terminated call in real-time. The operator can then identify the calling party to the MET and take appropriate action.

* Voice Mail (VM) - allows call forwarding to a voice mail box and retrieved of messages by the MET.

* Alternate Accounts Charging (ACC) - allows the MET user to enter in an account code to charge the call to after entering the dialed digits

Fully Provision

Definition: Supply values to all attributes of a resource

Frequency Step Size

Definition: Minimum tuning increment acquired for a MET to tune in an assigned channel. CMIS will only have the MET Class ID that a particular MET's equipment maps to. NE originates this and other data that describes the MET Class and sends it to the NOC.

From MET Call Barring Flags

Definition: Describe actions available to a user originating a call from a MET. These call Barring flags relate to specific types of calls at an aggregate level to indicate if the MET can make or receive a call of a particular type. When this list indicates that an Inclusion or Exclusion to particular numbers or area codes is allowed, the values for those restrictions are indicated on a Call Barring List.

FTIN

Definition: Forward Terminal Identification Number - Downloaded to MET from NOC during commissioning. Used for MET to GC signaling.

Internal Data Time Stamp

Definition: NOC generated time stamp used for NOC audit purposes.

Internal Transaction Id

Definition: NOC generated transaction is used for NOC audit purposes.

Interim resource

Definition: The resource currently being modified by the engineer. Changes made to an interim resource are not added to the working configuration until the resource is committed to the working configuration

L Band Beam

Definition: Current beam MET is logged into.

Determined by the GC during commissioning.

CMIS has no role in creating or updating
this field.

LCC

Definition: Line Class Code - type of phone, required
by the switch.

MCC Class Id

Definition: Part of the Event Record received from the
NOC. CMIS has no part in creating or
updating events - they arrive unsolicited
from the NOC.

MCC Instance

Definition: Part of the Event Record received from the
NOC. CMIS has no part in creating or
updating events - they arrive unsolicited
from the NOC.

MCC Instance Id

Definition: Part of the Event Record received from the
NOC. CMIS has no part in creating or
updating events - they arrive unsolicited
from the NOC.

MCC Instance Type

Definition: Part of the Event Record received from the
NOC. CMIS has no part in creating or
updating events - they arrive unsolicited
from the NOC.

Message Status 1

Definition: Used in the message initiated by the NOC to
acknowledge success or failure of a
previously transmitted CMIS request. Used
by the DM.

Message Status 2

Definition: Used in the message initiated by the NOC to
acknowledge success or failure of a

previously transmitted CMIS request. Will be used by the DM.

Message Verb

Definition: Action required at the NOC on data passed in a message from CMIS. This field is in the message relaying the results of a CMIS request.

Modulation Scheme

Definition: Non-standard modulation schemes. CMIS will only have the MET Class ID that a particular MET's equipment maps to. NE/SE originates this and other data that describes the MET Class and sends it to the NOC.

MSA

Definition: Mobile Servicing Area - identifies the last call's servicing area. Atomic data element within MSR. Transient data maintained in call processing not on the cellular switch table. Same as MSR.

MSR

Definition: Mobile Servicing Region id (table) contains multiple MSA assignments for the MET. For a roamer, the operator will input the MSR for temporary assignment. Allows up to 1024 cust groups - At CGS startup there will be 1 MSR.

MET ASK

Definition: Access Key MET must match during call setup/validation.

MET Class ID

Definition: Identifies the operating characteristics of the MET. Associated to MET by CMIS during registration from data supplied by NE/SE. The technical characteristics the MET Class ID encompasses are not needed by CMIS.

These are stored on a table in the NOC and referenced by having the ID on the MET Information record. This ID applies to MET level regardless of how many services, etc. the MET has tied to it.

MET Commanded State

Definition: Current CGS status of MET.

MET Fraud Flag

Definition: Indicates fraud has been detected on the MET. Updated by GC and CMIS only. This field is set at the MET level regardless of the number of services, etc. the MET has.

MET ID

Definition: CMIS assigned unique MET identifier. This can be a unique random number assigned to each MET registered for service. This is a MET level characteristic set once for the MET regardless of how many services, etc. the MET has. The MET ID is used by the NOC to identify METs. It does not have to be used within CMIS as a key field. MET ID cannot be updated once it has been assigned. A MET that requires a new MET ID for any reason would have to go through the registration process anew.

MET Signaling Code

Definition: Dialed digits from MET that identifies VN selection. Signaling codes would be assigned when a MET has multiple Virtual Network memberships. After the MET user enters the destination phone number, the pound key is hit and then the signaling code is entered if the caller wants to associated the outbound call with a particular virtual network. When no

signaling code is entered, implies default
VN be associated with the call.

Pending NVRAM Init Flag

Definition: Instructs the GC to download/initialize
parameters for a MET.

Pending PVT Flag

Definition: This flag indicates that a PVT is required
following next MET access. If CMIS
requests a PVT to help diagnose customer
troubles, an update would be sent to NOC
with the Flag set to Perform PVT after Next
MET access (1).

Picssel

Definition: Flag indicating if user has asked for a
preferred IXC carrier. Carrier name is
contained in CARRIER field.

Record Type

Definition: Type of record defined by object. Part of
the Update Results Record.

Remote

Definition: Remote user - not required by the switch
for MSAT Application.

Recent Configuration Event

Definition: This is a serial list of events received
from the NOC that pertain to configuration
database changes.

Referential Integrity

Definition: Database "key field" relationships that
bind record within the databases, and
create dependencies for additions and
deletions of table instances.

RF Pin

Definition: Remote feature personal identification
number. A user is prompted for a pin when
attempting to use a remote feature.

Roam

Definition: Roam Capable - not required by the switch for MSAT Application.

RTIN

5 Definition: Reverse Terminal Identification Number
which is also the satellite electronic
serial number on satellite only and dual
mode cellular/satellite METs. This is a
unique identifier assigned by manufacturer
10 for each piece of equipment. Within CGS
processing the RTIN is used by the GC to
signal the MET.

Satellite Id

15 Definition: Satellite Id of current L-band beam. The
NOC populates this field based on MET
commissioning. CMIS does not ever create
or update this field.

SCM

Definition: Station Class Mark.

20 Secure Disable Flat

Definition: Channel Unit security check flag. Setting
this flag to bypass security would disable
ASK verification during call processing for
a MET. CMIS cannot change this flag.

25 Signaling Priority

Definition: Number of MET signaling requests to the GC
during network congestion. Assigned at the
MET level - each MET may have only one
signaling priority regardless of the number
30 of VN memberships it has. The highest
priority level is 0 and the lowest is
seven.

TDM Change Enable Flat

35 Definition: Restriction on MET from changing TDM (TDM
is the GSI)

Telephone Number

Definition: Phone number associated with a call type (voice, data, fax, avd) in a given virtual network.

5 **Template**

Definition: An initial set of default attribute values for each resource being added.

To MET Call Barring Flags

10 Definition: Describes actions available to a user receiving a call at their MET.

Trunk Access Priority

Definition: Satellite trunk queuing priority used during network congestion. Determines access to channels.

15 **Virtual Network Id**

Definition: Identifies the Virtual Network that the service and feature profiles relate to. Within a single VN a MET may have one voice, data, fax and/or avd service type. Features and restrictions for those services are defined on the basis of the METs membership in that VN. If the MET required an additional instance of a service that it already subscribed to, 20 (e.g. a second voice number), a second virtual network assignment would be required. Features and restrictions for that second membership can be defined with no relation to the existing VN membership, 25 but all elements that relate to the MET level cannot change without a ripple effect to the other services. 30

VMS Instance Type

Definition: Part of the Event Message

Vocoder Id

Definition: Vocoder version currently installed in the MET. CMIS will only have the MET Class ID that a particular METs equipment maps to. NE/SE originates this and other data that describes the MET Class and sends it to the NOC.

Working Configuration

Definition: The set of resources currently being modified by the engineer. This may be an existing, complete configuration which the engineer is modifying, or may be a new, partial (or initially empty) configuration.

GLOSSARY

	A	Availability
	AAC	Airline Administrative Communications
	AARM	Access Authentication Request
5	ABH	Average Busy Hour
	AC	Alternating Current
	ACU	Access Channel Unit
	ACU	Antenna Control Unit
	AD	Attribute Dictionary
10	AEDC	After Effective Date of Contract
	AFC	Automatic Frequency Control
	AFS	Antenna/Front-end Subsystem
	AGC	Automatic Gain Control
	AIOD	Automatic Number Identification Outward Dialing
15	AMI	Alternative Mark Inversion
	AMPS	North American Analog and Digital Cellular Networks
	AMSC	American Mobile Satellite Corporation
	AMS(R)S	Aeronautical Mobile Satellite (Route) Service
20	AMSS(R)	Aeronautical Mobile Satellite Services (Reserved)
	ANI	Automatic Number Identification
	ANSI	American National Standards Institute
	ANT	Antenna
25	AOC	Aircraft Operational Communications
	APC	Airline Passenger Communications
	API	Applications Program Interface
	AR	Automatic Roaming
	ARC	Atlantic Research Corporation
30	ASK	Access Security Key
	ASN.1	Abstract Syntax Notation One
	AT	Command set for a DTE to communicate with asynchronous host
	ATC	Air Traffic Control
35	AVD	Alternate Voice/Data Calls
	AWGN	Additive White Gaussian Noise

	AZ	Azimuth
	B8ZS	Bipolar with 8 Zeros Substitution
	BB	Bulletin Board
	BBS	Bulletin Board Service
5	BER	Bit Error Rate
	BERT	Bit Error Rate Tester
	BID	Beam Identifier Code
	BIT	Built In Test
	BITE	Built-In Test Equipment
10	BPS	Bits Per Second
	BS	Base Station
	BSPU	Baseband Signaling Processing Unit
	BSS	Base Station Switch
	C/No	Carrier to Noise Power Density Ratio
15	CAC	Channel Access and Control
	CAF	Call Failure Message
	CCCS	Command, Control, and Communications Subsystem
	CCIR	Consultative Committee International de Radio
20	CCITT	Consultative Committee International Telegraph and Telephone
	CCU	Communications Channel Unit
	CD	Call Delivery
	CDR	Call Detail Record
	CDR	Critical Design Review
25	CDRL	Contract Data Requirements List
	CE	Common Equipment
	CG	Control Group
	CGID	Control Group Identification Number
	CGS	Communications Ground Segment
30	CHA	Channel Assignment Message
	CHREL	Channel Release Message
	CHREQ	Channel Request Message
	CI	Configuration Item
	CIBER	Cellular Intercarrier Billing Exchange Roamer

	CIC	Carrier Identification Code
	CM	Configuration Management
	CMIP	Common Management Information System
	CMIS	Configuration Management Information System
5	CMIS	Customer Management Information System
	COTS	Commercial off-the-Shelf
	CP	Circuit Pool
	CPD	Call Processing Demonstration
	CPS	Circuit Pool Segment
10	CPU	Central Processing Unit
	C/PV	Commissioning/Performance Verification
	CRC	Cyclic Redundancy Check
	CS	Communications System
	CSC	Computer Software Component
15	CSCI	Computer Software Configuration Item
	CSDT	Channel Switchover Detection Time
	CSF	Critical System Functionality
	CSMA/CD	Carrier Sense Multiple Access with Collision Detection
20	CSMP	Circuit Switch Management Processor
	CSMPCS	Circuit Switch Management Data Processor Equipment Communications System
	CSPU	Channel Signal Processing Unit
	CSR	CAC Statistics Request
25	CSREP	Call Status Reply Message
	CSREQ	Call Status Request Message
	CSU	Computer Software Unit
	CSUG	Computer Software Unit Group
	CTB	Customer Test Bed
30	CTN	Cellular Telephone Network
	CTN	Cellular Terrestrial Network
	CTNI	Cellular Telephone Network Interface
	CU	Channel Unit
	CUD	Call User Data
35	CUG	Closed User Group
	CUP	Channel Unit Pool

	CUS	Channel Unit Subsystem
	CVR	Cellular Visitor Registration
	CVRACK	Cellular Visitor Registration Acknowledge
	CW	Carrier Wave
5	CWCHA	Call Waiting Channel Assignment Message
	DAMA	Demand Assignment Multiple Access
	db	Database
	dbc	Decibel Relative to Carrier
	dB	decibels
10	dB _i	dB Relative to Isotropic
	dB _m	dB relative to 1 milli watt
	dBW	decibels relative to 1 watt
	D bit	'Data Configuration' bit in X.25
	DBMS	DataBase Management System
15	dB _w	dB Relative to 1 Watt
	DC	Direct Current
	DCE	Data Circuit Terminating Equipment
	DCE	Data Communications Equipment
	DCL	Digital Command Language
20	DCN	Down CoNverter
	DCR#	Document Control Release #
	DCU	Data Channel Unit
	DD	Design Document
	DDCMP	Digital Data Communications Message Protocol
25	DDS	Direct Digital Synthesis
	DEC	Digital Equipment Corporation
	DECmcc	Digital's Network Management System
	DEQPSK	Differential Encoded Quadrature Phase Shift
	Keying	
30	DET	Data Equipment Terminal
	DFD	Data Flow Diagram
	DH	Data Hub
	DH-D	Outbound Time Division Multiplex Channel from Data Hub to Mobile Terminal
35	DHP	Data Hub Processor

	DHSI	DH-D Selector Identification Code
	DID	Direct Inward Dialing
	DIDs	Data Item Descriptions
	DME	Dial-Up Modem Emulation
5	DMQ	DEC Message Queue
	DMS	Digital Multiplex System
	DN	Directory Number
	DNS	Digital Name Service
	DOC	Canadian Department Of Communications
10	DOD	Direct Outward Dialing
	DPSK	Differential Phase Shift Keying
	DQPSK	Differentially Encoded Quadrature Phase Shift Keying
15	DS0	Digital Service Level Zero (single 64K b/s channel)
	DS 1	Digital Service Level One (twenty four voice channels)
	DSP	Digital Signal Processing
	DSSS 1	Digital Subscriber Signaling System 1
20	DTC	Digital Trunk Controller
	DTE	Data Terminal Equipment
	DTE	Data Terminal Element
	DTMF	Dual Tone Multiple Frequency
	DVSI	Digital Voice Systems, Inc.
25	Eb/No	Bit Energy to Noise Power Density Ratio
	ECN	Engineering Change Notice
	EFD	EF Data, Inc.
	EFTIN	Encrypted Forward Terminal Identification Number
30	E-I	Exchange - Interexchange
	EIA	Electronic Industries Association
	EICD	Element Interface Control Document
	EIE	External Interface Equipment
	EIRP	Equivalent Isotropic Radiated Power
35	E1	Elevation

	EMC	ElectroMagnetic Compatibility
	EMI	ElectroMagnetic Interference
	eng	engineer or engineering
	EO	End Office
5	EO	External Organizations
	EOD	End of Data
	ESN	Electronic Serial Number
	FAX	Facsimile
	FCA	Functional Configuration Audit
10	FCC	Federal Communications Commission
	FCS	Fading Channel Simulator
	FDMA	Frequency Division Multiple Access
	FEC	Forward Error Correction
	FES	Feederlink Earth Station
15	FES-C	Inbound Communication channel from Feederlink Earth Station to Mobile Terminal
	FES-I	Interstation signaling channel from Feederlink Earth Station to Group Controller
	FES/MT	Feederlink Earth Station/Mobile Terminal
20	FES-RE	Feederlink Earth Station-Radio Frequency Equipment
	FES-TE	Feederlink Earth Station Terminal Equipment
	FFT	Fast Fourier Transform
	FIS	Feederlink Earth Station Interface Simulator
25	FIT	Fault Isolation Tests
	FIU	Fax Interface Unit
	FMT	Fixed Mobile Terminal
	FMA	Field Programmable Gate Array
	FPMH	Failures per Million Hours
30	FRO	Frequency Reference Oscillator
	FT	Fault Tolerant
	FTE	Fax Terminal Equipment
	FTIN	Forward Terminal Identification Number
	G/T	Gain to System Noise Ratio

	GBF	Gateway/Base Function
	GBS	Gateway Base System
	GC	Group Controller
5	GC-I	Interstation signaling channel from Group Controller to Feederlink Earth Station
	GC-S	Time Division Multiplex Signaling channel from Group Controller to Mobile Terminal
	GCSST	GC-S Search Time
	GEN	Generator
10	GHz	Giga (1,000,000,000) Hertz (cycles per second)
	GMACS	Graphical Monitor And Control System
	GPIB	General Purpose Instrument Bus
	GPS	Global Positioning System
	GS	Gateway Station
15	GSI	GC-S Selector Identifier
	GW	Gateway
	GWS	Gateway Switch
	GWS/BSS	Gateway Switch/Base Station Switch
	H/W	Hardware
20	HCHREQ	Handoff Channel Request
	HDP	Hardware Development Plan
	HLR	Home Location Register
	HMI	Human Machine Interface
	HOT	Hand-off Test
25	HPA	High Power Amplifier
	HRS	Hardware Requirements Specification
	HWCI	Hardware Configuration Item
	HW/SW	Hardware/Software
	Hz	Hertz
30	I	In Phase channel
	IAW	In Accordance With
	IC	Interexchange Carrier
	ICD	Interface Control Document
	ICI	Instrument Control Interface

	ICP	Intelligent Cellular Peripheral
	ICU	Interstation Channel Unit
	ICWG	Interface Control Working Group/Interface Coordination Working Group
5	ID	Identification
	IEEE	Institute of Electrical and Electronics Engineers
	IF	Intermediate Frequency
	IFIS	Intermediate Frequency Subsystem
10	IFL	Interfacility Link
	IF IFL	Intermediate Frequency Internal Facility Link
	IHO	Interstation Hand-Off
	IICD	Internal Interface Control Document
	IICWG	Internal Interface Control Working Group
15	IM	Intermodulation
	IMBE	Improved Multiband Excitation
	IOC	Input/Output Controller
	IP	Internet Protocol
	ISCU	Interstation Signaling Channel
20		Unit/Interstation Channel Unit
	ISDN	Integrated Services Digital Network
	ISL	Interstation Signaling Link
	ISO	International Standards Organization
	IVDCPD	Integrated Voice & Data Call Processing
25		Demonstration
	IVDM	Integrated Voice/Data Mobile Terminal
	KBPS	Kilo (1,000) Bits per Second
	KHz	Kilohertz
	KLNA	K-band Low Noise Amplifier
30	KP	Key Pulse
	LAN	Local Area Network
	LAP	Link Access Procedure
	LAPB	Link Access Procedure using a balanced mode of operation

	LATA	Local Access and Transport Area
	LBP	Local Blocking Probability
	LCN	Logical Channel Number
	LLCSC	Lower Level Computer Software Component
5	LLNA	L-band Low Noise Amplifier
	LLS	Lower Level Specification
	LNA	Low Noise Amplifier
	LOI	Level of Integration
	LPP	Link Peripheral Processor
10	LRU	Line Replaceable Unit
	LRU	Lowest Replaceable Unit
	LSSGR	Local Access and Transport Area Switching Systems Generic Requirements
	MAP	Maintenance Administrative Position
15	MAP	Mobile Application Part
	M bit	'More Data' bit in X.25
	M&C	Monitor and Control
	MCC	Management Control Center
	MCGID	Mobile Data Service Control Group
20		Identification Number
	MDLP	Mobile Data Service Data Link Protocol
	MDS	Mobile Data Service
	MDSR	MDLP Statistics Request
	MEA	Failure Modes and Effects Analysis
25	MEF	Minimum Essential Functionality
	MELCO	Mitsubishi Electronic Company
	MET	Mobile Earth Terminal (a.k.a. MT)
	MET-C	Communication Channel Between Mobile Terminal and Feederlink Earth Station
30	MET-DRd	Inbound Slotted Aloha Data Channel
	MET-DRr	Inbound Slotted Aloha Reservation Channel
	MET-DT	Inbound Packet Time Division Multiple Access Channel
35	MET-SR	Random Access Signaling Channel from Mobile Terminal to Group Controller

	MET-ST	Time Division Multiple Access signaling channel from Mobile Terminal to Group Controller
	MF	Multiple Frequency
	MFID	Manufacturer Identification
5	MGSP	Mobile Terminal to Group Controller Signaling Protocol
	MHz	Mega Hertz (cycles per second)
	MIB	Management Information Base
	MIR	Management Information Region
10	MIRQ	MT Initialization Request
	MIS	Mobile Terminal Interface Simulator
	MIS	Mobile Earth Terminal Interface Simulator
	ML	Message Layer
	MLCSC	Mid Level Computer Software Component
15	MLP	Multilink Procedure
	MMI	Man Machine Interface
	MMRS	Mobile Road Service
	MMSS	Maritime Mobile Satellite Services
20	MNMS	Mobile Data Service Network Management Subsystem
	MNP	Multi Network Protocol
	MODEM	MODulator/DEModulator
	MOS	Mean Opinion Score
	MOV	Method of Verification
25	MPLP	Mobile Data Service Packet Layer Protocol
	MPR	MPR Teltech Inc.
	MRI	Minimum Request Interval
	MRS	Mobile Radio Service
	MSAT	Mobile Satellite
30	MSC	Mobile Switching Center
	MSS	Mobile Satellite Service
	MSSP	Mobile Terminal Specialized Services Protocol
	ms	millisecond
	MT	Mobile Terminal
35	MT-C	Communication Channel Between Mobile Terminal and Feederlink Earth Station

	MT-DRd	Inbound Slotted Aloha Data Channel
	MT-DRr	Inbound Slotted Aloha Reservation Channel
	MT-DT	Inbound Packet Time Division Multiple Access Channel
5	MT ASK	Mobile Terminal Access Security Key
	MTBF	Mean-Time Between Failures
	MTBRA	Mean-Time Between Restoral Actions
	MTCRS	Mobile Telephone Cellular Roaming Service
	MT-MET	Mobile Terminal to Mobile Terminal
10	MT-MT	Mobile Terminal to Mobile Terminal
	MTP	Mobile Data Service Transaction Protocol
	MT-PSTN	Mobile Terminal/Public Switched Telephone Network
	MTS	Mobile Telephone Service
15	MT-SR	Random Access Signaling Channel from Mobile Terminal to Group Controller
	MTSR	MTP Statistics Request
	MT-ST	Time Division Multiple Access Signaling Channel from Mobile Terminal to Group Controller
20	MTTR	Mean-Time to Repair
	MTX	Mobile Telephone Exchange
	MULP	Mobile Data Service Unacknowledged Link Protocol
	MUSR	MULP Statistics Request
25	NACN	North American Cellular Network
	NADP	North American Dialing Plan
	NANP	North American Numbering Plan
	NAP	Network Access Processor
	NAP-C	Network Access Processor for the Communications Channel
30	NAP-CU	Network Access Processor-Channel Unit
	NAP-D	Network Access Processor for the Data Channel
	NAP-N	Network Access Processor for the Network Radio Channel

	NAP-S	Network Access Processor for the Signaling Channel
	NAS	Network Access Subsystem
	NASP	National Aerospace Plan
5	NCC	Network Communications Controller
	NCC	Network Control Center
	NCC-RE	Network Communications Controller Radio frequency Equipment
10	NCC-TE	Network Communications Controller Terminal Equipment
	NCS	Network Control System
	NE	Network Engineering
	NEBS	New Equipment Building System
	NE/SE	Network Engineering/System Engineering
15	NIM	Network Module
	NM	Network Module
	NMP	Network Management Process
	NMS	Network Management System
20	NMS/CMIS	Network Management System/Customer Management Information System
	NOC	Network Operations Center
	NOC-FES	Network Operations Center-Feederlink Earth Station
	NPA	Numbering Plan Area
25	NRZ	Non-Return to Zero
	NT	Northern Telecom
	NTL	Northern Telecom Limited
	NTP	Northern Telecom Practice
	NVM	Non-Volatile Memory
30	OA&M	Operation, Administration, and Maintenance
	O&M	Operations and Maintenance
	OJJ	On the Job Training
	OM	Operational Measurements (from GWS)
	OS	Operating System
35	OSF	Open Software Foundation

	OSI	Open Systems Interconnection
	OSR	Operational Support Review
	PA	Product Assurance
	PAC	Pre-emption Acknowledge Message
5	PAD	Packet Assembler/Disassembler
	PAP	Product Assurance Plan
	PBX	Private Branch Exchange
	PC	Process Control
	PCM	Pulse Code Modulation
10	PC-RFMCP	PC Based RFM Control Processor
	PC-SCP	PC Based Systems Control Processor
	PCSTR	Physical Channel Statistics Request
	PCT	Provisioning Criteria Table
	PCU	Pilot Control Unit
15	PCU	Pilot Channel Unit
	PDAMA	Priority Demand Assignment Multiple Access
	PDN	Packet Data Network
	PDR	Preliminary Design Review
	PDU	Protocol Data Unit
20	PE	Protocol Extension
	PER	Packet Error Rate
	PERSP	Packet Error Rate Sample Period
	PERT	Packet Error Rate Threshold
	PIP	Program Implementation Plan
25	PLP	Packet Layer Protocol
	PLT	Pilot
	PMR	Project Management Review
	PMT	Pre-emption Message
	PN	Private Network
30	PN	Pseudo Noise
	PNIC	Private Network Identification Code
	PPM	Pulses per Minute
	PS	Processor Subsystem
	PSDN	Private Switched Data Network
35	PSDN	Public Switched Data Network

	PSTN	Public Switched Telephone Network
	PTT	Push-To-Talk
	PVC	Performance Virtual Circuit
	PVT	Permanent Verification Test/Performance
5		Verification Test
	Q	Quadrature Phased Channel
	QA	Quality Assurance
	Q bit	'Qualified Data' bit in X.25
	QPSK	Quadrature Phase Shift Keying
10	RAM	Random Access Memory
	RAM	Reliability, Availability, Maintainability
	RDB	Relational DataBase
	REMS	Remote Environmental Monitoring System
	Req	Requirement
15	Rev	Revision
	RF	Radio Frequency
	RFE	Radio Frequency Equipment
	RF IFL	Radio Frequency Inter Facility Link
	RFM	Radio Frequency Monitor
20	RFP	Request For Proposal
	RFS	Radio Frequency Subsystem
	RHCP	Right Hand Circularly Polarized
	RMS	Remote Monitoring Station
	RMS	Remote Monitor Subsystem
25	RNO	Remote NOC Operator
	ROM	Read Only Memory
	RR	Receiver Ready
	RS	Requirements Specification
	RS-232C	Electronics Industry Standard for unbalanced
30		data circuits
	RSP	Radio Standard Procedure
	RTIN	Reverse Terminal Identification Number
	RTM	Requirements Traceability Matrix
	RTP	Reliable Transaction Protocol

	RTR	Reliable Transaction Router
	RTS	Reliable Transaction Service
	RTS	Receiver/Tuner System
	Rx	receive
5	S/W	Software
	SCADA	Supervisory Control and Data Acquisition
	SCCP	Signaling Connection Control Part
	SCPC	Single Channel Per Carrier
	SCR	Software Change Request
10	SCS	System Common Software
	SCU	Signaling Channel Unit
	SDD	Software Design Description
	SDID	Seller Data Item Description
	SDLC	Synchronous Data Link Control
15	SDP	Software Development Plan
	SDPAP	Software Development Product Assurance Plan
	SDR	System Design Review
	SDRL	Seller Data Requirements List
	SE	Systems Engineering
20	SEC	Setup Complete Message
	SEDP	Software Engineering Development Plan
	SEE	Software Engineering Environment
	SEEP	Software Engineering Environment Plan
	SID	System Identifier Code
25	SIF	System Integration Facility
	SIT	Special Information Tones
	SLOC	Source Lines of Code
	SLSS	Station Logic and Signaling Subsystem
	SM	Site Manager
30	SMAC	Station Monitor Alarm and Control Subsystem
	SMDS	Satellite Mobile Data Service
	SMP	Software Management Plan
	SMRS	Satellite Mobile Radio Service
	SMSC	Satellite Mobile Switching Center
35	SMTS	Satellite Mobile Telephone Service

	SNA	Systems Network Architecture
	SNAC	Satellite Network Access Controller
	SNACS	Satellite Network Access Controller Subsystem
	SNMP	Simple Network Management Protocol
5	SNR	Signal to Noise Ratio
	SOC	Satellite Operation Center
	SOW	Statement of Work
	SP	Start Pulse
	SPAP	Software Product Assurance Plan
10	SPP	Satellite Protocol Processor
	SQL	Software Query Language
	SRR	Systems Requirements Review
	SRS	Software Requirements Specification
	SS7	Signaling System No. 7
15	SSA	Sloppy Slotted Aloha
	SSTS	Satellite Transmission Systems, Inc.
	STP	Signal Transfer Point
	STP	System Test Program
	STS	System Test Station.
20	STSI	Satellite Transmission Systems, Inc.
	SU	Signaling Unit
	SUES	Shared-Use Earth Station
	SVC	Switched Virtual Circuit
	SVVP	Software Verification and Validation Plan
25	SVVPR	Software Verification and Validation Plan
	Review	
	S/W	Software
	[TI]	Top Level Specification
30	T- 1	Digital Transmission link, 1.544 Mega-bits per second
	TCP/IP	Transmission Control Protocol/Internet Protocol
	TCAP	Transactions Capabilities Application Part
	TCF	Training Check Frame
	TD	Transmission Demonstration
35	TDM	Time Division Multiplex

	TDMA	Time Division Multiple Access
	TDMSI	Time Division Multiplex Selector ID
	TE	Terminal Equipment
	Telecom	Telephonic Communications
5	TDM	Time Division Multiplex
	TDMA	TDM Access
	TID	Terminal Identification
	TIM	Timing
	TIM	Technical Interchange Meeting
10	TIN	Terminal Identification Number
	TIS	Terrestrial Interface Subsystem
	TLCSC	Top Level Computer Software Component
	TLS	Top Level Specification
	TMI	Telesat Mobile Incorporated
15	TMS	Test and Monitor Station
	TNI	Terrestrial Network Interface
	TPP	Test Plan and Procedure
	TT&C	Telemetry, Tracking and Control
	Tx	Transmit
20	UCN	Up CoNverter
	UDS	Unacknowledged Data Delivery Service
	UIS	User Interface Subsystem
	UPC	Uplink Power Control
	UTR	Universal Tone Receiver
25	UW	Unique Words
	V&V	Verification and Validation
	VAC	Value-Added Carrier
	VAX	Model Identification of a Digital Equipment Corporation system
30	VAX	Virtual Address eXtension (proprietary name used by DEC for some of its computer systems)
	VCN	Virtual Circuit Number
	VF	Voice Frequency
	VLR	Visitor Location Register

	VN	Virtual Network
	VPN	Virtual Private Network
	VUP	VAX Unit of Processing
5	V.22bis	Modem Standard for 24()0 Baud Service Over Telephone Lines
	V.25	Procedure for setting up a data connection on the Public Switched Telephone Network
10	V.26, V.28	Electrical specification of interchange circuits at both the Data Terminal Equipment and Data Communications Equipment sides of the interface (similar to RS-232-C)
	V.32	High Speed Serial Link, Physical Layer Definition
15	V.35	X.25 physical layer interface used to access wideband channels (at data rates up to 64kbit/s)
	WAN	Wide Area Network
	XCR	X.25 Configuration Request
20	XICD	External Interface Control Document
	XICWG	External Interface Control Working Group
	X.3	Specification for facilities provided by the Packet Assembler/Disassembler
25	X.21	X.25 physical layer interface for Data Terminal Equipment and Data Communications Equipment using synchronous transmission facilities
	X.21bis	X.25 physical layer interface for Data Terminal Equipment designed for interfacing to synchronous V-series modems to access data networks
30	X.25	Specification for interface between Data Terminal Equipment and Data Communications

Equipment for terminals operating in packet mode

X.28 Specification for interaction between local terminal and Packet Assembler/Disassembler

5 X.29 Specification for interaction between Packet Assembler/Disassembler and remote packet mode terminal

Field No.	Field Name	Description
1	RECORD CODE	This is the type of Call Entry (#F7)
2	ENTRY CODE	<p>This field tells whether the call is local or toll. The value in this field is determined by the TELCO through the datafill of Table TOLLENTC. The DMS-MTX indexes this table based upon the CHARGE CLASS assigned to the call and obtains the associated ENTRY CODE. More information can be found in NTP 411-2131-451, section 029. The following CHARGE CLASSES are used:</p> <ul style="list-style-type: none"> • Local Mobile call - MOBL • Direct dialed Mobile call (1-) - MOB1 • Operator Assisted Mobile call (0+) - MOB0 • Local Land Origination - LLOR
3	OFEATCD	<p>This is the originating feature code. It records whether or not each feature type has occurred during the call. This field is Y or N or each character in the field. Y indicates that the feature assigned to that location occurred during the call. N indicates that the feature did not occur. The feature designated positions are displayed in the following order:</p> <ul style="list-style-type: none"> • Call Forwarding Instigation • Call Forwarding Activation • Call Forwarding Deactivation • Call Forwarding Busy Instigation • Call Forwarding Busy Activation • Call Forwarding Busy Deactivation • Call Forwarding No Answer Instigation • Call Forwarding No Answer Activation • Call Forwarding No Answer Deactivation • Three Way Calling • Call Transfer • Call Waiting • Vertical Feature Flag • Directed Inward Mobile Access • Hotline • Intersystem Handoff • Call Delivery • Automatic Roaming • Follow Me Roaming • Call Delivery Activatable • Surveillance • RF PIN Verification • RF PIN Change Features

TABLE A

Field No.	Field Name	Description
4	TFEATCD	<p>Terminating feature code. It records whether or not each feature type has occurred during the call. This field is Y or N for each character in the field. Y indicates that the feature assigned to that location occurred during the call, N indicates that the feature did not occur. The feature designated positions are displayed in the following order:</p> <ul style="list-style-type: none"> • Call Forwarding Instigation • Call Forwarding Activation • Call Forwarding Deactivation • Call Forwarding Busy Instigation • Call Forwarding Busy Activation • Call Forwarding Busy Deactivation • Call Forwarding No Answer Instigation • Call Forwarding No Answer Activation • Call Forwarding No Answer Deactivation • Three Way Calling • Call Transfer • Call Waiting • Vertical Feature Flag • Directed Inward Mobile Access • Hotline • Intersystem Handoff • Call Delivery • Automatic Roaming • Follow Me Roaming • Call Delivery Activatable • Surveillance • RF PIN Verification • RF PIN Change Features
5	CALLING NUMBER	<p>This field is the calling party's number. It contains a Mobile Identification Number (MIN) for cellular originated calls. When the mobile is registered roamer, this field contains the assigned directory number rather than the MIN.</p>
6	FILLER	
7	CALLING SYSTEM ID	<p>This field is the calling party system identification. If Split Ticket Billing is activated for the originator, the calling system ID in the new CDR is set to the system ID of the MSA that the mobile is in when the new record is started.</p> <p>Note: With the current version of CIS-3, this field can only be filled for subscribers and permanent roamers.</p>

Field No.	Field Name	Description
8	ORIGINATING MSA	This field is the initial calling party MSA, if it is a cellular originated call. Otherwise, it is filled with the background character.
9	ORIGINATING ROAMER INDICATOR	This field is the roamer or home status of the calling party, if it is a mobile originated call. Otherwise, it is filled with the background character. If the field equals 0, the mobile is a permanent subscriber. If the field value is 1, then the subscriber is either a temporary or a mobile denied service. When the value is 2, then the mobile is a permanent roamer. When the value is 3 the mobile is a network roamer.
10	ORIGINATING STATION CLASS MARK	This field is the station classmark as transmitted by the originating mobile. This field consists of the Power Class (1-8) followed by Y or N for Expanded Spectrum and Y or N for Discontinuous Transmission. Note: This field consists of three blanks if the originator is not a mobile.
11	FILLER	
12	ORIGINATING CHANNEL TYPE CAPABILITY	This field is the channel type capability as transmitted by the originating mobile. This field is Y or N for each character in the field. Y indicates that this channel type is available, N indicates that this channel type is not applicable. The channel type designated positions are: <ul style="list-style-type: none"> • Other voice coding • Other DQPSK channels • Digital half rate channels • Digital full rate channels • Analog channels Note: This field will consists of 5 blanks if the originator is not a mobile.
13	ORIGINATING CHANNELS USED	This field consists of the channels used the terminating mobile during a call. This field is Y or N for each character in the field. Y indicates that this channel type is used, N indicates that this channel type is not applicable. The channel type designated positions are: <ul style="list-style-type: none"> • Other voice coding • Other DQPSK channels • Digital half rate channels • Digital full rate channels • Analog channels Note: This field will consists of 5 blanks if the originator is not a mobile.

Field No.	Field Name	Description
14	CALLING SERIAL NO	This field consists of the 2 subfields: manufacturer's code and serial number. The manufacturer's code range is 0 to 255. The calling party mobile unit serial number field is only filled if the S-bit is set to ON. The valid range of this field is 0 to 16777215.
15	FILLER	
16	CREDCARD	This field is the credit card number used by the mobile.
17	DIALED NUMBER	This field is the number dialed by the originator mobile. It is captured with the exact digits dialed. It contains a speed number, MIN, or NPA-NXX-XXXX number. The range of this field is a valid number of up to 32 digits (for international calls).
18	CALLED NUMBER	<p>This field is the called party's number from the mobile. It displays the outpulsed digits for terminated calls, and the EA prefix (10XXX) of an EA call. If the called party is a roamer, it contains a MIN and the DIALED NUMBER field contains its temporary NPA-NXX-XXXX number. If wire terminated, it contains an NPA-NXX-XXXX number. The range of this field is a valid number of up to 24 digits (for international calls).</p> <p>NOTE: although the DIALED NUMBER is always translated, fields 10 to 11 can contain the same information. the prefix 10XXX in EA calls will be shown regardless whether the prefix was dialed or not in addition to showing the outpulsed number to the Access Tandem or the IC. The XXX indicates the chosen carrier.</p>
19	CALLED SYSTEM ID	<p>This field is called party system identification. When Split Ticket Billing is activated for the terminator, the calling system ID in the new CDR is set to the system ID for the MSA that the terminator is in when the new CDR is started.</p> <p>NOTE: with the current version of CIS-3, this field can only be filled for subscribers and permanent roamers.</p>
20	TERMINATING MSA	This field is the initial called party MSA, if it is cellular terminated call. Otherwise, it is filled with the background character.
21	TERMINATING ROAMER INDICATOR	This field is the roam or home status of the called party, it is a mobile terminated call. Otherwise, it is filled with the background character.

Field No.	Field Name	Description
22	TERMINATING STATION CLASS MARK	<p>This field is the station classmark as transmitted by the terminating mobile. This field consists of the Power Class (1-8) followed by Y or N for Expanded Spectrum and Y or N for Discontinuous Transmission.</p> <p>NOTE: This field consists of three blanks if the originator is not a mobile.</p>
23	FILLER	
24	TERMINATING CHANNEL TYPE CAPABILITY	<p>This field is the channel type capability as transmitted by the terminating mobile. This field is Y or N for each character in the field. Y indicates that this channel type is available, N indicates that this channel type is not applicable. The channel type designated positions are:</p> <ul style="list-style-type: none"> • Other voice coding • Other DQPSK channels • Digital half rate channels • Digital full rate channels • Analog channels <p>Note: This field will consist of 5 blanks if the originator is not a mobile.</p>
25	TERMINATING CHANNELS USED	<p>This field consists of the channels used by the terminating mobile during a call. This field is Y or N for each character in the field. Y indicates that this channel type is used, N indicates that this channel type is not applicable. The channel type designated positions are:</p> <ul style="list-style-type: none"> • Other voice coding • Other DQPSK channels • Digital half rate channels • Digital full rate channels • Analog channels <p>Note: This field will consist of 5 blanks if the originator is not a mobile.</p>
26	CALLED SERIAL NO	<p>This field is the called party mobile unit serial number. The field is only filled if the S-bit is set to ON.</p>
27	CALL TYPE	<p>This field is the type of call made. It is determined by the type of trunks on each side of the call. The valid call types are:</p> <ul style="list-style-type: none"> • Mobile-to-Mobile - 0 • Mobile-to-Land - 1 • Mobile-to-Operator - 2 • Land-to-Mobile - 3 • Land - to - Land - 4 • Operator - to - Mobile - 6

Field No.	Field Name	Description
28	BILLING NUMBER	This field is the number of the billed party. It always contains a MIN. The billing party fields are pertinent only to Vertical Services.
29	FILLER	
30	ACCNTCOD	This field is the account code number dialed by the originator.
31	FILLER	
32	AUTHCODE	This field contains the authorization code entered by the subscriber. It will contain a system wide authorization code if one was entered or a station specific one if it was entered and the subscriber has station specific authorization code recording on. field AUTHREC in Table CELLFEAT for the MAC feature. If no authorization code is entered, this field will be blank.
33	FILLER	
34	TREATMENT CODE	<p>This field is the treatment given a call before it is answered. Treatments provided by the DMS-MTX are listed below along with the conditions which cause them to be routed.</p> <p>UNDT (00): UNDEFINED TREATMENT - This field is the default value for entries in Class of Service Screening and Prefix Treatment tables when no treatment is required. The operating company does not supply any input data.</p> <p>NOSC (01): NO SERVICE CIRCUIT - NOSC is applied when a DIMA facility cannot attach a DT receiver to the call. This condition occurs when: 1) a request for a DT receiver is queued, but a wait timeout occurs before a DT receiver becomes available 2) the DT receiver wait queue is full.</p> <p>PDIL (02): PARTIAL DIAL TIMEOUT - PDIL occurs in the following instances: 1) An insufficient number of digits have been received for a call 2) No ST pulse is received on a MF trunk. 3) An invalid digit is collected.</p> <p>PSIG (03): PERMANENT SIGNAL TIMEOUT - This field is the treatment to which a trunk is routed when origination occurs on an incoming or two-way trunk, but no digits are dialed within the period of time specified by the trunk group parameter PSPDSEIZ.</p> <p>VACT (06): VACANT CODE TREATMENT - An unassigned NPA code, office code, or country code is dialed.</p>

Field No.	Field Name	Description
34	TREATMENT CODE (continued)	<p>MSCA (07): MISDIRECTED CAMA CALL - This field is the treatment to which a mobile is routed when making local calls which attempt to switch via the toll network but are not permitted, or when the prefix digits 0 or 1 is dialed in error on a local call.</p> <p>MSLC (08): MISDIRECTED LOCAL CALL - This field is the treatment given in the following cases: 1) For a mobile originating an operator assisted call (0+) to 800 or 555 codes. 2) When prefix digit 0 or 1 is not dialed on a toll call and the prefix treatment table specifies a mandatory prefix digits on toll calls.</p> <p>NBLH (09): NETWORK BLOCKED HEAVY TRAFFIC - This field is the treatment given when the immediate cause of failure is the inability to get a path through the network.</p> <p>NBLN (10): NETWORK BLOCKING NORMAL TRAFFIC - This field is the treatment given when a call is aborted due to blocking (failure to get a channel) in the terminating peripheral module.</p> <p>HNPI (16): HOME NPA INTERCEPT - This field is the treatment to which a mobile or trunk is routed upon dialing home NPA when home NPA dialing is not permitted.</p> <p>BLDN (18): BLANK DIRECTORY NUMBER - This field is the treatment given for unassigned directory numbers.</p> <p>BUSY (19): BUSY LINE - This field is the treatment given in either of the cases: 1) A mobile dials its own directory number 2) A mobile or trunk dials a directory number that is busy.</p> <p>TDND: TOLL DENIED - This field is the treatment to which a mobile is routed when a toll call is attempted by a subscriber who is denied toll access.</p>

Field No.	Field Name	Description
34	TREATMENT CODE (continued)	<p>RODR (25): REORDER - RODR is given in either of the following conditions: 1) More than the maximum number of digits required for a call is outpulsed by an incoming trunk. 2) An unexpected error condition occurs on an outgoing trunk while a call is up. An example of this would be either network integrity loss, invalid A&B bit state received, or force release is ordered from MAP position for a terminating circuit.</p> <p>ORSS (27): ORIGINATING SERVICE SUSPENSION - This is the treatment to which a temporarily - invalid mobile is routed upon originating a call.</p> <p>TESS (28): TERMINATING SERVICE SUSPENSION - This is the treatment to which a call is routed when the terminating mobile is temporarily invalid.</p> <p>DNTR (33):</p> <p>DENIED TERMINATION - This treatment is applied when the 10 over-dialed digits correspond to a Permanent Roamer or Normal Subscriber with the DTM (denied Termination) option.</p> <p>GNCT (58): GENERALIZED NO CIRCUIT - This is the treatment to which a call is routed when no DOD trunk is available for mobile_to_land calls.</p> <p>ANTO (66): ANSWER TIMEOUT - This is the treatment to which the originator is routed when a ringing mobile does not answer within the ringing timeout value.</p> <p>FNAL(68): FEATURE NOT ALLOWED - An attempt to access a vertical feature that is not allocated in Table Cellular to the Mobile ID number, or an attempt has been made to access two different vertical features that cannot coexist from the same control mobile.</p>

Field No.	Field Name	Description
34	TREATMENT CODE (continued)	<p>UMOB (69): UNREGISTERED MOBILE - This is the treatment to which a mobile attempting origination is routed when its MIN does not verify.</p> <p>PGTO (86): MOBILE PAGE TIME OUT - This is the treatment to which an originator is routed when the terminating mobile fails to respond to a page request.</p>
35	FILLER	
36	BILLING SERIAL NO	This is the billing party mobile unit serial number. This field is only filled if the S-bit is set ON. Valid range is 0 to 16777215.
37	EVENT INFO DIGIT	<p>The following information is provided on a per call event basis:</p> <ul style="list-style-type: none"> • YYNNYYNNN - Answer • NYNYNYNYN - Calling Party Disconnect • NYNYNYNYN - Called Party Disconnect • NNNNYYYYN - Blue Box Fraud • NNNNNNNNY - Blocked
38	ORIGINATING INTERSYSTEM BILLING ID	This is the originating intersystem billing ID. This ID is used to associate CDRs for intersystem calls on various switches. The first 5 digits are the switch ID, the next three digits are the switch number, and the final eleven digits are an ID number intended to make the entire billing ID unique.
39	FILLER	
40	TERMINATING INTERSYSTEM BILLING ID	This is the terminating intersystem billing ID. This ID is used to associate CDRs for intersystem calls on various switches. The first five digits are the switch ID, the next three digits are the switch number, and the final eleven digits are an ID number intended to make the entire billing ID unique.
41	FILLER	
42	FIRST ORIGINATING CLI	This is the CLI for the voice trunk that the call began on. All eight fields which indicate the trunks and their members are updated during the call. It is not changed when Split Ticket Billing is activated.

Field No.	Field Name	Description
43	FIRST ORIGINATING MEMBER	This field is the trunk member number for the voice trunk that the call began on. It is not changed when Split Ticket Billing is activated.
44	PREVIOUS ORIGINATING CLLI	This field is the CLLI for the voice trunk that the originator was on before the last handoff was activated and the CDR was reported. IF there are no handoffs on the originating side of the call, the background character is filled. It is not affected by Split Ticket Billing.
45	PREVIOUS ORIGINATING MEMBER	This field is the trunk member number for the voice trunk that the originator was on before the last handoff was activated and the CDR was reported. It is not affected by Split Ticket Billing. If there are no handoffs on the originating side of the call, the background character is filled.
46	LAST ORIGINATING CLLI	This field is the CLLI for the voice trunk that the originator was on when the CDR was reported. It is not affected by Split Ticket Billing.
47	LAST ORIGINATING MEMBER	This field is the trunk member number for the voice trunk that the originator was on when the CDR was reported. It is not affected by Split Ticket Billing.
48	ORIGINATING TIME	For the billing entry of a cellular originator, this is the day of the year and time (hour, minute, second) that a voice channel is allocated for the billing entry of a cellular terminated call, this is the day of the year and the time that the terminating trunk is seized.
49	HANDOFFS	This field is the number of handoffs made during the call. This count begins at 1 and continues to 255. Upon reaching 255 it does not wrap around to 0.
50	FIRST TERMINATING MEMBER	This field is the CLLI for the voice trunk that the terminator was on when the call was answered. Not affected by Split Ticket Billing.
51	FIRST TERMINATING MEMBER	This field is the trunk member number for the voice trunk that the terminator was on when the call was answered. Not affected by Split Ticket Billing.
52	PREVIOUS TERMINATING CLLI	This field is the CLLI for the voice trunk that the terminator was on before the last handoff was activated and the CDR was reported. If there are no handoffs on the terminating side of the call, the background character is filled. Not affected by Split Ticket Billing (STB).

Field No.	Field Name	Description
53	PREVIOUS TERMINATING MEMBER	This field is the trunk member for the voice trunk that the terminator was on before the last handoff was activated and the CDR was reported. If there are no handoffs on the terminating side of the call, the background character is filled. Not affected by Split Ticket Billing.
54	LAST TERMINATING CLLI	This field is the CLLI for the voice trunk that the terminator was on the CDR was reported. Not affected by Split Ticket Billing.
55	LAST TERMINATING MEMBER	This field is the trunk member number for the voice trunk that the terminator was on when the CDR was reported. Not affected by Split Ticket Billing.
56	DISCONNECT TIME	This field is the day of the year and time that a on-hook is detected on either end of the call.
57	SERVING TRANSLATION SCHEME	This field is the number of the translation scheme applied to the dialed number.
58	CALL DURATION	This is the connection duration of the call in seconds. For a normally completed call (completion code 00), this is the time duration between off-hook detection on the terminating mobile or line and on-hook at either end of the call (conversation time). Upon reaching 999999, it does not wrap around to zero.
59	INFO DIGITS	<p>The following events are observed during the call; information is provided on a per call event basis:</p> <ul style="list-style-type: none"> • 1 N Y N Y N Y N Y Service Observed ? • 1 N N Y Y N N Y Y Charge? • 1 N N N N Y Y Y Y Traffic Sampled ? • 2 N Y N Y N Y N Y ANI fail? • 2 N N Y Y N N Y Y Operator Dialed ? • 2 N N N N Y Y Y Y Operator Identified? <p>NOTE: This field is not yet implemented.</p>
60	ORIG HOLD	This is the total amount of time, in seconds, on hold by the originator.
61	IX (CARRIER)	This is the equal access toll carrier.
62	TERM HOLD	This is the total amount of time, in seconds, on hold by the terminator.

Field No.	Field Name	Description
63	COMPLETION CODE	<p>This the manner in which a call is terminated.</p> <p>NOTE : Completion code values other than 00 indicate abnormal call completions. For value 4 (RF Signal Lost), the call duration indicates the time span between answer and signal lost detection by the DMS-MTX. Values 5 and 6 indicate billable calls, but the call duration field can not indicate the full conversation time. For these codes, the call duration can be calculated as the difference between the disconnect and the origination times.</p> <p><u>Code</u> <u>Meaning</u></p> <p>00 NORMAL CALL - The call is completed after a on-hook is detected at either side of the call.</p> <p>01 TREATMENT SET - The call is not completed as intended by the calling party. Instead it is routed to a treatment. The exact treatment set can be determined from the TREATMENT CODE.</p> <p>02 CALL ABANDON - An on-hook by the originating party is detected before the call is completely routed.</p> <p>03 ABNORMAL CALL - This field is the default completion code given to an abnormally completed call. This results only if the cause of the termination is specifically determined.</p> <p>04 RF SIGNAL LOST - A mobile unit failure message is received from a (CSC) while call processing is waiting for SAT.</p> <p>05 MOBILE UNIT FAILURE - A mobile unit failure message is received from a CSC while call processing is in any state other than waiting for SAT. Note: The RF SIGNAL LOST is a special case of a mobile unit failure.</p> <p>06 CELL SITE FAILURE - AS cell site failure message is received from a CSC.</p> <p>10 HANDOFF OCCURRED - The CDR record was split due to a handoff.</p>
64	OEXTSYS	This is the amount of time the originator is not in the first reporting system.

Field No.	Field Name	Description
65	ANSWER TYPE	<p>This field displays the manner in which a call is answered. The following answer types are valid:</p> <p><u>Code</u> <u>Meaning</u></p> <p>01 ANSWER DETECT NO VOICE - The ATD has detected an answer, but an identifiable signal has not been present for 7.2 seconds or longer.</p> <p>02 ANSWER DETECT VOICE - The ATD has detected a pattern of signals not classifiable as call progress tones.</p>
65	ANSWER TYPE (CONTINUE)	<p><u>Code</u> <u>Meaning</u></p> <p>03 RING BACK SOFTWARE DETECT - The ATD has counted the default number of audible rings.</p> <p>04 HARDWARE ANSWER - The conventional off-hook signal has been detected on a line or trunk.</p> <p>05 ATD HIGH DRY TIMEOUT - The ATD has not detected a constant tone of 60 ms within the default timeout limit.</p> <p>07 ATD NO CMS BIT TRANSITION - The end-of-outpulsing has not been detected within a 20-second wait period.</p> <p>08 BUSY SOFTWARE DETECT - The ATD has counted 4 signals identified as a busy call process tone.</p> <p>09 REORDER SOFTWARE DETECT - The ATD has counted eight signals identified as a reorder call progress tone.</p>
66	TEXTSYS	This field is the amount of time the terminator is not in the first system.
67	SPARE	

What is claimed is:

1. In a mobile satellite system including a satellite communication switching office having a satellite antenna for receiving/transmitting a satellite message via a satellite from/to a vehicle
5 using a mobile communication system, a central controller receiving/transmitting the satellite message from/to the satellite communication switching office issued from the vehicle via the satellite, a method of providing satellite communication and satellite
10 management for multiple users in a virtual network arrangement, said method comprising the steps of:
 - (a) first and second mobile earth terminals (METs) registering with the mobile satellite system;
 - (b) the first MET selecting a virtual network
15 identifier (VN ID) representing a virtual network group including at least the first and second METs to establish voice communication therewith;
 - (c) the first MET transmitting the VN ID to the central controller;
 - 20 (d) the central controller receiving the VN ID, allocating a frequency for the virtual network group, and broadcasting the message to the virtual network group including the second MET informing the virtual network group of the allocated frequency and the voice
25 communication associated therewith;
 - (e) the second MET tuning to the frequency in response to the message broadcast by the central controller; and
 - (f) the first and second METs communicating with
30 each other on the frequency.

2. The method according to claim 1, further comprising the steps of:

(1) a third MET included in the virtual network group registering with the mobile satellite system;

5 (2) the central controller broadcasting the message to the virtual network group including the third MET informing the virtual network group of the allocated frequency and the voice communication associated therewith; and

10 (3) the third MET tuning to the allocated frequency for the virtual network group to gain access thereto and communicate with the first and second METs.

3. The method according to claim 1, wherein the central controller controls the satellite communication of the virtual network arrangement including virtual network parameters used by the first and second METs.

4. The method according to claim 1, wherein the central controller collects billing information regarding the satellite communication and transmits the billing information to the mobile satellite system, and
5 wherein the mobile satellite system charges a service fee to a customer that has requested the virtual network arrangement.

5. The method according to claim 1, further comprising the steps of:

(1) a non-MET accessing the mobile satellite system via one of a public switched telephone network
5 and a cellular network to initiate a communication with the virtual network group including at least one of the first and second METs;

(2) the central controller broadcasting the message to the virtual network group informing the
10 virtual network group of the allocated frequency and the voice communication associated therewith; and

(3) the at least one of the first and second METs tuning to the frequency in response to the message broadcast by the central controller to communicate with the non-MET in the virtual network arrangement.

6. The method according to claim 1, further comprising the steps of:

(1) the first MET selecting the virtual network identifier (VN ID) representing the virtual network group including the first MET and a non-MET serviced by one of a public switched telephone network and a cellular network to establish voice communication therewith;

(2) the first MET transmitting the VN ID to the central controller;

(3) the central controller receiving the VN ID, determining that the virtual network group includes the non-MET, and broadcasting a non-MET message to the one of the public switched telephone network and the cellular network including the voice communication associated therewith; and

(4) the one of the public switched telephone network and the cellular network receiving the non-MET message from the central controller and transmitting the non-MET message to the non-MET to establish the virtual network arrangement between the MET and the non-MET.

7. In a mobile satellite system including a satellite communication switching office having a satellite antenna for receiving/transmitting a satellite message via a satellite from/to a vehicle using a mobile communication system, a central controller receiving/transmitting the satellite message from/to the satellite communication switching office issued from the vehicle via the satellite, a system for

providing satellite communication between multiple
10 users in a virtual network arrangement, comprising:
first and second mobile earth terminals (METs)
responsively connected to and registering with the
mobile satellite system, the first MET selecting a
virtual network identifier (VN ID) representing a
15 virtual network group including the first and second
METs to establish voice communication therewith and
transmitting the VN ID; and
a central controller responsively connected to the
first and second METs, the central controller receiving
20 the VN ID from the first MET, validating the first MET
for communication, validating the VN ID, allocating a
frequency for the virtual network group, and
broadcasting the message to the virtual network group
including the second MET informing the virtual network
25 group of the allocated frequency and the voice
communication associated therewith, the second MET
tuning to the frequency in response to the message
broadcast by the central controller, and the central
controller assigning the first MET as current speaker
30 for the virtual network group.

8. The system according to claim 7, wherein the
central controller controls the satellite communication
including virtual network parameters used by the first
and second METs.

9. The system according to claim 7, wherein the
central controller collects billing information
regarding the satellite communication and transmits the
billing information to the mobile satellite system, and
5 wherein the mobile satellite system charges a service
fee to a customer that has requested the virtual
network arrangement.

10. The system according to claim 7, wherein
a non-MET accesses the mobile satellite system via
one of a public switched telephone network and a
cellular network to initiate a communication with the
5 virtual network group including at least one of the
first and second METs,

the central controller broadcasts the message to
the virtual network group informing the virtual network
group of the allocated frequency and the voice
10 communication associated therewith, and

the at least one of the first and second METs tunes
to the frequency in response to the message broadcast
by the central controller to communicate with the non-
MET in the virtual network arrangement.

11. The system according to claim 7, wherein
the first MET selects the virtual network
identifier (VN ID) representing the virtual network
group including the first MET and a non-MET serviced by
5 one of a public switched telephone network and a
cellular network to establish voice communication
therewith, and transmits the VN ID to the central
controller,

the central controller receives the VN ID,
10 determines that the virtual network group includes the
non-MET, and broadcasts a non-MET message to the one of
the public switched telephone network and the cellular
network including the voice communication associated
therewith, and

15 the one of the public switched telephone network
and the cellular network receives the non-MET message
from the central controller and transmits the non-MET
message to the non-MET to establish the virtual network
arrangement between the MET and the non-MET.

12. The system according to claim 7, further comprising a third MET responsively connected to said central controller and included in the virtual network group registering with the mobile satellite system, and
5 wherein

the central controller broadcasts the message to the virtual network group including the third MET informing the virtual network group of the allocated frequency and the voice communication associated
10 therewith,

the third MET generating a scrambling vector for access to the voice communication, and tuning to the allocated frequency for the virtual network group using the scrambling vector to gain access thereto.

13. A satellite network system comprising:

a satellite antenna for receiving and transmitting messages via a satellite and satellite beams to and from feederlink earth stations (FESs) connected to at
5 least one land line communications network and mobile earth terminals (METs) of a mobile communication system;

a satellite communication switching office connected to said antenna and coupled through a
10 satellite interface system to a central controller; and

a network operations center (NOC) for managing and controlling resources of the satellite network system, the NOC communicating with various internal and external entities via a control network, said NOC
15 comprising:

data management means for transmission and receipt of information with other components of the network operations center, said data management means including a NOC data base;

20 configuration management means for allocating system resources;

network management means for updating network functions;

25 call records management means for enabling monitoring of customer usage;

event management means for detecting fault conditions; and

operator interface means for transmitting system information to an operator station.

5 14. In a mobile satellite system including a satellite communication switching office and network system having a satellite antenna for receiving and transmitting a satellite message via a satellite and satellite beams to and from feederlink earth stations (FESs) and mobile earth terminals (METs) using a mobile communication system, a satellite interface system, a central controller receiving and transmitting the satellite message to and from the satellite
10 communication switching office, the mobile satellite system being responsively connected to said mobile communication system and comprising:

15 a network operations center (NOC) managing and controlling the resources of the satellite network system and carrying out the administrative functions associated with the management of the network system, the NOC communicating with various internal and external entities via a control network;

20 a first network communications controller (NCC) managing the real time allocation of circuits between METs and FESs for the purposes of supporting communications, available circuits being held in circuit pools managed by group controllers (GCs) within the NCC, the NCC communicating with the NOC via a
25 satellite network internetwork, with FESs via Ku-to-Ku band interstation signaling channels or terrestrial

links, and with METs via Ku-to-L band signaling channels;

30 a FES supporting communications links between METs, the public switched telephone network (PSTN), private networks, and other METs, call completion and service feature management being accomplished via in-band signaling over the communication channel following the establishment of such a channel, the FES including a
35 gateway FES providing mobile telephone service (MTS) and mobile telephone cellular roaming service (MTCRS) services, and a base FES providing mobile radio service (MRS) and net radio (NR) services; and

40 a group controller subsystem (GCS) incorporating one or multiple group controllers (GC), each GC maintaining state machines for every call in progress within its control group and allocating and de-allocating circuits for FES-MET calls within each beam of the system, managing virtual network call
45 processing, MET authentication, and providing elements of call accounting, the GC providing satellite bandwidth resources to the NOC for AMS(R)S resource provisioning and monitoring the performance of call processing and satellite circuit pool utilization, and
50 performing MET management, commissioning and periodic performance verification testing and database management.

15. In a mobile satellite system including a satellite communication switching office (SCSO) having a satellite antenna for receiving/transmitting a satellite message via a satellite from/to a mobile
5 communication system (MCS), a central controller receiving/transmitting the satellite message from/to the satellite communication switching office issued from the MCS via the satellite to another party, a method of performing a call setup procedure in the

- 10 mobile satellite system from a call initiated by a
destination served by a public switched telephone
network (PSTN) to the MCS, said method comprising the
steps of:
- 15 (a) receiving by the SCSO a call from the
destination served by the PSTN;
- (b) transmitting by the SCSO to the central
controller a channel request including a destination
number;
- 20 (c) determining by the central controller an
identity of the MCS responsive to the destination
number, and transmitting a call announcement;
- (d) acknowledging by the MCS the call announcement
to the central controller;
- 25 (e) transmitting frequency assignments to the MCS
and to the SCSO, the frequency assignment including the
call type, and the destination phone number, and a
security field used to verify the MCS's identity;
- (f) receiving by the MCS the frequency assignment,
and transmitting an identification message to the SCSO;
- 30 (g) verifying by the SCSO the identity of the MET
responsive to the identification message;
- (h) upon successful verification in said verifying
step (g), transmitting by the SCSO a ring command to
the MCS;
- 35 (i) receiving by the MCS of the ring command,
generating a ringing signal to a MET user, and
transmitting a ring command acknowledgement to the
SCSO; (j) receiving by the SCSO the ring command
acknowledgement from the MCS;
- 40 (k) once the call setup is complete and the MET
user has acknowledged the ringing signal by going off-
hook, transmitting by the MCS a disable signal to the
SCSO and disabling voice activation in the MCS for a
predetermined period of time;

45 (1) upon detection of the MCS switching to a voice mode, switching by the SCSO to the voice mode, and re-enabling voice activation by the MCS; and

 (m) establishing voice communication between the PSTN and the MCS.

 16. In a mobile satellite system including a satellite communication switching office (SCSO) having a satellite antenna for receiving/transmitting a satellite message via a satellite from/to a mobile communication system (MCS), a central controller receiving/transmitting the satellite message from/to the satellite communication switching office issued from the MCS via the satellite to another party, a method of performing a call setup procedure in the mobile satellite system from a call initiated by the MCS to a destination served by a public switched telephone network (PSTN), said method comprising the steps of:

- (a) initiating the call by the MCS;
- 15 (b) the MCS formatting and transmitting an access request message including call type and destination number;
- (c) receiving by the central controller the access request message, and transmitting frequency assignments to the MCS and to the SCSO, the frequency assignment including the call type, and the destination phone number, and a security field used to verify the MCS's identity;
- 20 (d) receiving by the MCS the frequency assignment, and transmitting an identification message to the SCSO;
- 25 (e) verifying by the SCSO the identity of the MET responsive to the identification message;

30 (f) upon successful verification in said verifying step (e), switching by the SCSO and the MCS from call setup mode to voice mode;

(g) transmitting by the SCSO a disable signal to the MCS to disable voice activation in the MCS for a predetermined time period after which voice activation is re-enabled in the MCS, and transmitting a
35 destination number to the PSTN; and

(h) establishing voice communication between the PSTN and the MCS.

AMENDED CLAIMS

[received by the International Bureau on 9 May 1997 (09.05.97);
new claims 17-20 added; remaining claims unchanged (5 pages)]

17. In a mobile communication system including a communication switching office for receiving/transmitting a message, a central controller receiving/transmitting the message from/to the communication switching office, a method of providing communication and management for multiple users in a virtual network arrangement, said method comprising the steps of:

(a) first and second mobile earth terminals (METs) registering with the mobile communication system;

(b) the first MET selecting a virtual network identifier (VN ID) representing a virtual network group including at least the first and second METs to establish voice communication therewith;

(c) the first MET transmitting the VN ID to the central controller;

(d) the central controller receiving the VN ID, allocating a frequency for the virtual network group, and broadcasting the message to the virtual network group including the second MET informing the virtual network group of the allocated frequency and the voice communication associated therewith;

(e) the second MET tuning to the frequency in response to the message broadcast by the central controller; and

(f) the first and second METs communicating with each other on the frequency.

18. A network system comprising:

an antenna for receiving and transmitting messages to and from mobile earth terminals (METs) of a mobile communication system;

5 a communication switching office connected to said antenna and coupled through an interface system to a central controller; and

a network operations center (NOC) for managing and controlling resources of the network system, the NOC communicating with various entities via a control network, said
10 NOC comprising:

data management means for transmission and receipt of information with other components of the network operations center, said data management means including a NOC data base;

15 configuration management means for allocating system resources;

network management means for updating network functions; call records management means for enabling monitoring of customer usage;

20 event management means for detecting fault conditions; and operator interface means for transmitting system information to an operator station.

19. In a mobile communication system including a communication switching office for receiving/transmitting a message, a central controller receiving/transmitting the message from/to the communication switching office, the mobile

5 communication system comprising:

a network operations center (NOC) managing and controlling the resources of the mobile communication system and carrying out the administrative functions associated with the management of same, the NOC communicating with various internal and external
10 entities via a control network;

a first network communications controller (NCC) managing the real time allocation of circuits for the purposes of supporting communications, available circuits being held in circuit pools managed by group controllers (GCs) within the NCC;

15 a FES supporting communications links between at least one of mobile earth terminals (METs), the public switched telephone network (PSTN), private networks, and other METs, and providing call completion and service feature management, the FES including a gateway FES providing access to at least one of mobile
20 telephone service (MTS) and mobile telephone cellular roaming service (MTCRS) services, and a base FES providing mobile radio service (MRS) and net radio (NR) services; and

a group controller subsystem (GCS) incorporating one or multiple group controllers (GC), each GC at least one of
25 maintaining controlling calls in progress within its control


group and allocating and de-allocating circuits, managing virtual network call processing, MET authentication, and providing elements of call accounting, monitoring the performance of call processing and circuit pool utilization, performing MET
30 management, commissioning, periodic performance verification testing and database management.

20. A method of performing a call setup procedure in a mobile satellite system from a call initiated by a mobile communication system (MCS) to a destination served by a public switched telephone network (PSTN), said method comprising the
5 steps of:

- (a) initiating a call by the MCS;
- (b) receiving by the central controller the call, and transmitting frequency assignments to the MCS and to a satellite communication switching office (SCSO);
- 10 (c) receiving by the MCS the frequency assignment, and transmitting an identification message to the SCSO;
- (d) verifying by the SCSO the identity of the MET responsive to the identification message;
- (e) upon successful verification in said verifying step
15 (d), switching by the SCSO and the MCS from call setup mode to voice mode;
- (f) transmitting by the SCSO a disable signal to the MCS to disable voice activation in the MCS for a predetermined time

period after which voice activation is re-enabled in the MCS, and
20 transmitting a destination number to the PSTN; and

(g) establishing voice communication between the PSTN and
the MCS.



PARAMETER	REQUIREMENT
L-BAND AEIRP	56.6 dBW AT NOISE POWER RATIO OF 18 dB
Ku-BAND AEIRP	36.7 dBW
L-BAND RECEIVE G/T	+2.7 dB/K
Ku-BAND RECEIVE G/T	-3.6 dB/K
L-BAND FREQUENCIES	1530 TO 1559 MHz (TRANSMIT) 1631.5 TO 1660.5 MHz (RECEIVE)
Ku-BAND FREQUENCIES	10,750 - 10,950 MHz (CENTRAL SATELLITE TRANSMIT) 13,000 - 13,150 MHz & 13,200 - 13,250 MHz (CENTRAL SATELLITE RECEIVE) 11,700 - 11,900 MHz (WING SATELLITE TRANSMIT) 14,000 - 14,200 MHz (WING SATELLITE RECEIVE)

FIG. 2





FIG. 3

**FIG. 4**




FIG. 5




FIG. 6




FIG. 7

8/28




FIG. 8a

9/28




FIG. 8b

10/28




FIG. 9a

11/28




FIG. 9b




FIG. 10

13/28





FIG. 11A

14/28



15/28




FIG. 11C

16/28




FIG. 12




FIG. 13

18/28




FIG. 14

19/28




FIG. 15

20/28




FIG. 16




FIG. 17

22/28




FIG. 18




FIG. 19




FIG. 20





FIG. 21

**EXAMPLE:**

- AN ORGANIZATION
- THEY HAVE 3,300 METs AND 125 DIFFERENT COMMUNICATION NETS
- THEY HAVE 4 BASE FESs ACROSS CANADA
- A VIRTUAL NETWORK IS ASSIGNED TO THE ORGANIZATION

VIRTUAL NETWORK DATABASE**MET FILES**

MET 1 {DN, TN, ETC.}

MET 2 {DN, TN, ETC.}

TO

MET 3300 {DN, TN, ETC.}

(DN=DIRECTORY NUMBER)

VN ID FILES

VN ID 1 {#, ... ETC.}

VN ID 2 {#, ... ETC.}

TO

VN ID 125 {#, ... ETC.}

FIG. 22




FIG. 23




FIG. 24

INTERNATIONAL SEARCH REPORT

International application No.
PCT/US96/19120

A. CLASSIFICATION OF SUBJECT MATTER

IPC(6) :H01Q 11/12

US CL :455/121

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

U.S. : 455/121

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched
NONEElectronic data base consulted during the international search (name of data base and, where practicable, search terms used)
NONE

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A, E	US 5,590,395 A (DIEKELMAN) 31 DECEMBER 1996, see abstract and FIG. 1	1-16
A, E	us 5,594,740 A (LADUE) 14 JANUARY 1997, see Abstract and FIG. 1	1-16
A,E	US 5,586,165 A (WIEDEMAN) 17 DECEMBER 1996, see Abstract	1-16
A,E	US 5,594,780 A (WIEDEMAN ET AL.) 14 JANUARY 1997, see FIG. 1	1-16
A,P	US 5,526,404 A (WIEDEMAN ET AL.) 11 JUNE 1996, see Abstract	1-16

☐

Further documents are listed in the continuation of Box C.

☐

See patent family annex.

* Special categories of cited documents:	* T later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
* A document defining the general state of the art which is not considered to be of particular relevance	* X document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
* E earlier document published on or after the international filing date	* Y document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art
* L document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)	* G document member of the same patent family
* O document referring to an oral disclosure, use, exhibition or other means	
* P document published prior to the international filing date but later than the priority date claimed	

Date of the actual completion of the international search

15 FEBRUARY 1997

Date of mailing of the international search report

10 MAR 1997

Name and mailing address of the ISA/US
Commissioner of Patents and Trademarks
Box PCT
Washington, D.C. 20231

Facsimile No. (703) 305-3230

Authorized officer

MARSHA D. BANKS-HAROLD

Telephone No. (703) 305-4700